

Cluster ID	Cluster Name	Description
0x005E	Microwave Oven Mode	Modes associated with a Microwave Oven
0x005F	Microwave Oven Control	Commands and attributes for controlling a Microwave Oven
Oven Clusters		
0x0048	Oven Operational State	Operational states and phases associated with an Oven
0x0049	Oven Mode	Modes associated with an Oven
Refrigerator Clusters		
0x0052	Refrigerator And Temperature Controlled Cabinet Mode	Commands and attributes for controlling a refrigerator or a temperature controlled cabinet
0x0057	Refrigerator Alarm	Alarm definitions for Refrigerator devices

8.2. Temperature Control Cluster

This cluster provides an interface to the setpoint temperature on devices such as washers, refrigerators, and water heaters. The setpoint temperature is the temperature to which a device using this cluster would attempt to control to. This cluster does not provide access to the actual or physical temperature associated with any device using this cluster. Access to the physical temperature associated with a device using this cluster would be provided by other clusters as part of that device's device type definition.

The values and constraints of the attributes communicated to clients SHOULD match the controls on any physical interface on a device implementing this server. For example, the value of the Step attribute SHOULD match the incremental value by which the temperature setpoint can be changed on the physical device.

8.2.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.

Revision	Description
1	Initial revision

8.2.2. Classification

Hierarchy	Role	Scope	PICS Code
Base	Application	Endpoint	TCTL