

ID	Name
0x0099	Energy EVSE

9.3.4. Features

This cluster SHALL support the FeatureMap bitmap attribute as defined below.

Bit	Code	Feature	Conformance	Summary
0	PREF	ChargingPreferences	M	EVSE supports storing user charging preferences
1	SOC	SoCReporting	O	EVSE supports reporting of vehicle State of Charge (SoC)
2	PNC	PlugAndCharge	O	EVSE supports PLC to support Plug and Charge
3	RFID	RFID	O	EVSE is fitted with an RFID reader
4	V2X	V2X	O	EVSE supports bi-directional charging / discharging

9.3.4.1. ChargingPreferences Feature

Since some EVSEs cannot obtain the SoC from the vehicle, some EV charging solutions allow the consumer to specify a daily charging target (for adding energy to the EV's battery). This feature allows the consumer to specify how many miles or km of additional range they need for their typical daily commute. This range requirement can be converted into a daily energy demand with a target charging completion time.

The EVSE itself can use this information (or may allow a controller such as an EMS) to compute an optimized charging schedule. For example, an optimizer may be able to use the [Commodity Price](#) cluster to determine the cheapest and lowest GHG based charging schedule for the vehicle.

An EVSE device which includes a Device Energy Management device with the Device Energy Management cluster **PFR** (PowerForecastReporting) feature can use the charging preferences information to produce its power forecast.

EVSE devices that support the Device Energy Management cluster's **FA** feature can have their charging profiles set by a controller device such as an EMS. For example, if the EVSE advertises a simple power forecast which allows the EMS to adjust over a wide range of power and time durations, then the EVSE may allow the EMS to propose a revised optimized forecast (which is the charging profile). For example, a solar PV ESA may also share its Forecast, so enabling an EMS to adjust the EVSE forecast to the best time to charge so that any excess solar generation is used to charge the EV.