

9.3.9.8. ClearTargets Command

Allows a client to clear all stored charging targets.

9.3.9.8.1. Effect on Receipt

On receipt of this command, all weekly targets that are currently stored SHALL be cleared and a default response of SUCCESS SHALL be sent in response. There are no error responses to this command.

If the EVSE is currently charging based on being in automatic mode, then it SHALL stop the EVSE charging.

9.3.10. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	EVConnected	INFO		V	M
0x01	EVNotDetected	INFO		V	M
0x02	EnergyTransferStarted	INFO		V	M
0x03	EnergyTransferStopped	INFO		V	M
0x04	Fault	CRITICAL		V	M
0x05	RFID	INFO		V	[RFID]

9.3.10.1. EVConnected Event

This event SHALL be generated when the EV is plugged in.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	SessionID	uint32	all			M

9.3.10.1.1. SessionID Field

This is the new session ID created after the vehicle is plugged in.

9.3.10.2. EVNotDetected Event

This event SHALL be generated when the EV is unplugged or not detected (having been previously plugged in). When the vehicle is unplugged then the session is ended.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	SessionID	uint32	all			M