

	<pre> { "band": "fm", "number": 87500, "hd_program": 0 "text": "BBC1" }, ... { "band": "unknown", "number": 0, "hd_program": 0 }], "func_list": ["clear", "move"] } </pre>
--	---

6.2. getPlayInfo

For retrieving playback information of Tuner

Request Parameters

URI	<BaseURL>/v1/tuner/getPlayInfo
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/tuner/getPlayInfo

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details
band	string	Returns current Band Values: "am" / "fm" / "dab"
auto_scan	boolean	Returns Auto Scan (Up or Down) status
auto_preset	boolean	Returns Auto Preset execution status
am	object	Returns AM related information
- preset	integer	Returns current preset number. 0 when there's no presets Values: 0 (no presets), or one in the range gotten via /system/getFeatures
- freq	integer	Returns frequency (unit in kHz)
- tuned	boolean	Returns Tuned status
fm	object	Returns FM related information
- preset	integer	Returns current preset number. 0 when there's no presets Values: 0 (no presets), or one in the range gotten via /system/getFeatures
- freq	integer	Returns frequency (unit in kHz).
- tuned	boolean	Returns Tuned status
- audio_mode	string	Returns Audio Mode Values: "mono" / "stereo"
rds	object	Returns RDS information. Available only when RDS is valid