



9.1.4. Adding a client to the Group

Here shows how to add DeviceC to the Group.

1. Setup GroupID and target Zone of the adding client(s) by “setClientInfo”.

Request (URI)

`http://{Device C}/ YamahaExtendedControl/v1/dist/setClientInfo`

Request (json)

```
{
  "group_id": "9A237BF5AB80ED3C7251DFF49825CA42",
  "zone": [
    "main"
  ]
}
```

Response

```
{
  "response_code": 0
}
```

2. Setup the master with GroupID and adding client list by “setServerInfo (add)”.

Request (URI)

`http://{Device B}/ YamahaExtendedControl/v1/dist/setServerInfo`

Request (json)

```
{
  "group_id": "9A237BF5AB80ED3C7251DFF49825CA42",
  "zone": "main",
  "type": "add",
  "client_list": [
    "192.168.0.6" ← Device C IP address
  ]
}
```

Response

```
{
  "response_code": 0
}
```