```
        "reasons":[
          "unknown"
        ]
      }
    ]
    "audio_dropout":false,
  }
```

When group_id isn't 00000000000000000000000000000000 and client_list isn't empty, process "role" is "server" , not "none".

9.3. Stereo Pair

Establish Stereo Pair setting by operating Devices. Stereo Pair setting is established as following.

Comfirm Stereo Pair status.

Request

http://{DeviceA}/ YamahaExtendedControl/v1/system/getStereoPairInfo

Response

```
{
      "response_code":0,
      "status":"master_left",
      "pair_info":{
        "alive":true,
        "ip_address":"192.168.0.11",
        "mac_address":"00A0DE012345"
      }
}
```

Request

http://{DeviceB}/ YamahaExtendedControl/v1/system/getStereoPairInfo

Response

```
{
      "response_code":0,
      "status":"slave_right",
      "pair_info":{
        "alive":true,
        "ip_address":"192.168.0.10",
        "mac_address":"00A0DE012346"
      }
}
```