



NANO SERIES **DIGITAL** **PANEL METER**

Our ET2111 Series is basic 1Ph volt meter which is the simple slimmest, robust solution for advanced voltage measurement.

CLASS 1.0

1 PH VOLT METER

TRUE RMS

LOGGING ENABLED

FEATURES

- Single row display, Displays for L-N voltage.
- A single 3 Element Meter caters to 2 Wire.
- Field programmable.
- Automatic scaling for Kilo or Mega units. Automatic placement of decimal point.
- Unrestricted range of user programmable CT and PT ratios from the front panel of the meter.
- Unique service support over-the-counter free replacement within warranty.

PARAMETERS DISPLAYED

Model	V(1Ph)	Remarks
ET 2111	●	Single row display

TECHNICAL PARTICULARS

● Configuration	1 Phase, 1 Element; 2 Wire (Note Order code)
● Input V Nominal	230 V LT or 110 V through PT (line to line)
● Range	50% to 120% of Nominal
● Computation	True RMS for all Voltages
● Accuracy	Class 1.0 IEC 62053-21
● Display	Displays of 4 digit, 12.5 mm, 7 segment, super-bright LEDs
● Isolation	2000 V AC for one minute
● Safety	Measurement Category III, Pollution Degree 2 as per EN61010-1 First Edition
● Volts	Auto scaling depending on input
● Aux Supply	85 - 270 V AC or DC
● Burden	0.1 VA typical per Voltage
● Ambient	Temp. 0-50 deg C, RH < 95% non-condensing

OFFERED SPECIFICATION

• Weight	~ 300 gm
• Dimensions	96 x 96 mm (Bezel), x 28 mm
• Panel Cutout	(90+1-0) mm x (90+1-0) mm
• Mounting	Panel Mount with Slide & Lock clamp
• Warranty	12 months from date of sale

Note: * Ordering option,
Type test carried at "Electrical Research and Development Association" Vadodara India.
Reports are available on request.



118,000+
Telecom Towers



700+
Solar Sites



15+ Global
MNO/Tower CO



26+
Countries



500,000+
Connected Assets



20,000+
Enterprise Users

DIN EN ISO 9001:2015

Get in touch :



sales@invendis.com



www.invendis.com



No. 230, 1st Cross, 38th Main, BOOHBCS Layout,
BTM 2nd Stage, Bangalore – 560 068

Invendis
Invent, Discover.

**SCAN FOR
MORE DETAILS**

