



LITE SERIES DIGITAL PANEL METER

Our ET2071 Series is basic 3Ph Volts, Amps & Frequency meter with built in selector switch are the simple, robust solution for advanced Phase to Phase, Phase to Neutral & unbalanced voltage, 3 Ph current & Supply frequency measurement.

CLASS 1.0

VAF METER

TRUE RMS

LOGGING ENABLED

FEATURES

- 3 simultaneous display of 3 row, 3 digit super bright display, Displays for both L-L and L-N voltages, Voltage UB, Phase wise currents, IUB Frequency(Hz).
- A single 3 Element Meter caters to 3 Wire or 4 Wire.
- Field programmable on primary and secondary.
- Automatic scaling for Kilo or Mega units. Automatic placement of decimal point.
- Unrestricted range of user programmable CT and PT ratios from the front panel of the meter.
- Unique service support over-the-counter free replacement within warranty.

PARAMETERS DISPLAYED

Model	V	A	Hz	Remarks
ET 2071	●	●	●	Three row display

TECHNICAL PARTICULARS

- Configuration
- Input V Nominal
 - Range
- Computation
- Accuracy
- Display
- Isolation
- Safety
- Aux Supply
- Burden

OFFERED SPECIFICATION

- 1/3 Phase, 3 Element; 3 / 4 Wire
- 415 V LT or 110 V through PT (line to line)
- 50% to 120% of Nominal
- True RMS
- Class 1.0 IEC 62053-21
 - ± (0.5% of FS + 0.5% of Rdg + 1 digit)
 - ± 1.0% of FS for Current
 - ± 0.2% for Frequency
- Displays of 3 digit, 12.5 mm, 7 segment, super-bright LEDs
- 2000 V AC for one minute
- Measurement Category III, Pollution Degree 2 as per EN61010-1 First Edition
- 85 - 270 V AC or DC
- 0.1 VA typical per Voltage

• Ambient	Temp. 0-50 deg C, RH < 95% non-condensing
• Weight	~ 400 gm
• Dimensions	96 x 96 mm (Bezel), x 28 mm
• Panel Cutout	(90+1-0) mm x (90+1-0) mm
• Mounting	Panel Mount with Slide & Lock clamp
• Warranty	12 months from date of sale

Note: * Ordering option,
Type test carried at "Electrical Research and Development Association" Vadodara India.
Reports are available on request.



118,000+
Telecom Towers



700+
Solar Sites



15+ Global
MNO/Tower CO



26+
Countries



500,000+
Connected Assets



20,000+
Enterprise Users

DIN EN ISO 9001:2015

Get in touch :



sales@invendis.com



www.invendis.com



No. 230, 1st Cross, 38th Main, BOOHBCS Layout,
BTM 2nd Stage, Bangalore – 560 068

Invendis
Invent, Discover.

**SCAN FOR
MORE DETAILS**

