Polyphony v1 — quick install

v3.26 + p1

andrewdesena.github.io/ground-control-patcher · unofficial

1 **Back up the microSD card.**
Copy the whole card somewhere safe first.

2 **Get the stock firmware.**
Download the official `gc-*.hex` (v3.26) from endorphin.es.

3 **Build in the browser.**
Open the patcher (Chrome/Edge, https), select the `.hex`, tick **Polyphony v1**, click **Build**. Confirm ✓ `v3.26`.

4 **Mount the card.**
Hold **PROJ ~5 s** on the module. In the tool: **Connect GC SD card** → pick it → **Install to GC**.

5 **One file, root, same name.**
The patched `gc-*.hex` goes to the **card ROOT**, unchanged name, and must be the **only** firmware `.hex` there.

6 **Flash.**
Press **PROJ ~5 s** again — the module reboots and flashes. Power-cycle when done.

The patcher makes a file; it does not flash the module. The module's bootloader flashes a `gc-*.hex` at the card root. Keep the v2.x SD-recovery method handy for the first modded image.

Unofficial, not affiliated with Endorphin.es. Record chords on this firmware to get poly data (stock projects load as mono). Return to stock: original `gc-*.hex` at root, PROJ ~5 s.