Casino sign - parts list: strips, LED counts and cutting list

3 strips, 14 pieces, 164 LEDs = 2.73 m of strip (60 LEDs per metre, pitch 16.7 mm).

Cut the strip only between two LEDs (at the cut marks). See layout-diagram.svg for the positions.

LED counts and cutting list

Strip	Pin	LEDs	Pieces	LEDs per piece (index range)
frameCw	D9	**53**	2	top edge 28 (#0-27), right edge 25 (#28-52)
frameCcw	D10	**53**	2	left edge 25 (#0-24), bottom edge 28 (#25-52)
letters	D11	**58**	10	see the letter table below
Total		**164**	**14**	3 strips, 164 LEDs, 14 pieces

Letters (strip D11): LEDs per letter group and LED index range

C (line 1)	A (line 1)	S (line 1)	I (line 1)	N (line 1)	O (line 1)	O (line 2)	P (line 2)	E (line 2)	N (line 2)
6 LEDs	6 LEDs	6 LEDs	4 LEDs	6 LEDs	6 LEDs	6 LEDs	6 LEDs	6 LEDs	6 LEDs
#0-5	#6-11	#12-17	#18-21	#22-27	#28-33	#34-39	#40-45	#46-51	#52-57

The letter pieces are joined in reading order (CASINO, then OPEN) with wire jumpers; together they are the one strip 'letters' on pin D11.

Grove sticks: 10 arrow sticks + the CLOSED light (in the shield, not cut)

Stick	Connector	LEDs	Position
1 L-CAP	D2	10	left vertical bar
2 L-WING-UP	D3	10	left upper wing
3 L-WING-DN	D4	10	left lower wing
4 RAIL-UP-L	D5	10	upper rail, left stick
5 RAIL-UP-R	D6	10	upper rail, right stick
6 RAIL-DN-L	D7	10	lower rail, left stick
7 RAIL-DN-R	D8	10	lower rail, right stick
8 R-CAP	A0	10	right vertical bar
9 R-WING-UP	A1	10	right upper wing
10 R-WING-DN	A2	10	right lower wing
11 CLOSED	A3	10	CLOSED light, behind the plate

Stick body 83 x 10 mm, LED window 74 x 4 mm; arrow geometry and drill template: arrow_sticks/.