Casino Open Sign V2 - parts: strips, pixel numbers and cutting list

2 strips, 28 pixels = 2.8 m of 12 V WS2811 strip (30 LEDs per metre, 1 pixel = 10 cm); 11 Grove sticks of 10 LEDs.
Cut the strip only at the cut marks (between two pixels). Both strips are single pieces: no joints.

Strips

Strip	Pin	Pixels	LEDs	Length / contents
letters	D10	**10**	30	100 cm, one piece 1-6 C A S I N O, 7-10 N E P O (reversed)
frame	D12	**18**	54	180 cm, one piece 1-6 bottom 7-9 right 10-15 top 16-18 left
Total		**28**	84	2.8 m of one 5 m reel (50 pixels): 2.2 m left over

Frame strip (D12): pixel numbers (front view, counter-clockwise)

Pixels	Position	Corners
1 - 6	bottom edge, left to right	pixel 1 = lower-left corner, pixel 6 = lower-right corner
7 - 9	right edge, going up	
10 - 15	top edge, right to left	pixel 10 = upper-right corner, pixel 15 = upper-left corner
16 - 18	left edge, going down	the strip ends here (DOUT end)

Frame light, arrow right: start pixel 15 (upper left), end pixel 6 (lower right).
Frame light, arrow left: start pixel 10 (upper right), end pixel 1 (lower left).

Letters strip (D10): one pixel per letter

C (line 1)	A (line 1)	S (line 1)	I (line 1)	N (line 1)	O (line 1)	O (line 2)	P (line 2)	E (line 2)	N (line 2)
pixel 1	pixel 2	pixel 3	pixel 4	pixel 5	pixel 6	pixel 10	pixel 9	pixel 8	pixel 7

The strip order is C A S I N O N E P O: the OPEN letters are wired in REVERSED order (O is the last pixel).
The program maps every letter to its pixel, so all patterns run in reading order for the viewer.

Grove sticks: 10 arrow sticks + the CLOSED light (in the shield, not cut)

Stick	Connector	LEDs	Position
1 L-CAP	D2	10	left vertical bar
2 L-WING-UP	D6	10	left upper wing
3 L-WING-DN	D5	10	left lower wing
4 RAIL-UP-L	D7	10	upper rail, left stick
5 RAIL-UP-R	D8	10	upper rail, right stick
6 RAIL-DN-L	D3	10	lower rail, left stick
7 RAIL-DN-R	D4	10	lower rail, right stick
8 R-CAP	A3	10	right vertical bar
9 R-WING-UP	A1	10	right upper wing
10 R-WING-DN	A2	10	right lower wing
11 CLOSED	A0	10	CLOSED light, behind the plate

Stick body 83 x 10 mm, LED window 74 x 4 mm; arrow geometry and drill template: ../arrow_sticks/.