

BATTERY INFORMATION FOR EU REGULATION

R03 (AAA Size) Zinc-Carbon Primary Battery (non-rechargeable)

Compliant with Regulation (EU) 2023/1542 - Manufacturer: Luoyang
Anxin & Wuhan Lixin New Energy Technology Co., Ltd.

General information

Battery Name:inc-Carbonprimarycylindricalbattery(non-rechargeable)

Category: Portable battery

Chemistry System: Zn-MnO₂ (zinc-manganese dioxide carbon type)

Model: R03 (commercial name: AAA / Size 7 carbon-zinc battery)

Norminal Voltage: 1.5V

Shelf Life: 24 months under normal indoor storage environment;
retains ≥85% initial capacity at end of shelf-life

Country of Origin: China

Approx. Weight: 7.5-9.0 g (for reference only)

Trade/Brand name: ETEnergy/No-brand/OEM brands

Manufacturer

Manufacture Name: Luoyang Anxin New Energy Technology Co.,
Ltd. AND Wuhan Lixin New Energy Technology Co., Ltd.


- **Address:** Anxin Industrial Park, Dongdajiao Village, Dianzhuang Town,
Luolong District, Luoyang City, Henan Province, P.R. China AND Wuhan
Huangpi Qianchuan Industrial Park

- **Post Code:** 471942
 - **E-mail:** hl448925760@gmail.com
-

Critical raw materials

Lithium, Manganese, Graphite

Marking



KEEP OUT OF REACH OF CHILDREN -

Swallowing can lead to chemical burns, perforation of soft tissue, and death. Severe burns can occur within 2 hours of ingestion. Seek medical attention immediately



Warning & Caution

WARNING

- Since the battery is not designed to be charged, there are risks of electrolyte leakage or causing damage to the device if the battery is charged.
- The battery shall be installed with its '+' and '-' polarity in correct position, otherwise may cause the battery to be charged or over-discharged.
- Short-circuiting, heating, disposing of in fire and disassembling the battery are prohibited.
- Battery cannot be forced discharge, which leads to excess internal gas generation and may result in bulging, leakage and explosion.
- New and used batteries cannot be mixed at the same time; when replacing batteries, it is recommended to replace all with the same brand type.

- Exhausted batteries should be removed from compartment to prevent over-discharge, which causes leakage and damage to the device.
- Direct soldering is not allowed, which will damage the battery.
- Keep the battery out of the reach of children to prevent swallowing; in case of accident should contact physician at once.
- The battery should not be dismantled and deformed.
- Do not store or carry batteries with metal objects (keys, coins, etc.) to avoid short-circuit.
- Do not immerse batteries in water or expose them to high humidity.
- Do not attempt to modify or solder the battery directly.
- If battery leakage occurs, avoid contact with skin and eyes. In case of contact, flush with plenty of water and seek medical advice immediately.

CAUTION

- If a battery leaks and materials contact eyes, flush immediately with running water for at least 15 minutes. Consult an ophthalmologist at once.
- If battery emits an odor, fever, discoloration, deformation or any abnormal phenomena appear in the process of use/storage,

remove the battery immediately from the device and dispose of the battery.

- Do not mix batteries of different types, brands, or significantly different capacities.
- Avoid exposing batteries to extreme heat (e.g., direct sunlight, radiators).

Information on Prevention and Management of Waste Batteries for Primary Batteries

In accordance with the requirements of the EU Battery Directive and the Waste Framework Directive, for primary (non-rechargeable) batteries supplied within the territory of an EU Member State, producers or their authorised producer responsibility organisations shall make the following information available to end-users and distributors:

(a) Role of end-users in waste prevention

Follow the device manufacturer's instructions for correct battery insertion and usage. Avoid storing or using batteries in extreme temperatures or high humidity. Remove batteries from devices that will not be used for an extended period to prevent leakage or unnecessary discharge. Primary batteries are not rechargeable; do not attempt to recharge them, as this may cause leakage or rupture.

When the battery is depleted, encourage users to bring it to designated collection points to enable potential material recovery or recycling.

(b) Role of end-users in separate collection (Article 64)

End-users are obliged to separate spent batteries from other household waste. Do not discard batteries in unsorted municipal waste or litter them. Separate collection facilitates proper treatment and resource recovery (e.g., zinc, manganese, steel, lithium), aligning with EU environmental objectives.

(c) Separate collection, take-back and collection points, preparation for reuse, repurposing and treatment

Spent batteries can be returned via: collection bins at retail points; municipal recycling centres; designated battery collection points. Collected batteries will undergo sorting, pre-treatment (including neutralisation of electrolyte), and material recycling. Reuse or repurposing is generally not applicable for primary batteries, but material recovery is maximised.

(d) Safety instructions to handle waste batteries

Avoid storing waste batteries together with metal objects to prevent short-circuiting. If a battery shows signs of leakage (e.g., white or crystalline residue), deformation, or overheating, handle it with protective gloves and store it separately in a plastic bag. Never

dispose of batteries in fire, as this may cause explosion or release of hazardous fumes. Keep batteries out of reach of children. If swallowed, seek medical attention immediately.

(e) Meaning of labels and symbols (Article 13)



Crossed-out wheeled bin symbol: Indicates that the battery should not be disposed of with unsorted household waste; it must be separately collected.



CE marking: Indicates that the battery (or the device it is intended for) complies with applicable EU health, safety, and environmental protection requirements.



Keep out of reach of children symbol: A warning to prevent ingestion or mishandling, especially for small children.



Do not recharge symbol: This battery is non-rechargeable; attempting to recharge may cause leakage or explosion.

(f) Impact of substances on environment and human health

Primary batteries contain various materials (zinc, manganese, lithium, etc.). If improperly discarded (e.g., landfilled or incinerated), the electrolyte can leak and cause soil and water contamination; heavy metals may accumulate in the environment. Swallowing a battery can cause injury; batteries should be kept away from children.

Inappropriate disposal increases environmental burdens, wastes recoverable materials, and may lead to fires or injuries during waste handling. Leaking batteries can cause chemical burns; always handle with care.

This information is provided to support end-users in responsible battery use and disposal, in line with EU waste legislation.

Conformity with legislation

The above information is in conformity with the following

legislations: **REGULATION (EU) 2023/1542 OF THE EUROPEAN**

PARLIAMENT AND OF THE COUNCIL of 12 July 2023 on the

harmonisation of the laws of the Member States relating to

sustainability, safety, labeling/information of Batteries — battery was

assessed and found to be in conformity with the enforceable

requirements of Articles 6, 13 of the Regulation.

Supplier responsibility note: We understand that the OEM of the device which contains the battery, or battery supplied by the OEM as a replacement part in the European Economic Area (EEA), has the

responsibility of preparing the DOC & TDC. As a battery supplier stipulated in Article 39, we will provide the information included in this document as backup to our customers who are manufacturers.

Disclaimer: The information provided above is supplied by Anxin based on current product characteristics and EU regulatory requirements. This information is subject to change in response to amendments of legal requirements or changes in product characteristics. Anxin reserves the right to modify the content at any time without prior notice.

Relevant Certifications

By: Luoyang Anxin & Wuhan Lixin New Energy Technology Co., Ltd.

E-mail: hl448925760@gmail.com