METHOD STATEMENT

# Conducto Tape — Self-Adhesive Copper Tape for ESD Floor Grounding

| | | | |
|---|---|---|---|
| **Project Name** | | **Document No.** | OMX-MS-CONDUCTOTAPE |
| **Main Contractor** | | **Revision** | 01 |
| **Consultant** | | **Date of Issue** | Nov 2026 |
| **Product** | Conducto Tape | **Status** | For Approval |

## 1. Purpose

This method statement defines the procedure, sequence, resources, quality checks and safety measures for the supply and application of Conducto Tape on site. It ensures that the work is carried out safely, in line with the approved drawings and project specification, and achieves the performance stated in the O MIX Technical Data Sheet.

## 2. Scope of Work

This method statement covers layout, installation, earth connection and continuity checking of Conducto Tape copper grounding grids under conductive and ESD floor coatings.

- Review of the ESD floor design and earth points.
- Layout marking.
- Installation of the copper tape grid.
- Connection to earth points.
- Continuity checks before coating.

## 3. Definitions

| Term | Meaning |
|---|---|
| **ESD floor** | Electrostatic-dissipative floor that drains static charges safely. |
| **Grounding grid** | Network of copper tape connected to earth. |
| **Earth point** | Connection of the grid to the building earthing system. |
| **Continuity** | Uninterrupted electrical path along the grid. |

## 4. Roles & Responsibilities

| Role | Responsibility |
|---|---|
| **Project Manager** | Overall responsibility for planning, resources, approvals and coordination with the consultant and main contractor. |
| **Site Engineer** | Supervises the work daily; confirms substrate readiness, climate conditions, mixing, consumption and sequence; keeps daily records. |

| Role | Responsibility |
|---|---|
| **QA/QC Inspector** | Carries out inspections and tests at each stage, records results, raises inspection requests at hold points and signs the checklist. |
| **HSE Officer** | Conducts toolbox talks, checks PPE, ventilation, access and safe storage; stops work if unsafe conditions arise. |
| **Foreman / Applicators** | Carry out the work as per this method statement and report any deviation immediately. |
| **Storekeeper** | Receives, stores and issues materials in original packaging under the stated storage conditions; controls batch numbers. |

## 5. Materials

| Material | Description |
|---|---|
| **Conducto Tape** | Self-adhesive copper tape, 20 mm wide, 20 m or 50 m rolls |
| **Conductive primer and ESD coating** | As specified for the floor system |

### 5.1 Key product data

| Property | Typical Value |
|---|---|
| **Material** | Copper foil with conductive adhesive |
| **Thickness** | 0.05 – 0.08 mm |
| **Width** | 10 – 25 mm (standard 20 mm) |
| **Roll length** | 20 m or 50 m |
| **Function** | Grounding grid for ESD / conductive floors |

## 6. Tools & Equipment

- Chalk line
- Tape measure
- Scissors
- Hand roller
- Multimeter / resistance meter
- Thermo-hygrometer and surface thermometer (dew point check)
- Moisture meter
- Measuring buckets and scale
- Masking tape and protective sheeting
- Lighting and extension cables

### 6.1 Personal protective equipment

- Cut-resistant gloves
- Safety shoes

## 7. Storage & Handling

- Store in original packaging in a dry place at room temperature, away from moisture.
- Store on pallets, off the ground, in a dry, covered and ventilated area.
- Keep containers closed until use; use materials on a first-in, first-out basis.
- Store rolls and cartons flat, off the ground, protected from direct sunlight, heat, oil and mechanical damage.
- Handle with care to avoid damage to packaging; do not stack beyond the safe height.

## 8. Pre-Start Requirements

- Material submittal, this method statement and the inspection plan approved by the consultant.
- Work area handed over clean, free of other trades and with safe access.
- Adequate lighting, power supply and ventilation available.
- Climate conditions checked and recorded before work starts.
- A trial area prepared and approved where required by the project.
- Toolbox talk held with the work team covering this method statement and the safety measures.

## 9. Surface Preparation

1. Confirm the substrate is prepared and primed as per the floor system method statement.
2. Mark grid lines and earth-point positions as per the ESD design.
3. Clean the surface of dust along the lines.
4. Obtain QA/QC approval of the layout before installation.

## 10. Preparation of Material

1. Check the tape width and roll length against the specification.
2. Cut tape lengths as required; keep the liner on until laying.

## 11. Installation

1. Remove the liner progressively and lay the tape along the marked lines.
2. Press firmly with a hand roller to remove air pockets.
3. Form junctions by overlapping tape ends and pressing firmly.
4. Leave tails at earth points for connection by a qualified electrician.
5. Check continuity of the grid with a meter.
6. Record grid layout, earth points and continuity results.

## 12. Coating & Testing

- Apply the conductive primer and ESD coating over the grid as per their method statements.
- Measure the resistance of the finished floor as per the project specification.
- Protect the grid from damage until coated.

## 13. Quality Control & Inspection

| Check | Stage | Acceptance Criteria | By |
|---|---|---|---|
| **Layout** | Before installation | As per ESD design | QA/QC |
| **Adhesion** | After installation | Fully bonded, no air pockets | QA/QC |
| **Continuity** | Before coating | Continuous grid to earth points | QA/QC + Electrician |
| **Floor resistance** | After coating | As per project specification | QA/QC + Consultant |

### 13.1 Inspection and test plan

| Activity | Inspection / Test | Frequency | Record |
|---|---|---|---|
| **Material receipt** | Width, length, condition | Each delivery | Material inspection report |
| **Layout** | Grid spacing, earth points | Each area | Inspection request (hold point) |
| **Installation** | Adhesion, overlaps | Each area | Daily report |
| **Continuity** | Meter check | Each grid | Test record |
| **Finished floor** | Resistance test | As specified | Test report |

## 14. Defects & Remedies

| Defect | Likely Cause | Remedy |
|---|---|---|
| **Lifting tape** | Dusty surface; insufficient pressing | Clean and re-lay; roll firmly |
| **No continuity** | Broken tape or poor overlap | Repair with overlapping strip |
| **Bumps under coating** | Wrinkled tape | Re-lay flat before coating |

## 15. Health, Safety & Environment

| Hazard | Control Measures |
|---|---|
| **Cuts from copper edges** | Cut-resistant gloves |
| **Electrical connection** | Qualified electrician only |
| **Slips and trips** | Housekeeping |

- Copper edges are sharp; wear cut-resistant gloves.

- Electrical connections to earth must be made by a qualified electrician.
- Cuts: clean and dress the wound.
- Eyes: rinse with clean water if particles enter.

### 15.1 Waste & environment

- Collect empty containers and residues in designated bins.
- Do not discharge material or washings into drains or soil.
- Allow small quantities of leftover mixed material to cure before disposal; dispose of according to local regulations.

## 16. Cleaning

- Collect off-cuts and liners in waste bins.

## 17. Limitations

- Grid layout and earth points as per the approved ESD design.
- Earth connections by a qualified electrician.
- Any deviation from this method statement must be approved by the Site Engineer and the consultant.

## Appendix A — Inspection Checklist

| Inspection Item | Result | Remarks |
|---|---|---|
| **Layout marked as per design** | ☐ Yes ☐ No | |
| **Surface clean** | ☐ Yes ☐ No | |
| **Tape laid and rolled** | ☐ Yes ☐ No | |
| **Overlaps pressed** | ☐ Yes ☐ No | |
| **Earth tails left** | ☐ Yes ☐ No | |
| **Continuity checked** | ☐ Yes ☐ No | |
| **Coating applied** | ☐ Yes ☐ No | |
| **Resistance tested** | ☐ Yes ☐ No | |

| Inspected by | Signature | Date |
|---|---|---|
| | | |