Construction Chemicals

SUBMITTAL DOCUMENT

Conducto Tape

Self-Adhesive Copper Tape
for ESD Floor Grounding



Conductive
Copper foil

Self-Adhesive
Easy install

Grounding
ESD grid

Thin
0.05 – 0.08 mm

Project	
Main Contractor	
Consultant	
Submittal No. / Rev.	00
Date	Nov 2026

Construction Chemicals

Contents

1. Method Statement 3

2. Technical Data Sheet 8

3. Test Reports 11

4. Approvals & Certificates 12

METHOD STATEMENT

Conducto Tape — Self-Adhesive Copper Tape for ESD Floor Grounding

Project Name		**Document No.**	OMX-MS-CONDUCTOTAPE
Main Contractor		**Revision**	01
Consultant		**Date of Issue**	Nov 2026
Product	Conducto Tape	**Status**	For Approval

1. Purpose

This method statement defines the procedure, sequence, resources, quality checks and safety measures for the supply and application of Conducto Tape on site. It ensures that the work is carried out safely, in line with the approved drawings and project specification, and achieves the performance stated in the O MIX Technical Data Sheet.

2. Scope of Work

This method statement covers layout, installation, earth connection and continuity checking of Conducto Tape copper grounding grids under conductive and ESD floor coatings.

- Review of the ESD floor design and earth points.
- Layout marking.
- Installation of the copper tape grid.
- Connection to earth points.
- Continuity checks before coating.

3. Definitions

Term	Meaning
ESD floor	Electrostatic-dissipative floor that drains static charges safely.
Grounding grid	Network of copper tape connected to earth.
Earth point	Connection of the grid to the building earthing system.
Continuity	Uninterrupted electrical path along the grid.

4. Roles & Responsibilities

Role	Responsibility
Project Manager	Overall responsibility for planning, resources, approvals and coordination with the consultant and main contractor.
Site Engineer	Supervises the work daily; confirms substrate readiness, climate conditions, mixing, consumption and sequence; keeps daily records.

Role	Responsibility
QA/QC Inspector	Carries out inspections and tests at each stage, records results, raises inspection requests at hold points and signs the checklist.
HSE Officer	Conducts toolbox talks, checks PPE, ventilation, access and safe storage; stops work if unsafe conditions arise.
Foreman / Applicators	Carry out the work as per this method statement and report any deviation immediately.
Storekeeper	Receives, stores and issues materials in original packaging under the stated storage conditions; controls batch numbers.

5. Materials

Material	Description
Conducto Tape	Self-adhesive copper tape, 20 mm wide, 20 m or 50 m rolls
Conductive primer and ESD coating	As specified for the floor system

5.1 Key product data

Property	Typical Value
Material	Copper foil with conductive adhesive
Thickness	0.05 – 0.08 mm
Width	10 – 25 mm (standard 20 mm)
Roll length	20 m or 50 m
Function	Grounding grid for ESD / conductive floors

6. Tools & Equipment

- Chalk line
- Tape measure
- Scissors
- Hand roller
- Multimeter / resistance meter
- Thermo-hygrometer and surface thermometer (dew point check)
- Moisture meter
- Measuring buckets and scale
- Masking tape and protective sheeting
- Lighting and extension cables

6.1 Personal protective equipment

- Cut-resistant gloves
- Safety shoes

7. Storage & Handling

- Store in original packaging in a dry place at room temperature, away from moisture.
- Store on pallets, off the ground, in a dry, covered and ventilated area.
- Keep containers closed until use; use materials on a first-in, first-out basis.
- Store rolls and cartons flat, off the ground, protected from direct sunlight, heat, oil and mechanical damage.
- Handle with care to avoid damage to packaging; do not stack beyond the safe height.

8. Pre-Start Requirements

- Material submittal, this method statement and the inspection plan approved by the consultant.
- Work area handed over clean, free of other trades and with safe access.
- Adequate lighting, power supply and ventilation available.
- Climate conditions checked and recorded before work starts.
- A trial area prepared and approved where required by the project.
- Toolbox talk held with the work team covering this method statement and the safety measures.

9. Surface Preparation

1. Confirm the substrate is prepared and primed as per the floor system method statement.
2. Mark grid lines and earth-point positions as per the ESD design.
3. Clean the surface of dust along the lines.
4. Obtain QA/QC approval of the layout before installation.

10. Preparation of Material

1. Check the tape width and roll length against the specification.
2. Cut tape lengths as required; keep the liner on until laying.

11. Installation

1. Remove the liner progressively and lay the tape along the marked lines.
2. Press firmly with a hand roller to remove air pockets.
3. Form junctions by overlapping tape ends and pressing firmly.
4. Leave tails at earth points for connection by a qualified electrician.
5. Check continuity of the grid with a meter.
6. Record grid layout, earth points and continuity results.

12. Coating & Testing

- Apply the conductive primer and ESD coating over the grid as per their method statements.
- Measure the resistance of the finished floor as per the project specification.
- Protect the grid from damage until coated.

13. Quality Control & Inspection

Check	Stage	Acceptance Criteria	By
Layout	Before installation	As per ESD design	QA/QC
Adhesion	After installation	Fully bonded, no air pockets	QA/QC
Continuity	Before coating	Continuous grid to earth points	QA/QC + Electrician
Floor resistance	After coating	As per project specification	QA/QC + Consultant

13.1 Inspection and test plan

Activity	Inspection / Test	Frequency	Record
Material receipt	Width, length, condition	Each delivery	Material inspection report
Layout	Grid spacing, earth points	Each area	Inspection request (hold point)
Installation	Adhesion, overlaps	Each area	Daily report
Continuity	Meter check	Each grid	Test record
Finished floor	Resistance test	As specified	Test report

14. Defects & Remedies

Defect	Likely Cause	Remedy
Lifting tape	Dusty surface; insufficient pressing	Clean and re-lay; roll firmly
No continuity	Broken tape or poor overlap	Repair with overlapping strip
Bumps under coating	Wrinkled tape	Re-lay flat before coating

15. Health, Safety & Environment

Hazard	Control Measures
Cuts from copper edges	Cut-resistant gloves
Electrical connection	Qualified electrician only
Slips and trips	Housekeeping

- Copper edges are sharp; wear cut-resistant gloves.

- Electrical connections to earth must be made by a qualified electrician.
- Cuts: clean and dress the wound.
- Eyes: rinse with clean water if particles enter.

15.1 Waste & environment

- Collect empty containers and residues in designated bins.
- Do not discharge material or washings into drains or soil.
- Allow small quantities of leftover mixed material to cure before disposal; dispose of according to local regulations.

16. Cleaning

- Collect off-cuts and liners in waste bins.

17. Limitations

- Grid layout and earth points as per the approved ESD design.
- Earth connections by a qualified electrician.
- Any deviation from this method statement must be approved by the Site Engineer and the consultant.

Appendix A — Inspection Checklist

Inspection Item	Result	Remarks
Layout marked as per design	☐ Yes ☐ No	
Surface clean	☐ Yes ☐ No	
Tape laid and rolled	☐ Yes ☐ No	
Overlaps pressed	☐ Yes ☐ No	
Earth tails left	☐ Yes ☐ No	
Continuity checked	☐ Yes ☐ No	
Coating applied	☐ Yes ☐ No	
Resistance tested	☐ Yes ☐ No	

Inspected by	Signature	Date

Construction Chemicals

Technical Data Sheet

Conducto Tape — Submittal Document

Construction Chemicals

Product Datasheet
Edition: 01 | Date: Nov 2026
Accessories



Conducto Tape

Self-Adhesive Copper Tape
for ESD Floor Grounding

Product Description

Conducto Tape is a self-adhesive conductive copper tape for electrostatic-dissipative (ESD) and conductive floor systems. It is installed as a grid under the conductive primer and ESD coating and connected to earth points to dissipate static electricity safely.

Uses

- Grounding grid under conductive and ESD epoxy floors.
- Electronics production and assembly areas.
- Data centres and server rooms.
- Laboratories, clean rooms and pharmaceutical areas.
- Areas with explosive or sensitive materials.

Advantages

- Excellent electrical conductivity.
- Self-adhesive, easy installation.
- Forms a continuous grounding grid.
- Thin profile: 0.05 – 0.08 mm.
- Compatible with conductive primers and ESD coatings.

Application

1. **Layout**
   Mark the grid lines and earth-point positions on the primed, clean floor.
2. **Installation**
   Remove the liner and press the tape firmly along the lines; connect the grid to earth points.
3. **Coating**
   Apply the conductive primer and the ESD coating over the grid; test resistance.

Consumption

As per grid layout
grid spacing as per ESD floor design
Grid spacing and earth points as per the ESD floor design.

Packaging

Rolls of 20 m or 50 m; standard width 20 mm (10 – 25 mm available).

Storage & Shelf Life

Store in original packaging in a dry place at room temperature, away from moisture.

Technical Data

Typical values at 25 °C

Property	Typical Value	Test Method
Material	Copper foil with conductive adhesive	—
Thickness	0.05 – 0.08 mm	—
Width	10 – 25 mm (standard 20 mm)	—
Roll length	20 m or 50 m	—
Function	Grounding grid for ESD / conductive floors	—

Consumption

Item	Requirement
Grid layout	As per ESD floor design
Connection to earth	At designed earth points
Joints	Overlap and press firmly

Consumption is theoretical and varies with substrate porosity, profile and application method.

Application Conditions

- Install on a clean, dry, primed surface.
- Press firmly for full adhesion along the whole length.
- Connect the grid to earth points as per the design.
- Check continuity before applying the conductive primer.

Application Notes

- Install straight runs and form junctions by overlapping tape ends.
- Avoid wrinkles and air pockets.
- Leave tails at earth points for connection by an electrician.
- Measure resistance of the finished floor as per the project specification.

Health & Safety

- Copper edges are sharp; wear cut-resistant gloves.
- Electrical connections to earth must be made by a qualified electrician.

First Aid & Cleaning

- Cuts: clean and dress the wound.
- Eyes: rinse with clean water if particles enter.
- Skin: wash with soap and water.
- Collect off-cuts and liners in waste bins.

The information in this datasheet is based on laboratory tests and practical experience and is given in good faith. Users should verify product suitability for their specific application. O MIX reserves the right to update this information without prior notice.

Construction Chemicals

Test Reports

Conducto Tape — Submittal Document

To be attached: laboratory test reports supporting the values in the Technical Data Sheet.

Construction Chemicals

Approvals & Certificates

Conducto Tape — Submittal Document

To be attached: approvals and certificates, where available.