METHOD STATEMENT

O-Poxy Edge — Solvent-Free High-Performance Epoxy Floor Coating

Project Name		**Document No.**	OMX-MS-OPOXYEDGE
Main Contractor		**Revision**	01
Consultant		**Date of Issue**	Nov 2026
Product	O-Poxy Edge	**Status**	For Approval

1. Purpose

This method statement defines the procedure, sequence, resources, quality checks and safety measures for the supply and application of O-Poxy Edge on site. It ensures that the work is carried out safely, in line with the approved drawings and project specification, and achieves the performance stated in the O MIX Technical Data Sheet.

2. Scope of Work

This method statement covers substrate preparation, priming, filling, mixing and application of O-Poxy Edge, a two-component epoxy floor coating, on concrete floors in industrial, commercial and parking areas.

- Inspection and acceptance of the substrate and the work area.
- Surface preparation and repair of defects.
- Priming of the prepared surface.
- Mixing and application of the material as described in this document.
- Curing, protection and handover of the completed area.
- Quality control, inspection and documentation of each stage.

3. Definitions

Term	Meaning
Pot life	Time the mixed material remains workable after Part A and Part B are combined.
Recoat interval	Minimum and maximum time between coats to achieve inter-coat adhesion.
WFT / DFT	Wet film thickness measured during application / dry film thickness after cure.
Dew point	Temperature at which moisture condenses; the substrate must be at least 3 °C above it.
Kit / set	Pre-weighed Part A and Part B supplied to be mixed completely.

4. Roles & Responsibilities

Role	Responsibility
Project Manager	Overall responsibility for planning, resources, approvals and coordination with the consultant and main contractor.

Role	Responsibility
Site Engineer	Supervises the work daily; confirms substrate readiness, climate conditions, mixing, consumption and sequence; keeps daily records.
QA/QC Inspector	Carries out inspections and tests at each stage, records results, raises inspection requests at hold points and signs the checklist.
HSE Officer	Conducts toolbox talks, checks PPE, ventilation, access and safe storage; stops work if unsafe conditions arise.
Foreman / Applicators	Carry out the work as per this method statement and report any deviation immediately.
Storekeeper	Receives, stores and issues materials in original packaging under the stated storage conditions; controls batch numbers.

5. Materials

Material	Description
O-Poxy Edge	Epoxy floor coating, 5 kg A + B sets
O-Prime SF	Solvent-free epoxy primer
O-Putty	Epoxy filler for defects
Quartz sand	0.1 – 0.4 mm, dry, for broadcast

5.1 Key product data

Property	Typical Value
Mixing ratio (A : B)	100 : 15 by weight
Solids content	100 %
Specific gravity	1.57
Colour	On request
Pot life (25 °C)	40 min
Recoat interval	24 hours
Hardening	12 – 24 hours
Full cure	7 days

6. Tools & Equipment

- Grinder / shot blaster
- Industrial vacuum
- Slow-speed mixer
- Notched spatula
- Rollers
- Spiked roller
- Moisture meter
- Wet-film gauge

- Thermo-hygrometer and surface thermometer (dew point check)
- Moisture meter
- Wet-film thickness gauge
- Measuring buckets and scale
- Masking tape and protective sheeting
- Lighting and extension cables

6.1 Personal protective equipment

- Gloves
- Goggles
- Overalls
- Organic-vapour mask

7. Storage & Handling

- 12 months in original, unopened packaging. Store dry at +5 °C to +35 °C, away from direct sunlight.
- Store on pallets, off the ground, in a dry, covered and ventilated area.
- Keep containers closed until use; use materials on a first-in, first-out basis.
- Keep Part A and Part B of each kit together and do not mix parts from different batches.
- Store away from heat, sparks and ignition sources.
- Handle with care to avoid damage to packaging; do not stack beyond the safe height.

8. Pre-Start Requirements

- Material submittal, this method statement and the inspection plan approved by the consultant.
- Work area handed over clean, free of other trades and with safe access.
- Adequate lighting, power supply and ventilation available.
- Climate conditions checked and recorded before work starts.
- A trial area prepared and approved where required by the project.
- Toolbox talk held with the work team covering this method statement and the safety measures.

9. Surface Preparation

1. Check concrete age (≥ 28 days), strength (≥ 25 N/mm²) and moisture (< 4 %).
2. Grind or shot blast to remove laitance, oil, curing compounds and old coatings.
3. Vacuum all dust. Repair cracks and holes with O-Putty.
4. Measure substrate temperature, air temperature and relative humidity; confirm the substrate is at least 3 °C above dew point.
5. Protect adjacent surfaces, drains and fixtures with masking tape and sheeting.
6. Obtain QA/QC approval of the prepared surface before starting the next step.

10. Mixing

1. Condition materials to between +15 °C and +25 °C before mixing.
2. Check the batch numbers and expiry dates of both parts and record them.
3. Stir Part A to redistribute settled solids.
4. Add the full contents of Part B (ratio 100:15 by weight) and mix 2 – 3 minutes at low speed.
5. Mix complete sets only; do not thin.
6. Mix only the quantity that can be applied within the pot life.

11. Application

1. Apply O-Prime SF at 0.10 – 0.15 kg/m² and allow to cure.
2. Apply O-Putty where required and sand lightly.
3. Apply O-Poxy Edge at 0.25 – 0.30 kg/m² per coat with a notched spatula or roller, then de-aerate with a spiked roller.
4. Apply the next coat within 24 hours; if exceeded, abrade the surface first.
5. Work in manageable bays, keeping a wet edge to avoid lap marks.
6. Check consumption by area and wet film thickness regularly during application and record the results.

12. Curing & Protection

- Pot life 40 minutes at 25 °C.
- Hardening 12 – 24 hours; full cure 7 days.
- Protect from water, dirt and traffic during curing.
- Protect the applied area from water, dust, other trades and traffic until the stated cure times are reached.
- Barricade the area and display warning signs.

13. Quality Control & Inspection

Check	Stage	Acceptance Criteria	By
Substrate	Before priming	≥ 28 days, ≥ 25 N/mm², moisture < 4 %	QA/QC
Climate	During work	+10 °C to +35 °C, RH ≤ 85 %, 3 °C above dew point	Site Engineer
Film thickness	During application	WFT checked with gauge per coat	QA/QC
Finished floor	After cure	Uniform colour, no pinholes, bubbles or soft spots	QA/QC

13.1 Inspection and test plan

Activity	Inspection / Test	Frequency	Record
Material receipt	Product, batch, expiry, packaging condition	Each delivery	Material inspection report

Activity	Inspection / Test	Frequency	Record
Climate	Air / substrate temperature, RH, dew point	Start of shift and every 4 hours	Daily climate log
Surface preparation	Visual, moisture, soundness	Each area	Inspection request (hold point)
Application	Consumption, thickness, appearance	Each coat / area	Daily progress report
Final inspection	Visual, continuity, finish	Each completed area	Handover checklist

14. Defects & Remedies

Defect	Likely Cause	Remedy
Pinholes / bubbles	Outgassing from porous substrate; air entrapped in mixing	Seal with primer; mix at low speed; de-aerate with spiked roller; sand and recoat
Blushing / tacky surface	High humidity or low temperature during cure	Wash and abrade; recoat in suitable conditions
Poor adhesion	Contaminated, weak or damp substrate; recoat window exceeded	Remove, re-prepare surface and reapply
Soft spots	Incorrect mixing or ratio	Remove affected area and reapply with full kits
Uneven colour / lap marks	Loss of wet edge; different batches	Abrade and apply a further coat from one batch

15. Health, Safety & Environment

Hazard	Control Measures
Skin and eye contact	Gloves, goggles, overalls; eye-wash available
Inhalation of vapours / dust	Ventilation; masks as required
Slips and trips	Housekeeping; barricades and signs
Manual handling	Correct lifting technique; mechanical aids
Electrical tools	Inspected tools; protected cables

- Wear nitrile gloves, safety goggles and overalls.
- Uncured epoxy may cause skin sensitisation; avoid skin and eye contact.
- Ensure good ventilation in enclosed areas.
- Eyes: rinse with clean water for 15 minutes and seek medical advice.
- Skin: wash with soap and water.

15.1 Waste & environment

- Collect empty containers and residues in designated bins.
- Do not discharge material or washings into drains or soil.
- Allow small quantities of leftover mixed material to cure before disposal; dispose of according to local regulations.

16. Cleaning

- Clean tools with epoxy thinner before the material cures.

17. Limitations

- Ambient and substrate temperature: +10 °C to +35 °C.
- Substrate at least 3 °C above dew point.
- Do not apply in rain or when rain is expected before the material has set.
- Any deviation from this method statement must be approved by the Site Engineer and the consultant.

Appendix A — Inspection Checklist

Inspection Item	Result	Remarks
Substrate age, strength and moisture verified	☐ Yes ☐ No	
Surface ground and vacuumed	☐ Yes ☐ No	
Primer applied and cured	☐ Yes ☐ No	
Defects filled with O-Putty	☐ Yes ☐ No	
Complete sets mixed (100:15)	☐ Yes ☐ No	
Climate conditions within limits	☐ Yes ☐ No	
Consumption / WFT per coat verified	☐ Yes ☐ No	
Recoat within 24 hours	☐ Yes ☐ No	
Final visual inspection passed	☐ Yes ☐ No	

Inspected by	Signature	Date