

Algebraic Coding Theory

arnaucube

2026

Abstract

Notes taken while studying Algebraic Coding Theory, mostly from Hill book [1] and Lint book [2].

Usually while reading books and papers I take handwritten notes in a notebook, this document contains some of them re-written to *LaTeX*.

The proofs may slightly differ from the ones from the books, since I try to extend them for a deeper understanding.

Contents

1	Vector spaces over finite fields, quick recap	2
2	Linear codes	3
2.1	Some definitions	3
2.2	Equivalence	4
2.3	Encoding with a linear code	4
2.4	Decoding with a linear code	5
2.4.1	Cosets	5
2.5	Probability of error correction (in binary linear codes)	7
2.6	Exercises	8
3	Dual code, PCM and Syndrome	12
3.1	Dual code	12
3.2	PCM (parity-check matrix)	13
3.3	Syndrome	14
3.4	Incomplete decoding	16
3.5	Exercises	16
4	Hamming Codes	19
4.1	Extended binary Hamming codes	21
4.2	q-ary Hamming codes	22
5	MLCT - Main Linear Coding Theory problem	23
5.1	The projective geometry $PG(r-1, q)$	25

6	MDS Codes	26
6.1	Vandermonde determinant	28
7	Cyclic Codes	29
7.1	Recap on ideals	29
7.2	Cyclic Codes intro	30
7.3	Generator polynomial and check polynomial	33
7.4	Maximal and minimal cyclic codes	36
7.5	Hamming cyclic codes	37
7.6	Idempotent of a cyclic code	38
7.7	Trace representation	39
7.8	Mattson-Solomon Polynomial	40
8	BCH Codes	41

1 Vector spaces over finite fields, quick recap

Let q be a prime power.

$V(n, q)$: set $GF(q)^n$ of all ordered n -tuples over $GF(q)$. $V(n, q)$ is a vector space.

A set of vectors $\{v_1, v_2, \dots, v_r\}$ is said to be *linear dependent* if $\exists$ scalars $a_1, \dots, a_r$, not all zero, such that

$$a_1v_1 + a_2v_2 + \dots + a_rv_r = 0$$

They are *linear independent* if

$$a_1v_1 + a_2v_2 + \dots + a_rv_r = 0 \xrightarrow{\text{implies}} a_1 = a_2 = \dots = a_r = 0$$

Let C a subspace of $V(n, q)$. Then a subset $\{v_1, v_2, \dots, v_r\} \subseteq C$ is called a *generating set* (or *spanning set*) of C if every vector in C can be expressed as a linear combination of $v_1, \dots, v_r$.

A generating set of C which is also linearly independent is called a *basis* of C .

Theorem 4.3. Suppose $\{v_1, v_2, \dots, v_k\}$ is a basis of a subspace C of $V(n, q)$. Then

- every vector of C can be expressed uniquely as a linear combination of the basis vectors.
- C contains exactly q^k vectors.

Proof. i. suppose vector $x \in C$ such that

$$x = a_1v_1 + a_2v_2 + \dots + a_kv_k$$

$$x = b_1v_1 + b_2v_2 + \dots + b_kv_k.$$

then

$$(a_1 - b_1)v_1 + (a_2 - b_2)v_2 + \cdots + (a_k - b_k)v_k = 0.$$

But the set $\{v_1, v_2, \dots, v_k\}$ is linearly independent, and so

$$a_i - b_i = 0 \quad \text{for } i = 1, 2, \dots, k,$$

i.e.,

$$a_i = b_i \quad \text{for } i = 1, 2, \dots, k.$$

ii. By (i), the q^k vectors

$$\sum_{i=1}^k a_i v_i \quad (a_i \in \text{GF}(q))$$

are precisely the distinct vectors of C .

□

2 Linear codes

The theorems of this section are from [1] and follow the original enumeration of the book.

Note about notation:

A q -ary linear code $[n, k, d]$ -code is also a q -ary (n, q^k, d) -code, but the opposite is not always true.

2.1 Some definitions

Let q be a prime power. View $(F_q)^n$ as the vector space $V(n, q)$.

Definition (Linear code over $\text{GF}(q)$). A *linear code over $\text{GF}(q)$* is a subspace of $V(n, q)$, with $n \geq 0$.

Thus $C \subseteq V(n, q)$ is a linear code iff

- i. $u + v \in C \quad \forall u, v \in C$
- ii. $au \in C \quad \forall u \in C, a \in \text{GF}(q)$

If C is a k -dimensional subspace of $V(n, q)$, then the linear code C is called an $[n, k]$ -code. (sometimes with minimum distance d : $[n, k, d]$ -code).

Definition (Weight). Weight, $w(x)$, of a vector $x \in V(n, q)$ is the number of non-zero entries of x .

Lemma 5.1. if $x, y \in V(n, q)$, then $d(x, y) = w(x - y)$.

Proof. the vector $x - y$ has non-zero entries in precisely those places where x and y differ. $\square$

Theorem 5.2. let C a linear code, let $w(C)$ be the smallest of weights of the non-zero codewords of C . Then $d(C) = w(C)$.

Proof. $\exists x, y \in C$ s.th. $d(C) = d(x, y)$.

By Lemma 5.1, $d(C) = w(x - y) \geq w(C)$, since $x - y$ is a codeword of the linear code C (ie. $x - y \in C$).

On the other hand, for $x \in C$,
 $w(C) = w(x) = d(x, 0) \geq d(C)$, since $0 \in C$.

Hence, $d(C) \geq w(C)$ and $w(C) \geq d(C) \implies d(C) = w(C)$. $\square$

Definition (Generator matrix (GM)). a $k \times n$ matrix whose rows form a basis of a linear $[n, k]$ -code is called a *generator matrix* (GM) of the code.

2.2 Equivalence

Theorem 5.4. two known $k \times n$ matrices generate equivalent linear $[n, k]$ -codes over $GF(q)$ if one matrix can be obtained from the other by a sequence of operations of the following types:

- R1. permutation of the rows
- R2. multiplication of a row by a non-zero scalar
- R3. addition of a scalar multiple of one row to another
- C1. permutation of the columns
- C2. multiplication of any column by a non-zero scalar

Theorem 5.5. let G a GM of an $[n, k]$ -code. Then by performing the previous operations, G can be transformed to the standard form $[I_k | A]$ where I_k is the $k \times k$ identity matrix, and A is a $k \times (n - k)$ matrix.

2.3 Encoding with a linear code

Let C a $[n, k]$ -code over $GF(q)$ with GM G . C contains q^k codewords $\implies$ can be used to communicate any one of q^k distinct messages.

Identify these messages with the q^k tuples of $V(k, q)$.

Encoding:

msg vector: $u = u_1 u_2 \dots u_k$; rows of G : $r_1 r_2 \dots r_k$. Encode

$$uG = \sum_{i=1}^k u_i r_i \in C$$

ie. uG is a codeword of C ; a linear combination of the rows of the GM.

Encoding function:

$$\begin{aligned} V(k, q) &\longrightarrow C \subseteq V(n, q) \\ u &\longmapsto uG \end{aligned}$$

If G is in standard form (5.5), $G = [I_k | A]$ with $A = [a_{ij}]$, then encoding u is:

$$x = uG = x_1x_2 \dots x_kx_{k+1} \dots x_n$$

where

$$\begin{aligned} x_i &= u_i \quad \text{for } 1 \leq i \leq k, \text{ message digits} \\ x_{k+i} &= \sum_{j=1}^k a_{ji}u_j \quad \text{for } 1 \leq i \leq n-k, \text{ check digits} \end{aligned}$$

the check digits add redundancy to give protection against noise.

2.4 Decoding with a linear code

Codeword $x = x_1x_2 \dots x_n$, received vector $y = y_1y_2 \dots y_n$, error vector $e = y - x = e_1e_2 \dots e_n$.

2.4.1 Cosets

Cosets here are similar to the ones from typical group theory, just from another perspective.

Definition (Coset). Let C a $[n, k]$ -code over $GF(q)$ and $a \in V(n, q)$. Then the set $a + C = \{a + x | x \in C\}$ is called a *coset* of C .

Definition (Coset leader). the vector having minimum weight in a coset is called the *coset leader*.

Lemma 6.3. Let $a + C$ a coset of C and $b \in a + C$. Then $b + C = a + C$.

Proof. since $b \in a + C \implies b = a + x$ for some $x \in C$. If $b + y \in b + C$ then

$$b + y = (a + x) + y = a + (x + y) \in a + C$$

For the other direction, if $a + x \in a + C$ then

$$a + x = (b - x) + z = b + (z - x) \in b + C$$

hence $a + C \subseteq b + C$.

Therefore $b + C = a + C$. □

Theorem 6.4 (Lagrange). suppose $C \subseteq V(n, q)$ is a $[n, k]$ -code over $GF(q)$. Then

- i. every vector of $V(n, q)$ is in some coset of C
- ii. every coset contains exactly q^k vectors
- iii. two cosets either are disjoint or coincide (partial overlap is impossible)

Proof. i. if $a \in V(n, q)$ then $a = a + 0 \in a + C$

- ii. the map

$$\begin{aligned} C &\longrightarrow a + C \quad \forall x \in C \\ x &\longmapsto a + x \end{aligned}$$

is a one-to-one map, hence $|a + C| = |C| = q^k$.

- iii. by contradiction, suppose cosets $a + C$, $b + C$ overlap. Then for some vector v ,

$$v \in (a + C) \cap (b + C)$$

thus for some $x, y \in C$, $v = a + x = b + y$.

Hence $b = a + (x - y) \in a + C$, thus by Lemma 6.3 we have $b + C = a + C$. $\square$

Corollary . 6.4 shows that $V(n, q)$ is partitioned into disjoint cosets of C :

$$V(n, q) = (0 + C) \cup (a_1 + C) \cup \dots \cup (a_s + C)$$

where $s = q^{n-k} - 1$, and by Lemma 6.3 we may take $0, a_1, \dots, a_s$ to be coset leaders.

Example 6.5. Let C be the binary $[4, 2]$ -code with generator matrix

$$G = \begin{pmatrix} 1 & 0 & 1 & 1 \\ 0 & 1 & 0 & 1 \end{pmatrix}$$

ie. $C = \{0000, 1011, 0101, 1110\}$.

Then the cosets of C are

$$0000 + C = C \text{ itself}$$

$$1000 + C = \{1000, 0011, 1101, 0110\}$$

$$0100 + C = \{0100, 1111, 0001, 1010\} = 0001 + C$$

$$0010 + C = \{0010, 1001, 0111, 1100\}$$

by Lemma 6.3: $0001 \in 0100 + C$, thus $0001 + C = 0100 + C$.

2.5 Probability of error correction (in binary linear codes)

To evaluate how good a code is, must calculate the *probability* that a received vector will be decoded as the codeword which was sent.

Let p be the symbol error probability.

Probability that the error vector is agiven vector of weight i is $p^i(1-p)^{n-i}$.

Theorem 6.7. Let C a binary $[n, k]$ -code, and for $i = 0, 1, \dots, n$ let α_i denote the number of coset leaders of weight i .

Then the probability $P_{corr}(C)$ that a received vector decoded by means of a standard array is the codeword which was sent is

$$P_{corr}(C) = \sum_{i=0}^n \alpha_i \cdot p^i (1-p)^{n-i}$$

Example 6.8. $[n, k]$ -code from 6.5, coset leaders are 0000, 1000, 0100, 0010. Hence $\alpha_0 = 1$, $\alpha_1 = 3$, $\alpha_2 = \alpha_3 = \alpha_4 = 0$, so

$$P_{corr}(C) = (1-p)^4 + 3p(1-p)^3 = (1-p)^3(1+2p)$$

Remark 6.9. if $d(C) = 2t+1$ or $d(C) = 2t+2$, then C can correct any t errors.

Hence every vector of weight $\leq t$ is a coset leader and so $\alpha_i = \binom{n}{i}$ for $0 \leq i \leq t$.

Definition (Rate). $[n, k]$ -code C uses n symbols to send k message symbols; it has *rate* $R(C) = k/n$.

A good code will have a high rate.

Definition (Capacity). the *capacity* $\mathcal{C}(p)$ of a binary symmetric channel with symbol error probability p is

$$\mathcal{C}(p) = 1 + p \cdot \log_2(p) + (1-p) \cdot \log_2(1-p)$$

Theorem 6.12 (Shanon's theorem). channel binary symmetric with symbol error probability p .

Let $R < \mathcal{C}(p)$.

Then for any $\epsilon > 0$, $\exists$ for sufficient large n , an $[n, k]$ -code C of rate $k/n \geq R$ such that $P_{err}(C) < \epsilon$.

Definition (P_{symb}). P_{symb} denotes the average probability that a message symbol is in error after decoding.

Theorem 6.14. let C a binary $[n, k]$ -code and let A_i denote the number of codewords of C of weight i .

Then, if C is used for error detection, the probability of an incorrect message being undetected is

$$P_{undetec}(C) = \sum_{i=1}^n A_i \cdot p^i (1-p)^{n-i}$$

Example 6.15. for the code of 6.5,

$$P_{undetec}(C) = \underbrace{1 \cdot p^2(1-p)^2}_{0101} + \underbrace{2 \cdot p^3(1-p)^{4-3=1}}_{1011, 1110} = p^2 - p^4$$

2.6 Exercises

Exercise 5.1. is the binary $(11, 24, 5)$ -code linear?

Proof. recall: a q -ary linear $[n, k, d]$ -code is also a q -ary (n, q^k, d) -code, but the opposite is not always true.

$\implies$ $(11, 24, 5)$ -code to be linear it would mean that $24 = q^k$.

Since it is binary, $q = 2$. But $24 \neq 2^k$, so it can not be linear. $\square$

Exercise 5.2. E_n is the code of all even-weight vectors of $V(n, 2)$, which is linear. What are the parameters $[n, k, d]$ of E_n ? Write a GM for E_n in standard form.

Proof.

$$E_n = \{x \in V(n, 2) | w(x) \text{ is even}\}$$

$\longrightarrow$ is the binary even-weight code (the single parity-check code);
it's linear since

- the zero vector has even weight
- over $GF(2)$, the sum of two even-weight vectors has even weight

Recall: $F_q^n \iff V(n, q)$, so $V(n, 2) \cong F_2^n$

$$\implies E_n = \{(x_1, \dots, x_n) \in F_2^n | x_1 + \dots + x_n = 0\}$$

minimum distance is 2, since

- no word of weight 1 is in E_n
- words of weight 2 are in E_n

Therefore, parameters are $[n, n-1, 2]$

GM:

$$G = [I_{n-1} | 1]$$

which generates vectors of the form

$$(a_1, \dots, a_{n-1}, a_1 + \dots + a_{n-1})$$

$\square$

Exercise 5.5. Prove that in a *binary linear code*, either all the codewords have even weight or exactly half have even weight and half odd weight.

Proof. let C_e , C_o be subsets of C with even and odd weights respectively.

So that $C = C_e \cup C_o$ (disjoint union).

For binary vectors x, y :

$$w(x + y) = w(x) + w(y) \pmod{2}$$

ie. over F_2 , the parity of the weight is additive:

$$even + even = even$$

$$even + odd = odd$$

$$odd + odd = even$$

Now we have two possible cases:

- C has no odd weighted codewords:
 $C_o = \emptyset$, $\forall x \in C$ x is even weighted
- C has at least one odd-weighted codeword:
let $u \in C_o$, consider the map

$$\begin{aligned} \phi : C_e &\longrightarrow C_o \\ c &\longmapsto c + u \end{aligned}$$

with $c \in C_e$, $u \in C_o$, $\phi(c) \in C_o$.

ϕ is bijective, since $\phi(\phi(c)) = (c + u) + u = c$,

so ϕ is its own inverse; hence $|C_e| = |C_o|$.

Since $C = C_e \cup C_o$, half codewords are even weighted and half odd.

□

Exercise 6.1. construct standard arrays for codes having each of the GMs:

$$G_1 = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} \quad G_2 = \begin{pmatrix} 1 & 0 & 1 \\ 0 & 1 & 1 \end{pmatrix}$$

Proof. recall: for a binary code with GM G , the code C consists of all binary linear combinations of the rows of G .

For G_1 :

rows: $r_1 = (1, 0)$, $r_2 = (0, 1)$. A codeword is any linear combination:

$$uG_1 = a \cdot r_1 + b \cdot r_2, \quad \text{with } a, b \in \{0, 1\}$$

4 combinations:

$$0 \cdot r_1 + 0 \cdot r_2 = (0, 0)$$

$$1 \cdot r_1 + 0 \cdot r_2 = (1, 0)$$

$$0 \cdot r_1 + 1 \cdot r_2 = (0, 1)$$

$$1 \cdot r_1 + 1 \cdot r_2 = (1, 0) + (0, 1) = (1, 1)$$

$$\implies C_1 = \{00, 10, 01, 11\}$$

standard array: 00 01 10 11

For G_2 :

rows: $r_1 = (1, 0, 1)$, $r_2 = (0, 1, 1)$. Codeword: $a \cdot r_1 + b \cdot r_2$ with $a, b \in \{0, 1\}$.

4 combinations:

$$\begin{aligned} 0 \cdot r_1 + 0 \cdot r_2 &= (0, 0, 0) \\ 1 \cdot r_1 + 0 \cdot r_2 &= (1, 0, 1) \\ 0 \cdot r_1 + 1 \cdot r_2 &= (0, 1, 1) \\ 1 \cdot r_1 + 1 \cdot r_2 &= (1, 0, 1) + (0, 1, 1) = (1, 1, 0) \end{aligned}$$

$$\implies C_2 = \{000, 101, 011, 110\}$$

$\implies$ so the 1st row of the standard array is: 000 101 011 110.

Now, pick a non used vector: 001, add it to the code C_2 :

$$\begin{aligned} 001 + C_{2_i} \\ 001 + 000 &= 001 \\ 001 + 101 &= 100 \\ 001 + 011 &= 010 \\ 001 + 110 &= 111 \end{aligned}$$

$\implies$ 2nd row of the standard array: 001 100 010 111

Thus the standard array is

$$\begin{array}{cccc} 000 & 101 & 011 & 110 \\ 001 & 100 & 010 & 111 \end{array}$$

ie. $2^3 = 8$ vectors, a $V(3, 2)$ vector space. □

Exercise 6.4. C a binary $[n, k]$ -code with minimum distance $2t + 1$ (or $2t + 2$). Given that p is very small, show that an approximate value of $P_{err}(C)$ is $\left(\binom{n}{t+1} - \alpha_{t+1}\right) p^{t+1}$, where α_{t+1} is the number of coset leaders of C of weight $t + 1$.

Proof. From 6.9, if $d(C) = 2t + 1$ (or $2t + 2$) $\implies C$ can correct any t errors.

Hence every vector of weight $\leq t$ is a coset leader and so $\alpha_i = \binom{n}{i}$ for $0 \leq i \leq t$.

$$P_{corr}(C) = \sum_{i=0}^n \alpha_i \cdot p^i (1-p)^{n-i} \quad (1)$$

where α_i is the number of coset leaders of weight i

From the $\binom{n}{i}$ vectors of weight i , exactly α_i are coset leaders, so the non coset leaders are $\binom{n}{i} - \alpha_i$. This is when a decoding error happens.

$$\implies P_{err}(C) = \sum_{i=0}^n \left(\binom{n}{i} - \alpha_i \right) p^i (1-p)^{n-i}$$

Alternatively from 1:

$$P_{err}(C) = 1 - P_{corr}(C) = 1 - \sum_{i=0}^n \alpha_i \cdot p^i (1-p)^{n-i}$$

Notice that

$$\sum_{i=0}^n \binom{n}{i} p^i (1-p)^{n-i} = (p + (1-p))^n = 1^n = 1$$

thus

$$\begin{aligned} P_{err}(C) &= \sum_{i=0}^n \binom{n}{i} p^i (1-p)^{n-i} - \sum_{i=0}^n \alpha_i \cdot p^i (1-p)^{n-i} \\ &= \sum_{i=0}^n \left(\binom{n}{i} - \alpha_i \right) p^i (1-p)^{n-i} \end{aligned}$$

Now, from 6.9, $\forall i \leq t$, $\alpha_i = \binom{n}{i}$, thus $\binom{n}{i} - \alpha_i = 0$ for the first t terms in the sum.

Thus

$$\begin{aligned} P_{err}(C) &= \sum_{i=0}^n \left(\binom{n}{i} - \alpha_i \right) p^i (1-p)^{n-i} \\ &= \left(\binom{n}{t+1} - \alpha_{t+1} \right) p^{t+1} (1-p)^{n-t-1} + \dots \end{aligned}$$

where the $\dots$ represent the terms with p^{t+2} and higher.

Then, since p is very small (by the exercise definition), $(1-p)^{n-t-1} \equiv 1$, and the other higher powers of p are negligible.

Hence,

$$P_{err}(C) = \left(\binom{n}{t+1} - \alpha_{t+1} \right) \cdot p^{t+1}$$

□

3 Dual code, PCM and Syndrome

3.1 Dual code

Definition (Orthogonal). Inner product:

$$u \cdot v = u_1v_1 + \dots + u_nv_n = \sum_{i=1}^n u_iv_i$$

If $u \cdot v = 0$, then u and v are called *orthogonal*.

Lemma 7.1. for any $u, v, w \in V(n, q)$ and $\lambda, \mu \in GF(q)$,

- i. $u \cdot v = v \cdot u$
- ii. $(\lambda u + \mu v) \cdot w = \lambda(u \cdot w) + \mu(v \cdot w)$

Proof. (at exercise 7.1). □

Definition (Dual code). given a linear $[n, k]$ -code C , the *dual code* of C , denoted $C^\perp$, is defined to be the set of those vectors of $V(n, q)$ which are orthogonal to every codeword of C . ie.

$$C^\perp = \{v \in V(n, q) \mid v \cdot u = 0 \forall u \in C\}$$

Lemma 7.2. C a $[n, k]$ -code with GM G . Then $v \in V(n, q)$ belongs to $C^\perp$ iff v is orthogonal to every row of G , ie.

$$v \in C^\perp \iff v \cdot G^T = 0$$

Proof. let rows of G be $r_1, \dots, r_k$, suppose $v \cdot r_i = 0 \forall i$ (ie. v orthogonal to every row of G).

If $u \in C$ (ie. a codeword of C), then $u = \sum_{i=1}^k \lambda_i r_i$ for some scalars λ_i , so that

$$v \cdot u = v \cdot \sum_{i=1}^k \lambda_i r_i = \sum_{i=1}^k \lambda_i \cdot \underbrace{(v \cdot r_i)}_0 = \sum \lambda_i \cdot 0 = 0$$

$\implies$ hence v is orthogonal to every codeword of C , and so is in $C^\perp$. □

Theorem 7.3. C a $[n, k]$ -code over $GF(q)$. Then the dual code $C^\perp$ of C is a linear $[n, n - k]$ -code.

Proof. i. first show that $C^\perp$ is a linear code:

let $v_1, v_2 \in C^\perp$ and $\lambda, \mu \in GF(q)$. Then $\forall u \in C$,

$$(\lambda v_1 + \mu v_2) \cdot u = \lambda(v_1 \cdot u) + \mu(v_2 \cdot u)$$

notice that $v_1, v_2 \in C^\perp$, so

that v_1, v_2 are orthogonal with u

hence $(v_1 \cdot u)$ and $(v_2 \cdot u)$ are 0

$$= \lambda \cdot 0 + \mu \cdot 0 = 0$$

Hence $\lambda \cdot v_1 + \mu \cdot v_2 \in C^\perp$, and so $C^\perp$ is linear, since it is closed under linear combinations.

ii. Next, show that $C^\perp$ has dimension $n - k$:

Let $G = [g_{ij}]$ be a GM of C .

Then by Lemma 7.2, the elements of $C^\perp$ are the vectors $v = (v_1, v_2, \dots, v_n)$, since $v \in C^\perp \iff v \cdot G^T = 0$, satisfying

$$\sum_{j=1}^m g_{ij} v_j = 0, \forall i = [k]$$

$\longrightarrow$ this is a system of k independent homogeneous equations in n unknowns, with solution space $C^\perp$. From linear algebra we know that it has dimension $n - k$. To see it:

if codes C_1 and C_2 are equivalent, then $C_1^\perp$, $C_2^\perp$ are also equivalent. Hence is enough to show that $\dim(C^\perp) = n - k$, where C is a standard form GM:

$$C = \begin{pmatrix} 1 & \dots & 0 & a_{1,1} & \dots & a_{1,n-k} \\ \vdots & & \vdots & \vdots & & \vdots \\ 0 & \dots & 1 & a_{k,1} & \dots & a_{k,n-k} \end{pmatrix}$$

Then

$$C^\perp = \{(v_1, \dots, v_n) \in V(n, q) \mid v_i + \sum_{j=1}^{n-k} a_{i,j} v_{k+j} = 0, i = 1, 2, \dots, k\}$$

For each of the q^{n-k} choices of $(v_{k+1}, \dots, v_n)$, $\exists! (v_1, v_2, \dots, v_k) \in C^\perp$.

Hence $|C^\perp| = q^{n-k}$, therefore $\dim(C^\perp) = n - k$. □

Theorem 7.5. for any $[n, k]$ -code C , $(C^\perp)^\perp = C$.

Proof. clearly $C \subseteq (C^\perp)^\perp$, since every vector in C is orthogonal to every vector in $C^\perp$.

But $\dim((C^\perp)^\perp) = n - (n - k) = k = \dim(C)$, therefore $C = (C^\perp)^\perp$. □

3.2 PCM (parity-check matrix)

Definition (PCM). A *parity-check matrix* (PCM) H for a $[n, k]$ -code C is a generator matrix of $C^\perp$.

$\implies H$ is a $(n - k) \times n$ matrix satisfying $GH^T = 0$.

From 7.2 and 7.5,
if H a PCM of C , then

$$C = \{x \in V(n, q) \mid xH^T = 0\}$$

$\implies$ Any linear code is completely specified by a PCM.

Intuition . i. PCM: G specifies how to build a codeword, the PCM H specifies the rules a vector must follow to be considered a valid codeword.

ii. dual-code: orthogonal "shadow", see C as a plane through 3D origin; $C^\perp$ is the (normal vector) line emerging from the plane.

Rows of the PCM are the basis for the dual-code $C^\perp \implies$ ie. the rules that define C are themselves a code.

Theorem 7.6. if $G = [I_k | A]$ is the standard form generator matrix of an $[n, k]$ -code C , then a PCM for C is $H = [-A^T \mid I_{n-k}]$.

eg.

$$G = \begin{bmatrix} 1 & \dots & 0 & a_{1,1} & \dots & a_{1,n-k} \\ \vdots & & \vdots & \vdots & & \vdots \\ 0 & \dots & 1 & a_{k,1} & \dots & a_{k,n-k} \end{bmatrix}$$

$$H = \begin{bmatrix} -a_{1,1} & \dots & -a_{1,n-k} & 1 & \dots & 0 \\ \vdots & & \vdots & \vdots & & \vdots \\ -a_{k,1} & \dots & -a_{k,n-k} & 0 & \dots & 1 \end{bmatrix}$$

which, in binary, the minus signs are unnecessary.

Definition (Standard form). a PCM that is $H = [B \mid I_{n-k}]$

3.3 Syndrome

Definition (Syndrome). let H a PCM of a $[n, k]$ -code C .

Then $\forall y \in V(n, q)$, the $1 \times (n - k)$ row vector

$$S(y) = yH^T$$

is called the *syndrome* of y .

Remark . i. for $h_1, h_2, \dots, h_{n-k}$ being rows of H , then

$$S(y) = (y \cdot h_1, y \cdot h_2, \dots, y \cdot h_{n-k})$$

ii. $S(y) = 0 \iff y \in C$

Intuition . Syndrome is the "symptom" of the error. It ignores the valid part of the message and isolates the noise.

$$S(y) = yH^T = (c + e)H^T = \underbrace{cH^T}_0 + eH^T = 0 + eH^T = eH^T$$

Syndrome allows the receiver to identify what went wrong without knowing what was originally sent.

Lemma 7.8. two vectors u, v are the same coset of C iff they have the same syndrome.

Proof. if u, v in the same coset of C

$$\begin{aligned} \implies u + C &= v + C \\ \implies u - v &\in C \\ \implies (u - v)H^T &= 0 \\ \implies uH^T &= vH^T \\ \implies S(u) &= S(v) \end{aligned}$$

□

Corollary 7.9. There is a one-to-one correspondence between cosets and syndromes.

→ for small n , it's fast to locate the received vector y in the array, but for large n : use syndrome to find which coset (ie. which row of the array) contains y .

Example 7.10. (from example 6.5)

$$G = \begin{bmatrix} 1 & 0 & 1 & 1 \\ 0 & 1 & 0 & 1 \end{bmatrix}$$

by 7.6,

$$H = \begin{bmatrix} 1 & 0 & 1 & 0 \\ 1 & 1 & 0 & 1 \end{bmatrix}$$

Hence the syndromes of the coset leaders are

$$\begin{aligned} S(0000) &= 00 \\ S(1000) &= 11 \\ S(0100) &= 01 \\ S(0010) &= 10 \end{aligned}$$

The standard array becomes:

<i>coset leaders</i>				<i>syndromes</i>
0000	1011	0101	1110	00
1000	0011	1101	0110	11
0100	1111	0001	1010	01
0010	1001	0111	1100	10

so, decoding algorithm: when a vector y is received, calculate $S(y) = yH^T$, locate $S(y)$ in the *syndromes* column of the array.

Locate y in the corresponding row and decode as the codeword at the top of the column containing y .

→ in practice: *syndrome lookup table*:

syndrome z	coset leader $f(z)$
00	0000
11	1000
01	0100
10	0010

decoding procedure:

1. receive y , calculate $S(y) = yH^T$
2. let $z = S(y)$, locate z in the first column of the lookup table
3. decode y as $y - f(z)$

3.4 Incomplete decoding

For $d(C) = 2t + 1$ (or $2t + 2$), guarantee the correction of $\leq t$ errors in any codeword and also detect some cases of more than t errors.

→ Arrange the cosets in order of increasing weight of the coset leaders.

Divide the array into a top part and a bottom part; top: cosets whose leaders have weights $\leq t$.

- If y in top part: decode as usual (assuming $\leq t$ errors).
- If y in bottom part: conclude that $> t$ errors have occurred, ask for retransmission.

3.5 Exercises

Exercise 7.1. prove Lemma 7.1

Proof. For any $u, v, w \in V(n, q)$ and $\lambda, \mu \in GF(q)$,

- i. $u \cdot v = v \cdot u$

$$u \cdot v = \sum_{i=1}^n u_i \cdot v_i = \sum_{i=1}^n v_i \cdot u_i = v \cdot u$$

ii. $(\lambda u + \mu v) \cdot w = \lambda(u \cdot w) + \mu(v \cdot w)$

$$\begin{aligned}
(\lambda u + \mu v)w &= \sum (\lambda u_i + \mu v_i)w_i \\
&= \sum (\lambda u_i w_i + \mu v_i w_i) \\
&= \sum (\lambda u_i w_i) + \sum (\mu v_i w_i) \\
&= \lambda \sum (u_i w_i) + \mu \sum (v_i w_i) \\
&= \lambda \cdot (u \cdot w) + \mu \cdot (v \cdot w)
\end{aligned}$$

□

Exercise 7.2. prove that if E_n is the binary even weight code of length n , then $E_n^\perp$ is the repetition code of length n .

Proof. from exercise 5.2:

$$E_n = \{x \in V(n, 2) \mid w(x) \text{ is even}\} = \{(x_1, \dots, x_n) \in F_2^n \mid x_1 + \dots + x_n = 0\}$$

GM of E_n :

$$G = \left[I_{n-1} \mid \begin{array}{c} 1 \\ \vdots \\ 1 \end{array} \right]$$

thus, by 7.6, PCM is $H = [1 \ 1 \ \dots \ 1]$.

If H is a PCM for C , then the rows of H generate $C^\perp$.

Therefore

$$E_n^\perp = \langle \underbrace{[1 \ 1 \ \dots \ 1]}_{\text{generator}} \rangle$$

then it's codewords are:

$$0 \cdot (1, \dots, 1) = (0, \dots, 0)$$

$$1 \cdot (1, \dots, 1) = (1, \dots, 1)$$

$$\implies E_n^\perp = \{00 \dots 00, 11 \dots 1\}$$

ie. the repetition code of length n .

□

Exercise 7.4. for a binary linear code with PCM H , show that the transpose of the syndrome of a received vector is equal to the sums of those columns of H corresponding to where the errors occurred.

Proof. Let e the error, y the vector received, and x the original codeword. Then $y = x + e$.

Then

$$S(y) = yH^T = (x + e)H^T = \underbrace{xH^T}_{\substack{0, \text{ since } H \\ \text{is PCM of } C \\ \text{and } x \in C}} + eH^T = eH^T$$

So,

$$S(y)^T = e^T H = \sum_{j=1}^n e_j \cdot H_j$$

where H_j is the j -th column of H . □

Exercise 7.6. Let C be the ternary linear code with GM

$$G = \begin{bmatrix} 1 & 1 & 1 & 0 \\ 2 & 0 & 1 & 1 \end{bmatrix}$$

- (a) Find a generator matrix in standard form.
- (b) Find a parity check matrix (PCM) for C in standard form.
- (c) Use syndrome decoding to decode the received vectors: 2122, 1201, 2222

Proof. (a)

$$\begin{bmatrix} 1 & 1 & 1 & 0 \\ 2 & 0 & 1 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 1 & 1 & 0 \\ 0 & 1 & 2 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 0 & 2 & 2 \\ 0 & 1 & 2 & 1 \end{bmatrix}$$

thus $G = \begin{bmatrix} 1 & 0 & 2 & 2 \\ 0 & 1 & 2 & 1 \end{bmatrix}$ is PCM in standard form.

- (b) since $G = \begin{bmatrix} 1 & 0 & 2 & 2 \\ 0 & 1 & 2 & 1 \end{bmatrix}$ then

$$H = \begin{bmatrix} -2 & -2 & 1 & 0 \\ -2 & -1 & 0 & 1 \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 & 0 \\ 1 & 2 & 0 & 1 \end{bmatrix}$$

- (c)

$$S(y) = yH^T = S(y) = (y \cdot h_1, y \cdot h_2).$$

w/ h_i the rows of H .

compute the lookup table (syndrome table):

e	$S(e)$
0000	00
1000	11
2000	22
0100	12
0200	21
0010	10
0020	20
0001	01
0002	02

left: weight-1 errors, since we're over F_3 ; right: coset leaders for the 9 cosets.

i. $y = 2121$:

$$S(y) = \begin{bmatrix} 2 & 1 & 2 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & 2 \\ 1 & 0 \\ 0 & 1 \end{bmatrix} = [5, 5] \equiv [2, 2].$$

$S(y) = [2, 2]$, corresponds (in the table) to $e = 2000$.

$$\implies c = y - e = 2121 - 2000 = 0121$$

ii. $y = 1201$

$$S(y) = \begin{bmatrix} 1 & 2 & 0 & 1 \end{bmatrix} H^T = [3, 6] = [0, 0].$$

corresponds to $e = 0000$

$$\implies c = y - e = 1201$$

iii. $y = 2222$

$$S(y) = \begin{bmatrix} 2 & 2 & 2 & 2 \end{bmatrix} H^T = [6, 8] = [0, 2].$$

corresponds to $e = 0002$

$$\implies c = y - e = 2222 - 0002 = 2220$$

□

4 Hamming Codes

Definition (Binary Hamming Code). let r a positive integer, H a $r \times (2^r - 1)$ matrix whose columns are the distinct non-zero vectors of $V(r, 2)$.

The code having H as its PCM is called a *binary Hamming code*, denoted $Ham(r, 2)$.

Remark . $Ham(r, 2)$ has length $n = 2^r - 1$ and dimension $k = n - r$.

Redundancy of the code: $r = n - k$, the number of check symbols in each codeword.

Exercise 8.1. i. $r = 2$: $H = \begin{bmatrix} 1 & 1 & 0 \\ 1 & 0 & 1 \end{bmatrix}$

by Theorem 7.6, $G = \begin{bmatrix} 1 & 1 & \underbrace{1}_I \end{bmatrix}$

so $Ham(2, 2)$ is just the binary triple repetition code.

ii. $r = 3$: a PCM for $Ham(3, 2)$ is

$$H = \begin{bmatrix} 0 & 0 & 0 & 1 & 1 & 1 & 1 \\ 0 & 1 & 1 & 0 & 0 & 1 & 1 \\ 1 & 0 & 1 & 0 & 1 & 0 & 1 \end{bmatrix}$$

(have taken columns in the natural order of increasing binary numbers from 1 to 7)

H in standard form: rearrange columns:

$$H = \begin{bmatrix} 0 & 1 & 1 & 1 & 1 & 0 & 0 \\ 1 & 0 & 1 & 1 & 0 & 1 & 0 \\ 1 & 1 & 0 & 1 & 0 & 0 & 1 \end{bmatrix}$$

by Theorem 7.6, a generator matrix for $Ham(3, 2)$ is

$$G = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 1 & 1 \\ 0 & 1 & 0 & 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 0 & 1 & 1 & 0 \\ 0 & 0 & 0 & 1 & 1 & 1 & 1 \end{bmatrix}$$

Theorem 8.2. the binary Hamming code $Ham(r, 2)$, for $r \geq 2$,

1. is a $[2^r - 1, 2^r - 1 - r]$ -code
2. has minimum distance 3 (hence is single-error-correcting)
3. is a *perfect code*

Lemma (Decoding with a binary Hamming code). $Ham(r, 2)$ is a perfect single-error-correcting code $\implies$ the coset leader are precisely the 2^r ($= n + 1$) vectors of $V(n, 2)$ of weight ≤ 1 .

Let j -th column of H be the binary representation of j . Decoding algorithm:

1. receive vector y , calculate its syndrome: $S(y) = yH^T$
2. if $S(y) = 0$, assume $y = c$ (original sent codeword)
3. if $S(y) \neq 0$, assuming a single error, $S(y)$ gives the binary representation of the error position, and the error can be corrected.

Example . $H = \begin{bmatrix} 0 & 0 & 0 & 1 & 1 & 1 & 1 \\ 0 & 1 & 1 & 0 & 0 & 1 & 1 \\ 1 & 0 & 1 & 0 & 1 & 0 & 1 \end{bmatrix}$, if $y = 1101011$ then

$$S(y) = y \cdot H^T = 110$$

$\implies$ 6-th position, and so we decode y as 1101001

4.1 Extended binary Hamming codes

$\hat{Ham}(r, 2)$, obtained from $Ham(r, 2)$ by adding an overall parity-check.

Not ideal for complete decoding, but good for incomplete decoding (correct any single error and detect any double error).

Let H be a PCM for $Ham(r, 2)$. A PCM $\hat{H}$ for $\hat{Ham}(r, 2)$:

$$\hat{H} = \begin{bmatrix} & & & 0 \\ & H & & \vdots \\ & & & 0 \\ 1 & \cdots & 1 & 1 \end{bmatrix}$$

If H is taken with columns in increasing order of binary numbers, we have a neat incomplete decoding algorithm:

Example 8.3. $r = 3$, $\hat{Ham}(3, 2)$. Received y , $S(y) = y\hat{H}^T = (s_1, s_2, s_3, s_4)$

- i. if $s_4 = 0$ and $(s_1, s_2, s_3) = 0$: assume no errors
- ii. if $s_4 = 0$ and $(s_1, s_2, s_3) \neq 0$: assume ≥ 2 errors and ask retransmission
- iii. if $s_4 = 1$ and $(s_1, s_2, s_3) = 0$: assume 1 error in the last position
- iv. if $s_4 = 1$ and $(s_1, s_2, s_3) \neq 0$: assume 1 error in the j -th position, where j is the number binary-represented by (s_1, s_2, s_3)

Theorem 8.4. suppose C a linear $[n, k]$ -code over $GF(q)$ with PCM H . Minimum distance of C is d iff any $d - 1$ columns of H are linearly independent but some d columns are linearly dependent.

Proof. by 5.2, min. distance of C (ie. $d(C)$) = smallest of the weights of the non-zero codewords.

Let $x = x_1x_2 \dots x_n \in V(n, q)$, then

$$\begin{aligned} x \in C &\iff xH^T = 0 \\ &\iff x_1H_1 + x_2H_2 + \dots + x_nH_n = 0 \end{aligned}$$

where H_i denote the columns of H .

$\implies$ each codeword x of weight d corresponds with a set of d linearly dependent columns of H .

On the other hand, if $\exists$ a set of $d - 1$ lin.dependent columns of H , say $H_{i_1}, H_{i_2}, \dots, H_{i_{d-1}}$, then $\exists x_{i_1}, \dots, x_{i_{d-1}}$ scalars, not all zero, such that

$$x_{i_1}H_{i_1} + x_{i_2}H_{i_2} + \dots + x_{i_{d-1}}H_{i_{d-1}} = 0$$

But then, the vector

$$x = (0 \dots 0x_{i_1}0 \dots x_{i_2}0 \dots 0x_{i_{d-1}}0 \dots 0)$$

having x_{i_j} in the j -th position for $j \in [d-1]$, would satisfy $xH^T = 0$, and so would be a non-zero codeword of weight $< d$. $\square$

4.2 q-ary Hamming codes

For C a linear code with $d(C) = 3$ (min.dist), any 2 columns of a PCM H must be linearly independent

$\implies$ columns of H must be non-zero, and no column can be a scalar multiple of another

Any $0 \neq v \in V(r, q)$ vector has $q-1$ non-zero scalar multiples, forming the set

$$\{\lambda v \mid \lambda \in GF(q), \lambda \neq 0\}$$

$\longrightarrow$ the $q^r - 1$ non-zero vectors of $V(r, q)$ may be partitioned into $\frac{q^r - 1}{q - 1}$ such sets, called *classes*.

$\longrightarrow$ two vectors are scalar multiples of each other if they are in the same class

By choosing one vector from each class, obtain a set of $\frac{q^r - 1}{q - 1}$ vectors, where not two are linearly dependent.

By Theorem 8.4, taking these as columns of h gives a PCM for a

$$\left[\frac{q^r - 1}{q - 1}, \frac{q^r - 1}{(q - 1) - r}, 3 \right] \text{-code}$$

$\implies$ called *q-ary Hamming code*, $Ham(r, q)$.

$\longrightarrow$ PCM is unique up to permutation of columns

$\implies$ Hamming codes are linear codes

Theorem 8.6. $Ham(r, q)$ is a perfect single-error-correcting code.

Proof. $Ham(r, q)$ is constructed to be a $(n, M, 3)$ -code, with $n = \frac{q^r - 1}{q - 1}$ and $M = q^{n-r}$.

With $t = 1$, the LHS of the sphere-packing bound becomes

$$q^{n-r} \cdot (1 + n(q - 1)) = q^{n-r} \cdot (1 + q^r - 1) = q^n$$

which is the RHS, so $Ham(r, q)$ is a perfect code. $\square$

Decoding q-ary Hamming code Since Ham is perfect single-error correcting code, the coset leaders, other than 0, are the vectors of weight 1.

Syndrome of such coset leader:

$$S(0 \dots 0 b 0 \dots 0) = (0 \dots 0 b 0 \dots 0) \cdot H^T = b \cdot H_j^T$$

where H_j is the j -th column of H , and b is at the j -th position of y .

Decode:

- given received y , calculate $S(y) = yH^T$
- if $S(y) = 0$, assume no errors
- if $S(y) \neq 0$, then $S(y) = b \cdot H_j^T$ for some b and j
correct by: subtract b from the j -th entry of y .

Example:

$$q = 5, H = \begin{bmatrix} 0 & 1 & 1 & 1 & 1 & 1 \\ 1 & 0 & 1 & 2 & 3 & 4 \end{bmatrix}, y = 203031$$

Then,

$$\begin{aligned} S(y) &= y \cdot H^T = 2 \cdot H_1^T + 3 \cdot H_3^T + 3 \cdot H_5^T + 1 \cdot H_6^T \\ &= 2 \cdot [0 \ 1] + 3 \cdot [1 \ 1] + 3 \cdot [1 \ 3] + 1 \cdot [1 \ 4] \\ &= [0 \ 2] + [3 \ 3] + [3 \ 9] + [1 \ 4] \\ &= [7 \ 8] = [2 \ 3] = \underbrace{2}_b \cdot \underbrace{[1 \ 4]}_{H_6^T} \pmod{5} \end{aligned}$$

$\Rightarrow$ error is in position 6-th, with magnitude $b = 2$
 $\Rightarrow$ subtract b from the j -th entry of y : $1 - 2 \pmod{5} = -1 \pmod{5} = 4$,
therefore $y' = 203034$.

5 MLCT - Main Linear Coding Theory problem

A good (n, M, d) -code has

- small n , for fast transmission of messages
- large M , to enable transmission of a wide variety of messages
- large d , to correct many errors

Denote by $A_q(n, d)$ the largest M such that $\exists$ a q -ary (n, M, d) -code.

Theorem 2.7. Suppose d is odd. Then a binary (n, M, d) -code exists iff a binary $(n + 1, M, d + 1)$ -code exists.

Proof.

□

Corollary 2.8. If d is odd, then $A_2(n + 1, d + 1) = A_2(n, d)$.

Equivalently, if d is even, then $A_2(n, d) = A_2(n - 1, d - 1)$.

Definition (Sphere). $\forall u \in F_q^n$ (vector) and any integer $r \geq 0$, the *sphere* of radius r and centre u , denoted $S(u, r)$, is the set


$$\{v \in F_q^n \mid d(u, v) \leq r\}$$

Theorem 1.9 & 2.12. a code C can

- i. detect up to s errors in any codeword if $d(C) \geq s + 1$
- ii. correct up to t errors in any codeword if $d(C) \geq 2t + 1$

This is, the spheres of radius t centered on the codewords of C are disjoint (ie. have no overlap).

So, if $\leq t$ errors occur, then the received vector y may be different from the sent codeword x , hence being different from the centre of the sphere $S(x, t)$, but can not 'escape' from the sphere, so is 'drawn back' to x by nearest neighbour decoding.



Definition (Perfect codes). A code which achieves the sphere-packing bound is called a *perfect code*. Thus, for a perfect t -error-correcting code, the M spheres of radius t centred on codewords 'fill' the whole space F_q^n without overlapping.

In other words, every vector in F_q^n is at distance $\leq t$ from exactly one codeword.

Theorem (MLCT problem (Version 1)). For given length n , find the maximum dimension k such that $\exists$ an $[n, k, d]$ -code over $GF(q)$. (Then, for this k , $B_q(n, d) = q^k$).

Remark . *redundancy* r of an $[n, k, d]$ -code is just $r = n - k$ (the number of check symbols in a codeword).

Theorem (MLCT problem (Version 2)). For given redundancy r , find the maximum length n such that $\exists$ an $[n, n - r, d]$ -code over $GF(q)$.

Definition $((n, s)$ -set). a (n, s) -set in $V(r, q)$ is a set of n vectors in $V(r, q)$ with the property that any s of them are linearly independent.

Denote $max_s(r, q)$ the largest value of n for which $\exists$ a (n, s) -set in $V(r, q)$. ie.

- (n, s) -set: n vectors with s of them lin. independent

- $max_s(r, q)$: max n for which $\exists (n, s)$ -set

Definition (Packing problem). The *packing problem* for $V(r, q)$ is that of determining the values of $max_s(r, q)$ and the optimal (n, s) -sets.

Theorem 14.1. There exists an $[n, n - r, d]$ -code over $GF(q)$ iff $\exists$ an $(n, d - 1)$ -set in $V(r, q)$.

Proof. let C a $[n, n - r, d]$ -code over $GF(q)$ with PCM H . Then by Theorem 8.4, the columns of H form a $(n, d - 1)$ -set in $V(r, q)$.

On the other hand, let K a $(n, d - 1)$ -set in $V(r, q)$. If we form a $r \times n$ matrix H with the vectors of K as its columns, by Theorem 8.4, H is the PCM of a $[n, n - r]$ -code whose minimum distance is at least d . $\square$

Corollary 14.2. for given values q, d, r , the largest value of n for which there exists a $[n, n - r, d]$ -code over $GF(q)$ is $max_{d-1}(r, q)$.

$\implies$ the MLCT problem (V2) is the same as the packing problem of finding $max_{d-1}(r, q)$.

5.1 The projective geometry $PG(r-1, q)$

Let the vector space

$$V(r, q) = \{(a_1, a_2, \dots, a_r) \mid a_i \in GF(q)\}$$

Definition (Projective Geometry). $PG(r - 1, q)$

- *points* are the one-dimensional subspaces of $V(r, q)$
- *lines* are the two-dimensional subspaces of $V(r, q)$

Each point $P \in PG(r - 1, q)$, as a subspace of $V(r, q)$ of dimension 1, is generated by a single non-zero vector.

So if $a = (a_1, a_2, \dots, a_r) \in P$, then $P = \{\lambda a \mid \lambda \in GF(q)\}$.

$\implies$ for $a = (a_1, a_2, \dots, a_r)$, $b = (b_1, b_2, \dots, b_r) \in P$, then

$$a = b \text{ in } PG(r - 1, q) \text{ iff } a = \lambda b \text{ in } V(r, q)$$

for some non-zero scalar λ .

Lemma 14.6. in $PG(r - 1, q)$,

1. number of points is $\frac{q^r - 1}{q - 1}$
2. any two points lie on exactly one line
3. each line contains exactly $q + 1$ points
4. each point lies on $\frac{q^{r-1} - 1}{q - 1}$ lines

Proof. 1. number of points is $\frac{q^r-1}{q-1}$:

since each of the $q^r - 1$ nonzero vectors in $V(r, q)$ has $q - 1$ nonzero scalar multiples, the number of points of $PG(r - 1, q)$ is $\frac{q^r-1}{q-1}$

2. any two points lie on exactly one line:

if a, b distinct points of $PG(r - 1, q)$, then the unique line through them consists of the points $\lambda a + \mu b$, where λ, μ are scalars not both zero.

3. each line contains exactly $q + 1$ points:

in (ii) there are $q^2 - 1$ choices for the pair (λ, μ) , but we're identifying scalar multiples, so the number of distinct points on the line is

$$\frac{q^2 - 1}{q - 1} = q + 1$$

4. each point lies on $\frac{q^{r-1}-1}{q-1}$ lines:

let t be the number of lines on which a point P lies. Let the set

$$X = \{(Q, L) \mid Q \text{ is a point } \neq P, L \text{ is a line containing both } P \text{ and } Q\}$$

Count the members of X in two ways:

for each of the $\frac{q^r-1}{q-1} - 1$ choices of Q , $\exists!$ line containing P and Q . Thus,

$$|X| = \frac{q^r - 1}{q - 1} - 1 = \frac{q^r - q}{q - 1}$$

On the other hand, for each of the t lines through P , there are (by (iii)) q points Q other than P lying on L .

Thus, $|X| = tq$,

$$\implies tq = \frac{q^r - q}{q - 1}, \quad \implies t = \frac{q^{r-1} - 1}{q - 1}$$

□

Definition (Projective plane). The $PG(2, q)$ is called the *projective plane* over $GF(q)$.

6 MDS Codes

Theorem 15.1. a $[n, n - r, d]$ -code satisfies $d \leq r + 1$.

Proof. let C a $[n, n - r, d]$ -code, let $G = [I_{n-r} \mid A]$ be a standard form GM of C .

Since A has r columns, the codewords which are rows of G have weight $\leq r + 1$, ie. $w(C) \leq r + 1$.

The result follows from Theorem 5.2,

$$\begin{aligned} \implies w(C) &= d(C) \\ \implies d(C) &\leq r + 1. \end{aligned}$$

□

Definition (MDS). a $[n, n - r, r + 1]$ -code,

ie. a linear code of redundancy r whose min. distance is $r + 1$,
is called a *maximum distance separable code*, MDS.

→ by Theorem 14.1, max length of a MDS code over $GF(q)$ is $\max_r(r, q)$,
the largest size of a (n, r) -set in $V(r, q)$.

Conjecture 15.2. if $2 \leq r \leq q$, then $\max_r(r, q) = q + 1$
(except $\max_3(3, q) = \max_{q-1}(q - 1, q) = q + 2$ if $q = 2^h$)

Theorem 15.3. if $r \geq q$, then $\max_r(r, q) = r + 1$. Any MDS code of redundancy
 $r \geq q$ is equivalent to a repetition code of length $r + 1$.

Proof. repetition code of length $r + 1$: a $[r + 1, 1, r + 1]$ -code with GM $[1 \ 1 \ \dots \ 1]$.

Hence $\max_r(r, q) \geq r + 1$.

Also, any $[r + 1, 1, r + 1]$ -code is equivalent to a repetition code.

Suppose $r \geq q$ and by contradiction that $\max_r(r, q) \geq r + 2$.

Then, $\exists$ a $[r + 2, 2, r + 1]$ -code C over $GF(q)$.

→ C must be equivalent to a code having GM:

$$G = \begin{bmatrix} 1 & 0 & 1 & 1 & \dots & 1 \\ 0 & 1 & a_1 & a_2 & \dots & a_r \end{bmatrix}$$

in order that any linear combination of the rows of G has weight at least
 $r + 1$ with $0 \neq a_i \in GF(q)$.

This implies $r \leq q - 1$, contradiction.

□

Remark . the only binary MDS codes are

$V(n, 2)$, the even weighted codes E_n , and repetition codes.

Theorem 15.4. let $2 \leq r \leq q$, let $a_1, a_2, \dots, a_{q-1} \in GF(q)$ nonzero.

Then,

$$H = \begin{bmatrix} 1 & 1 & \dots & 1 & 1 & 0 \\ a_1 & a_2 & \dots & a_{q-1} & 1 & 0 \\ a_1^2 & a_2^2 & \dots & a_{q-1}^2 & 1 & 0 \\ \vdots & \vdots & & \vdots & \vdots & \vdots \\ a_1^{r-1} & a_2^{r-1} & \dots & a_{q-1}^{r-1} & 0 & 1 \end{bmatrix}$$

is the PCM of a MDS $[q + 1, q + 1 - r, r + 1]$ -code.

Equivalently, the columns of H form a $(q + 1)$ -arc in $PG(r - 1, q)$.

Proof. the determinant of a matrix formed by any r columns of H is equal to the determinant of a Vandermonde matrix, and so is non-zero (see a proof of this at section 6.1). Thus any r columns of H are linearly independent. $\square$

Corollary 15.7. The dual code of a MDS code is also MDS.

Corollary 15.8. $\exists$ a MDS $[n, k]$ -code over $GF(q)$ iff $\exists$ a MDS $[n, n - k]$ -code over $GF(q)$.

6.1 Vandermonde determinant

This section contains a simple proof of the Vandermonde matrix determinant. The proof was found in [3], here it is written with small modifications and expanded. A different proof can be found in [4].

Lemma (Vandermonde determinant).

$$\det V(x_1, \dots, x_n) = \det \begin{pmatrix} 1 & x_1 & x_1^2 & \dots & x_1^{n-1} \\ 1 & x_2 & x_2^2 & \dots & x_2^{n-1} \\ 1 & x_3 & x_3^2 & \dots & x_3^{n-1} \\ \vdots & \vdots & \vdots & & \vdots \\ 1 & x_n & x_n^2 & \dots & x_n^{n-1} \end{pmatrix} = \prod_{j < i} (x_i - x_j)$$

Proof. The equation is true for $n = 2$, as we have:

$$\det V(x_1, x_2) = \det \begin{pmatrix} 1 & x_1 \\ 1 & x_2 \end{pmatrix} = x_2 - x_1$$

We now assume that $n \geq 3$. Starting with column n and ending at column 2, we successively apply the following operation: subtract x_1 times column $i - 1$ from column i . The determinant remains the same and the resulting matrix is:

$$\begin{aligned} &= \det \begin{pmatrix} 1 & x_1 - (x_1 \cdot 1) & x_1^2 - (x_1 \cdot x_1) & \dots & x_1^{n-1} - (x_1 \cdot x_1^{n-2}) \\ 1 & x_2 - (x_1 \cdot 1) & x_2^2 - (x_1 \cdot x_2) & \dots & x_2^{n-1} - (x_1 \cdot x_2^{n-2}) \\ 1 & x_3 - (x_1 \cdot 1) & x_3^2 - (x_1 \cdot x_3) & \dots & x_3^{n-1} - (x_1 \cdot x_3^{n-2}) \\ \vdots & \vdots & \vdots & & \vdots \\ 1 & x_n - (x_1 \cdot 1) & x_n^2 - (x_1 \cdot x_n) & \dots & x_n^{n-1} - (x_1 \cdot x_n^{n-2}) \end{pmatrix} \\ &= \det \begin{pmatrix} 1 & 0 & 0 & \dots & 0 \\ 1 & (x_2 - x_1) & x_2(x_2 - x_1) & \dots & x_2^{n-2}(x_2 - x_1) \\ 1 & (x_3 - x_1) & x_3(x_3 - x_1) & \dots & x_3^{n-2}(x_3 - x_1) \\ \vdots & \vdots & \vdots & & \vdots \\ 1 & (x_n - x_1) & x_n(x_n - x_1) & \dots & x_n^{n-2}(x_n - x_1) \end{pmatrix} \end{aligned}$$

Applying the Laplace expansion along the first row and factoring out the scalar multiples $(x_i - x_1)$ in each column, we obtain:

$$= \det \begin{pmatrix} x_2 - x_1 & x_2^2 - x_1 x_2 & x_2^3 - x_1 x_2^2 & \dots & x_2^{n-1} - x_1 x_2^{n-2} \\ x_3 - x_1 & x_3^2 - x_1 x_3 & x_3^3 - x_1 x_3^2 & \dots & x_3^{n-1} - x_1 x_3^{n-2} \\ \vdots & \vdots & \vdots & & \vdots \\ x_n - x_1 & x_n^2 - x_1 x_n & x_n^3 - x_1 x_n^2 & \dots & x_n^{n-1} - x_1 x_n^{n-2} \end{pmatrix}$$

in each row, factor out $(x_i - x_1)$

$$= \det \begin{pmatrix} 1(x_2 - x_1) & x_2(x_2 - x_1) & x_2^2(x_2 - x_1) & \dots & x_2^{n-2}(x_2 - x_1) \\ 1(x_3 - x_1) & x_3(x_3 - x_1) & x_3^2(x_3 - x_1) & \dots & x_3^{n-2}(x_3 - x_1) \\ \vdots & \vdots & \vdots & & \vdots \\ 1(x_n - x_1) & x_n(x_n - x_1) & x_n^2(x_n - x_1) & \dots & x_n^{n-2}(x_n - x_1) \end{pmatrix}$$

$$= \prod_{2 \leq i \leq n} (x_i - x_1) \det \begin{pmatrix} 1 & x_2 & x_2^2 & \dots & x_2^{n-2} \\ 1 & x_3 & x_3^2 & \dots & x_3^{n-2} \\ \vdots & \vdots & \vdots & & \vdots \\ 1 & x_n & x_n^2 & \dots & x_n^{n-2} \end{pmatrix}$$

now, by induction

$$= \prod_{i=2}^n (x_i - x_1) \cdot \prod_{2 \leq j < i \leq n} (x_i - x_j) = \prod_{1 \leq j < i \leq n} (x_i - x_j)$$

□

7 Cyclic Codes

This section contains notes both from Hill [1] and Lint [2] books. Hill's notes are enumerated as $X.Y$ while Lint's notes as $X.Y.Z$.

7.1 Recap on ideals

More about ideals at the *Commutative Algebra notes* [5].

In the cyclic codes context, we're interested in ideals because

- cyclic codes are ideals of $R_n = \mathbb{F}_q[x]/(x^n - 1)$.
- R_n is a PID: every ideal in R_n is principal.

Definition (ideal). $I \subset R$ (R ring) such that $0 \in I$ and $\forall x \in I, r \in R, xr, rx \in I$.

ie. I absorbs products in R .

Definition (prime ideal). if $a, b \in R$ with $ab \in P$ and $P \neq R$ (P a prime ideal), implies $a \in P$ or $b \in P$.

Definition (principal ideal). generated by a single element, (a) .

(a) : principal ideal, the set of all multiples xa with $x \in R$.

Definition (prime spectrum - $\text{Spec}(A)$). set of prime ideals of A . ie.

$$\text{Spec}(A) = \{P \mid P \subset A \text{ is a prime ideal}\}$$

Definition (integral domain). Ring in which the product of any two nonzero elements is nonzero.

ie. no zerodivisors.

ie. $\forall 0 \neq a, 0 \neq b \in A, ab \neq 0 \in A$.

Every field is an integral domain, not the converse.

Definition (principal ideal domain - PID). integral domain in which every ideal is principal. ie. ie. $\forall I \subset R, \exists a \in I$ such that $I = (a) = \{ra \mid r \in R\}$.

7.2 Cyclic Codes intro

Definition (cyclic code). a code C is cyclic if

- i. C is a linear code
- ii. any cyclic shift of a codeword is also a codeword
ie. when $a_0a_1 \dots a_{n-1} \in C$,
then so $a_{n-1}a_0a_1 \dots a_{n-2} \in C$.

Remark (Notation). From now on,

$$F_q = \mathbb{F}_q = GF(q)$$

$F_q[x]$ is a ring; and for $f(x)$ irreducible in $F_q[x]$, then $\frac{F_q[x]}{f(x)}$ is a field.

From now on,

$$f(x) = x^n - 1 \implies F_q[x]/(x^n - 1) = R_n$$

Observe:

since $x^n \cong 1 \pmod{x^n - 1}$, to reduce any polynomial by modulo $x^n - 1$ can just replace x^n by 1, x^{n+1} by x , x^{n+2} by x^2 , etc.

Correspondence:

$$a_0a_1 \dots a_{n-1} \in V(n, q) \iff a(x) = a_0 + a_1x + \dots + a_{n-1}x^{n-1} \in R_n$$

In R_n ,

$$\begin{aligned} x \cdot a(x) &= a_0 \cdot x + a_1x^2 + \dots + \underbrace{a_{n-1}x^n}_{=a_{n-1} \cdot 1} \\ &= a_{n-1} + a_0x + \dots + a_{n-2} \cdot x^{n-1} \in R_n \end{aligned}$$

ie. $a_{n-1}a_0a_1 \dots a_{n-2} \in V(n, q)$

In R_n :

→ multiply by x corresponds to performing a single cyclic shift

→ multiply by x^m corresponds to a cyclic shift through m positions

Theorem 12.6 (Algebraic characterization of cyclic codes). a code $C \in R_n$ is a cyclic code iff

- i. $a(x), b(x) \in C \implies a(x) + b(x) \in C$
- ii. $a(x) \in C$ and $r(x) \in R_n \implies r(x)a(x) \in C$
ie. C closed under multiplication by any element of R_n

Proof. i. let $C \in R_n$ cyclic code, then C is linear, so (i) holds.

ii. let $a(x) \in C$ and $r(x) = r_0 + r_1x + \dots + r_{n-1}x^{n-1} \in R_n$.

Since mult. by x corresponds to a cyclic shift, then $x \cdot a(x) \in C$, thus

$$x \cdot (x \cdot a(x)) = x^2 \cdot a(x) \in C$$

and so on.

Hence,

$$r(x) \cdot a(x) = r_0 \cdot a(x) + r_1 \cdot x \cdot a(x) + \dots + r_{n-1} \cdot x^{n-1} \cdot a(x) \in C$$

since each summand is in C ; thus (ii) holds.

Conversely, suppose (i) and (ii) hold;

taking $r(x)$ to be a scalar, the conditions imply that C is linear.

Taking $r(x) = x$, in (ii) shows that C is cyclic.

□

Remark . i. Cyclic codes are the ideals of the ring R_n .

ii. Every ideal in R_n is a *principal ideal*.

ie. R_n is a PID.

Theorem 6.1.3. a linear code C in $\mathbb{F}_q^n$ is cyclic iff C is an ideal in $\mathbb{F}_q[x]/(x^n-1)$.

Proof. If C ideal in $\mathbb{F}[x]/(x^n-1)$ and $c(x) = c_0 + c_1x + \dots + c_{n-1}x^{n-1} \in C$, then

$$\begin{aligned} x \cdot c(x) &= c_0x + c_1x \cdot x + \dots + \underbrace{c_{n-1}x^{n-1} \cdot x}_{=c_{n-1} \cdot 1 \pmod{x^n-1}} \\ &= c_{n-1} + c_0x + c_1x^2 + \dots + c_{n-2}x^{n-1} \in C \\ \implies (c_{n-1}, c_0, c_1, \dots, c_{n-2}) &\in C \end{aligned}$$

Conversely, if C cyclic, then $\forall c(x) \in C, x \cdot c(x) \in C$.

Therefore $x^i \cdot c(x) \in C \forall i \in [n]$

and since C is linear, $a(x) \cdot c(x) \in C$

ie.

$$a_0 \cdot c(x) + a_1 \cdot x \cdot c(x) + a_2 \cdot x^2 \cdot c(x) + \dots + a_{n-1} \cdot x^{n-1} \cdot c(x) \in C$$

$$\forall a(x) \in \mathbb{F}_q[x]/(x^n-1). \quad \square$$

Corollary . $\mathbb{F}_q[x]/(x^n-1)$ is a PID (Principal Ideal Domain).

Thus C consists of the multiples of $g(x) \in C$ monic and of lowest degree.

Therefore,

$$\implies g(x) \text{ is the } \textit{generator polynomial} \text{ (more at 12.9) of } C: C = \langle g(x) \rangle.$$

$$\implies g(x) \text{ is divisor of } x^n - 1, \text{ ie. } g(x) | (x^n - 1).$$

since otherwise $\gcd(x^n - 1, g(x))$ would be a polynomial in C with degree $< \deg(g(x))$, a contradiction.

Let $f(x) \in R_n$, $\langle f(x) \rangle$ the subset of R_n consisting of all multiples of $f(x)$ (reduced modulo $x^n - 1$). ie.

$$\langle f(x) \rangle = \{r(x) \cdot f(x) \mid r(x) \in R_n\}$$

Theorem 12.7. for any $f(x) \in R_n$, the set $\langle f(x) \rangle$ is a cyclic code; named the *code generated by $f(x)$* .

Proof. check conditions (i), (ii) of Theorem 12.6:

- i. if $a(x)f(x), b(x)f(x) \in \langle f(x) \rangle$ then

$$a(x)f(x) + b(x)f(x) = (a(x) + b(x))f(x) \in \langle f(x) \rangle$$

- ii. if $a(x)f(x) \in \langle f(x) \rangle$ and $r(x) \in R_n$, then

$$r(x)(a(x)f(x)) = (r(x) \cdot a(x))f(x) \in \langle f(x) \rangle$$

□

Example 12.8. $C = \langle 1 + x^2 \rangle \in R_3$, with $GF(2)$.

R_3 has $2^3 = 8$ elements.

Multiply $1 + x^2$ by each of the 8 elements of R_3 (reducing modulo $x^3 - 1$), obtaining 4 distinct codewords:

$$0, 1 + x, 1 + x^2, x + x^2$$

Thus C is the code $\{000, 110, 101, 011\}$.

7.3 Generator polynomial and check polynomial

Theorem 12.9. let C a nonzero cyclic coded in R_n . Then

- i. $\exists!$ $g(x)$ monic, of smallest degree in C
- ii. $C = \langle g(x) \rangle$
- iii. $g(x)$ is a factor of $x^n - 1$

Proof. i. $\exists!$ $g(x)$ monic, of smallest degree in C :

let $g(x), h(x) \in C$ monic and of smallest degree. Then $g(x) - h(x) \in C$ with smaller degree, which is a contradiction if $g(x) \neq h(x)$

- ii. $C = \langle g(x) \rangle$:

let $a(x) \in C$. By division algorithm for $F_q[x]$,

$$a(x) = q(x)g(x) + r(x)$$

with $\deg(r(x)) < \deg(g(x))$.

But $r(x) = a(x) - q(x)g(x) \in C$ by the properties of cyclic codes (Theorem 12.6, $a, g \in C$ and C an ideal)

By minimality of $\deg(g(x))$, must have $r(x) = 0$, therefore

$$\begin{aligned} a(x) &\in \langle g(x) \rangle \forall a(x) \in C \\ \implies C &= \langle g(x) \rangle \end{aligned}$$

- iii. $g(x)$ is a factor of $x^n - 1$:
by division algorithm,

$$x^n - 1 = q(x)g(x) + r(x)$$

with $\deg(r(x)) < \deg(g(x))$.

But then $r(x) = -q(x)g(x) \bmod x^n - 1$, ie. $r(x)$ is a multiple of $g(x)$, and so $r(x) \in \langle g(x) \rangle$.

By the minimality of $\deg(g(x))$, we must have $r(x) = 0$, which implies

$$x^n - 1 = q(x) \cdot g(x) + 0$$

$\implies g(x)$ is a factor of $(x^n - 1)$.

□

Definition (Generator polynomial). let C cyclic code, monic polynomial of least ddegree (given by Theorem 12.9) is called the *generator polynomial* of C .

Remark C may contain other polynomials than the generator polynomial which also generate C .

Example 12.10. All cyclic codes of length 3:

ie. ideals in $\mathbb{F}_2[x]/(x^3 - 1) \implies$ factor $x^3 - 1$ in $\mathbb{F}_2$, every cyclic code corresponds to a divisor of $x^3 - 1$.

$$x^3 - 1 = (x + 1) \cdot (x^2 + x + 1)$$

so by Theorem 12.9(ii):

generator poly	code in R_3	Corresponding code in $V(3, 2)$
1	all of R_3	all of $V(3, 2)$
$x + 1$	$\{0, 1 + x, x + x^2, 1 + x^2\}$	$\{000, 110, 011, 101\}$
$x^2 + x + 1$	$\{0, 1 + x + x^2\}$	$\{000, 111\}$
$x^3 - 1$	$\{0\}$	$\{000\}$

Notice that the 2nd column contains the multiples $(\bmod x^3 - 1)$ of the polynomials at the 1st column.

Lemma 12.11. let $g(x) = g_0 + g_1x + \dots + g_rx^r$ be the generator polynomial. Then g_0 is nonzero.

Proof. by contradiction, let $g_0 = 0$. Then $x^{n-1} \cdot g(x) = x^{-1} \cdot g(x) \in C$ with degree $r - 1$.

This contradicts minimality of $\deg(g(x))$; thus $g_0 \neq 0$.

□

Theorem 12.12. let C cyclic code with generator polynomial $g(x) = g_0 + g_1x + \dots + g_rx^r$. Then $\dim(C) = n - r$, and a GM for C is

$$G = \begin{pmatrix} g_0 & g_1 & g_2 & \cdots & g_r & 0 & 0 & \cdots & 0 \\ 0 & g_0 & g_1 & g_2 & \cdots & g_r & 0 & \cdots & 0 \\ 0 & 0 & g_0 & g_1 & g_2 & \cdots & g_r & \cdots & 0 \\ \vdots & & & & & & & \ddots & \\ 0 & 0 & \cdots & 0 & g_0 & g_1 & g_2 & \cdots & g_r \end{pmatrix}$$

Proof. the $n-r$ rows of G are linear independent because the echelon of nonzero g_0 's with 0's below.

These $n-r$ represent the codewords $g(x), x \cdot g(x), x^2 g(x), \dots, x^{n-r-1} g(x)$.

It remains to show that every codeword in C can be expressed as a linear combination of them.

From Theorem 12.9.(ii), if $a(x) \in C$ then $a(x) = q(x) \cdot g(x)$ for $q(x) \in \mathbb{F}_q[x]$.

Since $\deg(a(x)) < n$, $\deg(q(x)) < n-r$.

Hence

$$\begin{aligned} q(x)g(x) &= (q_0 + q_1x + \dots + q_{n-r-1}x^{n-r-q}) \cdot g(x) \\ &= q_0g(x) + q_1xg(x) + \dots + q_{n-r-1}x^{n-r-q}g(x) \end{aligned}$$

which is the desired linear combination. $\square$

Definition (check polynomial). For generator polynomial $g(x)$, which we know is a factor of $x^n - 1$.

Then, the *check polynomial* $h(x)$ is such that

$$x^n - 1 = g(x)h(x)$$

Since $g(x)$ is monic, so also is $h(x)$. By Theorem 12.12,

$$\deg(g(x)) = n - k \implies \deg(h(x)) = k$$

Theorem 12.14. $c(x) \in R_n$ is $c(x) \in C$ iff $c(x) \cdot h(x) = 0$.

Proof. in R_n : $g(x) \cdot h(x) = x^n - 1 = 0 \pmod{x^n - 1}$,

hence

$$c(x) \in C \xrightarrow{\text{implies}} c(x) = a(x) \cdot g(x)$$

for some $a(x) \in R_n$.

$$\begin{aligned} \implies c(x) \cdot h(x) &= \overbrace{a(x) \cdot g(x)}^{c(x)} \cdot h(x) \\ &\text{(note that } g(x) \cdot h(x) = 0\text{)} \\ &= a(x) \cdot 0 = 0 \end{aligned}$$

$\implies c(x) \cdot h(x) = 0$ as stated.

Conversely, suppose $c(x) \cdot h(x) = 0$.

By division algorithm, $c(x) = q(x) \cdot g(x) + r(x)$ with $\deg(r) < n - k$.

Then, $c(x) \cdot h(x) = 0$ implies

$$\begin{aligned} (q(x) \cdot g(x) + r(x)) \cdot h(x) &= 0 \\ q(x) \cdot g(x) \cdot h(x) + r(x) \cdot h(x) &= 0 \\ \text{recall } g(x) \cdot h(x) &= x^n - 1, \text{ thus,} \\ 0 + r(x) \cdot h(x) &= 0 \\ r(x) \cdot h(x) &= 0 \\ \text{ie. } r(x) \cdot h(x) &= 0 \pmod{x^n - 1} \end{aligned}$$

But $\deg(r(x) \cdot h(x)) < n - k + k = n$, so $r(x) \cdot h(x) = 0$ in $\mathbb{F}_q$.
Hence $r(x) = 0$, thus

$$\begin{aligned} c(x) &= q(x) \cdot g(x) \in C \\ \implies c(x) &\in C \end{aligned}$$

since C is an ideal of R_n and $g(x) \in C$ and $q(x) \in R_n$. □

Theorem 12.15. C cyclic $[n, k]$ -code with check polynomial

$$h(x) = h_0 + h_1x + \dots + h_kx^k$$

Then

i. a PCM for C is

$$H = \begin{bmatrix} h_k & h_{k-1} & h_{k-2} & \cdots & h_0 & 0 & 0 & \cdots & 0 \\ 0 & h_k & h_{k-1} & h_{k-2} & \cdots & h_0 & 0 & \cdots & 0 \\ 0 & 0 & h_k & h_{k-1} & h_{k-2} & \cdots & h_0 & \cdots & 0 \\ & \vdots & & & & & & \vdots & \\ 0 & 0 & \cdots & 0 & h_k & h_{k-1} & h_{k-2} & \cdots & h_0 \end{bmatrix}$$

ii. $C^\perp$ is a cyclic code generated by

$$\bar{h}(x) = h_k + h_{k-1}x + \dots + h_0x^k$$

7.4 Maximal and minimal cyclic codes

Let $x^n - 1 = f_1(x) \cdot f_2(x) \cdot \dots \cdot f_t(x)$, with $f_i(x)$ irreducible polynomials.

Definition 6.1.6 (maximal and minimal cyclic codes). the cyclic code generated by $f_i(x)$ is called a *maximal cyclic code* (since it's a maximal ideal), denoted M_i^+ .

The code generated by $(x^n - 1)/f_i(x)$ is called a *minimal cyclic code*, denoted M_i^- . Also named *irreducible code*.

ie.

$$M_i^+ = \langle f_i(x) \rangle, \quad M_i^- = \left\langle \frac{(x^n - 1)}{f_i(x)} \right\rangle$$

Definition (Zeros of a cyclic code). Let $x^n - 1 = f_1(x) \cdot \dots \cdot f_t(x)$. Let β_i be a zero of $f_i(x)$ in some extension field $E \supset \mathbb{F}_q$,

ie. $f_i(\beta_i) = 0$, with $f_i(x)$ the minimal polynomial of β_i .

$\implies M_i^+$ is the set of polynomials $c(x)$ for which $c(\beta_i) = 0$.

Specify a cyclic code by requiring all codewords to have certain zeros, ie. let the set $\alpha_1, \alpha_2, \dots, \alpha_s$; define the code C by

$$c(x) \in C \text{ iff } c(\alpha_i) = 0 \ \forall i \in [s]$$

then C cyclic, and the generator polynomial is the lcm of the minimal polynomials of $\alpha_1, \alpha_2, \dots, \alpha_s$.

Take the $sm \times n$ matrix with columns $1, \alpha_i, \alpha_i^2, \dots, \alpha_i^{n-1}$, denoted H , with entries in $\mathbb{F}_q$. Then

$$\begin{aligned} cH^T &= 0, \text{ with } c = (c_0, c_1, \dots, c_{n-1}) \\ c(\alpha_i) &= 0 \ \forall i \in [s], \text{ with } c(x) \in C \end{aligned}$$

7.5 Hamming cyclic codes

Theorem 6.3.1. let $n := (q^m - 1)/(q - 1)$, let β a primitive n -th root of unity in $\mathbb{F}_{q^m}$. Let $(m, q - 1) = 1$.

The cyclic code $C := \{c(x) | c(\beta) = 0\}$ is equivalent to the $[n, n - m]$ Hamming code over $\mathbb{F}_q$.

Proof. since $n = (q - 1) \cdot (q^{m-2} + 2q^{m-3} + \dots + m - 1) + m$ have $(n, q - 1) = (m, q - 1) = 1$.

Therefore $\beta^{i(q-1)} \neq 1 \ \forall i \in [n]$, ie. $\beta^i \neq \mathbb{F}_q \ \forall i \in [n]$.

Columns of H , which are the representations of $1, \beta, \beta^2, \dots, \beta^{n-1}$ as vectors in $\mathbb{F}_{q^m}$, are pairwise linearly independent over $\mathbb{F}_q$.

So H is the PCM of an $[n, n - m]$ Hamming code. $\square$

Example 6.3.2. smallest extension of $\mathbb{F}_2$ which contains a primitive 9-th root of unity is $\mathbb{F}_{2^6}$.

Let α a primitive element of the field, then $\alpha^6 3 = 1$, and $\beta := \alpha^7$ is a primitive 9-th root of unity.

Then, the minimal polynomial of β has the zeros

$$\beta, \beta^2, \beta^4, \beta^8, \beta^{16} = \beta^7, \beta^{14} = \beta^5$$

$$\implies \text{min. polynomial: } (x^9 - 1)/(x^3 - 1) = x^6 + x^3 + 1.$$

$$\text{So } (x^9 - 1) = \underbrace{(x - 1)}_{f_1(x)} \underbrace{(x^2 + x + 1)}_{f_2(x)} \underbrace{(x^6 + x^3 + 1)}_{f_3(x)}.$$

The code M_3^+ has pairwise independent columns in H , ie. min.distance ≥ 3 .

M_3^+ consists of codewords $(c_0 c_1 c_2 \ c_0 c_1 c_2 \ c_0 c_1 c_2)$, so $d = 3$.

The code M_3^- has check polynomial $x^6 + x^3 + 1$, so it's a $[9, 6]$ -code.

Since $x^3 - 1 \in M_3^-$ (is a codeword), the distance is 2.

7.6 Idempotent of a cyclic code

Theorem 6.4.1. $\exists! c(x) \in C$ which is an identity element for C .

Proof. let $g(x)$ generator polynomial, $h(x)$ check polynomial.

ie. $g(x) \cdot h(x) = x^n - 1$ in $\mathbb{F}_q[x]$.

Since $x^n - 1$ has no multiple zeros (ie. has simple zeros),

we have $(g(x), h(x)) = 1$, hence by the Bezout identity:

$$\exists a(x), b(x) \in \mathbb{F}_q[x] \text{ s.th. } a(x)g(x) + b(x)h(x) = \gcd(g, h) = 1$$

Define $c(x) := a(x)g(x) = 1 - b(x)h(x)$.

Clearly $c(x) \in C$. Furthermore, if $p(x)g(x) \in C$ (ie. $p(x) \cdot g(x)$ is any codeword in C), then

$$\begin{aligned} c(x)p(x)g(x) &= \underbrace{(1 - b(x)h(x))}_{c(x)} p(x)g(x) \\ &= p(x)g(x) - b(x)h(x)p(x)g(x) \\ (\text{recall : } g(x)h(x) &= x^n - 1) \\ &= p(x)g(x) - b(x)p(x) \underbrace{g(x)h(x)}_{=x^n-1} \\ &= p(x)g(x) \pmod{x^n - 1} \end{aligned}$$

So $c(x)$ is an identity element for C , and hence is unique. $\square$

Recall:

nilpotent $a \in A$ s.th. $a^n = 0$ for $n > 0$

idempotent $e \in A$ s.th. $e^2 = e$

Definition 6.4.2 (primitive idempotent). the idempotent of an irreducible cyclic code M_i^- is called a *primitive idempotent*, denoted by $\theta_i(x)$.

Theorem 6.4.3. if C_1, C_2 are cyclic codes with idempotents $c_1(x), c_2(x)$, then

- i. $C_1 \cap C_2$ has idempotent $c_1(x) \cdot c_2(x)$
- ii. $C_1 + C_2$, ie. the set of all words $a + b$ with $a \in C_1$, $b \in C_2$, has idempotent $c_1(x) + c_2(x) + c_1(x) \cdot c_2(x) \in C_1 + C_2$.

Theorem 6.4.4. for the primitive idempotent we have:

- i. $\theta_i(x)\theta_j(x) = 0$ if $i \neq j$
- ii. $\sum_{i=1}^t \theta_i(x) = 1$
- iii. $1 + \theta_{i_1}(x) + \theta_{i_2}(x) + \dots + \theta_{i_r}(x)$ is the idempotent of the code with generator $f_{i_1}(x) \cdot f_{i_2}(x) \cdot \dots \cdot f_{i_r}(x)$.

7.7 Trace representation

Definition 1.1.29. $q = p^r$, trace: $Tr : \mathbb{F}_q \longrightarrow \mathbb{F}_p$.

If $\zeta \in \mathbb{F}_q$, then

$$Tr(\zeta) := \zeta + \zeta^p + \zeta^{p^2} + \dots + \zeta^{p^{r-1}} \in \mathbb{F}_p$$

Theorem 1.1.30. properties of the trace function:

- i. $\forall \zeta \in \mathbb{F}_q, Tr(\zeta) \in \mathbb{F}_p$
- ii. there are elements $\theta \in \mathbb{F}_p$ such that $Tr(\zeta) \neq 0$
- iii. Tr is a linear mapping.

Proof. i. by definition $(Tr(\zeta))^p = Tr(\zeta)$

ii. the equation $x + x^p + \dots + x^{p^{r-1}} = 0$ can not have q roots in $\mathbb{F}_q$

iii. since $(\zeta + \eta)^p = \zeta^p + \eta^p$ and $\forall a \in \mathbb{F}_p$ we have $a^p = a$

□

Corollary . Tr takes every value $p^{-1}q$ times, and the polynomial $x + x^p + \dots + x^{p^{r-1}}$ is a product of minimal polynomials.

Theorem 6.5.1. let k be the multiplicative order of $p \bmod n$, $q = p^k$, β a primitive n -th root of unity in $\mathbb{F}_q$.

Then the set

$$V := \{c(\zeta) := (Tr(\zeta), Tr(\zeta\beta), \dots, Tr(\zeta\beta^{n-1})) \mid \zeta \in \mathbb{F}_q\}$$

is an $[n, k]$ irreducible code over $\mathbb{F}_p$.

Proof. by Theorem 1.1.30, V is a linear code, and $c(\zeta\beta^{-1})$ is a cyclic shift of $c(\zeta)$; hence V is a cyclic code.

Since β is in no subfield of $\mathbb{F}_q$, we know that β is a zero of an irreducible polynomial $h(x) = h_0 + h_1x + \dots + h_kx^k$.

If $c(\zeta) = (c_0, c_1, \dots, c_{n-1})$, then

$$\sum_{i=0}^k c_i h_i = Tr(\zeta h(\beta)) = Tr(0) = 0$$

since β is a zero of $h(x)$, so that $h(\beta) = 0$.

So we observe $c(x)h(x) = 0$, from Theorem 12.14 this means that $h(x)$ is the check polynomial,

ie. we have a parity check equation for the code V .

Since $h(x)$ irreducible, $x^k \cdot h(x^{-1})$ is the check polynomial for V , therefore, V is an irreducible cyclic $[n, k]$ -code. □

7.8 Mattson-Solomon Polynomial

Definition (Mattson-Solomon polynomial). Let β primitive n -th root of unity in the extension field E of $\mathbb{F}_q$.

Let T the set of polynomials over E with degree at most $n - 1$, ie.

$$T = \{p(x) \in E \mid \deg(p(x)) \leq n - 1\}$$

Define $\Phi : T \longrightarrow T$ as:

let $a(x) \in T$, then $A(X) = (\Phi_a)(X)$ is defined by

$$A(X) := \sum_{j=1}^n a(\beta^j) X^{n-j}$$

If $a = (a_0, a_1, \dots, a_{n-1})$, the polynomial $A(X)$ obtained from $a_0 + a_1x + \dots + a_{n-1}x^{n-1}$ is called the *Mattson-Solomon polynomial* of the vector a .

Lemma 6.5.3. the inverse of Φ is given by

$$a(x) = n^{-1}(\Phi A)(x^{-1}) \pmod{x^n - 1}$$

Proof.

$$A(\beta^k) = \sum_{j=1}^n \sum_{i=0}^{n-1} a_i \beta^{ij} \beta^{-kj} = \sum_{i=0}^{n-1} a_i \sum_{j=1}^n \beta^{(i-k)j} = na_k$$

□

Remark . Notation:

$\circ$: multiplication of polynomials $\text{mod}(x^n - 1)$

$*$: defined by

$$\left(\sum a_i x^i\right) * \left(\sum b_i x^i\right) := \sum a_i b_i x^i$$

Φ is an isomorphism of the ring $(T, +, \circ)$ onto the ring $(T, +, *)$.

Lemma 6.5.4. let V a cyclic code over $\mathbb{F}_q$ generated by

$$g(x) = \prod_{k \in K} (x - \beta^k)$$

Suppose $\{1, 2, \dots, d-1\} \subset K$ and $a \in V$.

Then the degree of the Mattson-Solomon polynomial A of a is at most $n - d$.

Proof. $a(\beta^j) = 0$ for $j \in [d]$ since $g(x) \mid a(x)$.

Thus at the equation $A(X) := \sum_{j=1}^n a(\beta^j) X^{n-j}$, it will be 0 between $1 \leq j \leq d-1$, so that degree is $n - d$. □

Theorem 6.5.5. if there are r n -th roots of unity which are zeros of the Mattson-Solomon polynomial A of a word a , then $w(a) = n - r$.

Proof. consequence of Lemma 6.5.3. □

8 BCH Codes

Definition 6.6.1 (BCH Code). a cyclic code of length n over $\mathbb{F}_q$ is called *BCH code of designed distance δ* if its generator $g(x)$ is the lcm of the minimal polynomials of $\beta^l, \beta^{l+1}, \dots, \beta^{l+\delta-2}$ for some l , where β is a primitive n -th root of unity.

Usually $l = 1$; if $n = q^m - 1$ (ie. β a primitive element of $\mathbb{F}_q^m$), then the BCH code is called *primitive*.

Theorem 6.6.2 (BCH Bound). the minimum distance of a BCH code with designed distance d is $\geq d$.

Proof. wlog. take $l = 1$. By Lemma 6.5.4, the degree of the Mattson-Solomon polynomial A of a codeword c is $\deg(A) \leq n - d$.

Therefore, in theorem 6.5.5 we have $r \leq n - d$, ie. $w(c) \geq d$.

(recall: r is the amount of n -th roots of unity which are zeros of the M-S polynomial A) $\square$

Definition (Defining set). If $A = \{\alpha^{i_1}, \dots, \alpha^{i_l}\}$ is a set of n -th roots of unity such that

$$c(x) \in C \iff \forall \zeta \in A \ c(\zeta) = 0$$

we say that A is the *defining set* for C .

If A is the *maximal* defining set for C , we call A *complete*.

Definition 6.6.3. $M(A)$ or $M(\alpha^{i_1}, \dots, \alpha^{i_l})$: matrix $l \times n$ that has $1, \alpha^{i_k}, \alpha^{2i_k}, \dots, \alpha^{(n-1)i_k}$ as its k -th rows, ie.

$$M(A) = \begin{bmatrix} 1 & \alpha^{i_1} & \alpha^{2i_1} & \dots & \alpha^{(n-1)i_1} \\ 1 & \alpha^{i_2} & \alpha^{2i_2} & \dots & \alpha^{(n-1)i_2} \\ \vdots & & & & \vdots \\ 1 & \alpha^{i_l} & \alpha^{2i_l} & \dots & \alpha^{(n-1)i_l} \end{bmatrix}$$

$M(A)$ is the PCM corresponding to A .

Theorem 6.6.13. The primitive binary BCH code C of length $n = 2^m - 1$ and designed distance $\delta = 2^l - 1$ has minimum distance δ .

Corollary 6.6.14. a primitive BCH code of designed distance δ has distance $d \leq 2\delta - 1$.

Corollary 6.6.16. the minimum weight of a primitive binary BCH code is odd.

References

- [1] Raymond Hill. A First Course in Coding Theory, 1986.
- [2] J.H. van Lint. Introduction to Coding Theory, 1981.

- [3] Pedro Tamaroff. Vandermonde determinant proof.
[https://math.stackexchange.com/questions/525334/
vandermonde-determinant-by-induction](https://math.stackexchange.com/questions/525334/vandermonde-determinant-by-induction).
- [4] Thomas W. Judson. Abstract algebra, theory and applications. *sec.22.2*.
- [5] Commutative algebra notes. [https://github.com/arnaucube/math/blob/
master/commutative-algebra-notes.pdf](https://github.com/arnaucube/math/blob/master/commutative-algebra-notes.pdf).