

```
clc;
clear;
close all;
```

PART 1: VEHICLE PARAMETERS

```
m = 1800;           % Vehicle mass (kg)
g = 9.81;           % Gravity (m/s^2)
Crr = 0.01;         % Rolling resistance coefficient
rho = 1.225;        % Air density (kg/m^3)
Cd = 0.29;          % Drag coefficient
A = 2.2;            % Frontal area (m^2)

delta = 0.08;       % Rotational Mass factor
m_eq = m*(1 + delta);

r_wheel = 0.3;      % Wheel radius (m)
```

PART 2: IMPORT UDDS DRIVE CYCLE

```
udds_data = readtable("uddsdc.csv");

t = udds_data.UDDS;   % Time (s)
v_mph = udds_data.Var2; % Speed (mph)

v = v_mph * 0.44704; % Convert mph → m/s

dt = mean(diff(t));

a = [diff(v)/dt; 0]; % Acceleration

% Acceleration limits
a_max = 3;
a_min = -4;

a(a > a_max) = a_max;
a(a < a_min) = a_min;
```

=====

PART 3: LONGITUDINAL FORCES

=====

```
gear_ratio = 9;

omega_wheel = v / r_wheel;
omega = omega_wheel * gear_ratio;

F_rr = m * g * Crr;
F_aero = 0.5 * rho * Cd * A .* v.^2;
F_acc = m_eq .* a;

theta = deg2rad(2);
F_rg = m*g*sin(theta);

F_total = F_rr + F_aero + F_acc + F_rg;
```

=====

PART 4: WHEEL MECHANICAL POWER

=====

```
P_wheel = F_total .* v;

eta_tire = 0.95;
P_wheel = P_wheel / eta_tire;
```

=====

PART 5: MOTOR + REGEN LIMITS

=====

```
T_motor_max = 250;
T_regen_max = 120;
P_motor_max = 80e3;

v_min_regen = 1.5;

eta_drivetrain = 0.95;

P_mech = zeros(size(P_wheel));
```

```

omega_base = P_motor_max / T_motor_max;

for i = 1:length(P_wheel)

    if P_wheel(i) > 0

        if omega(i) <= omega_base
            T_avail = T_motor_max;
        else
            T_avail = P_motor_max / omega(i);
        end

        P_avail = T_avail * omega(i);

        P_mech(i) = min(P_wheel(i), P_avail);

    elseif P_wheel(i) < 0 && v(i) > v_min_regen

        P_regen_limit = T_regen_max * omega(i);

        P_mech(i) = -min(abs(P_wheel(i)), P_regen_limit);

    else

        P_mech(i) = 0;

    end

end

% drivetrain efficiency
P_mech = P_mech / eta_drivetrain;

```

=====

PART 6: DISTANCE & IDEAL ENERGY

=====

```

E_Wh = trapz(t, P_mech) / 3600;

dist_km = trapz(t, v) / 1000;

E_Wh_per_km = E_Wh / dist_km;

```

=====

PART 7: MOTOR + INVERTER EFFICIENCY

=====

```
omega_max = max(omega) + eps;

drive_eff = ones(size(P_mech));
regen_eff = ones(size(P_mech));

for i = 1:length(P_mech)

    if P_mech(i) > 0

        T_req = P_mech(i) / max(omega(i),eps);

        Tn = abs(T_req) / T_motor_max;

        on = omega(i) / omega_max;

        drive_eff(i) = 0.90 ...
            - 0.15*(1-on)^2 ...
            - 0.20*(Tn-0.6)^2;

        drive_eff(i) = min(max(drive_eff(i),0.75),0.92);

    elseif P_mech(i) < 0

        T_req = abs(P_mech(i)) / max(omega(i),eps);

        Tn = T_req / T_regen_max;

        on = omega(i) / omega_max;

        regen_eff(i) = 0.75 ...
            - 0.20*(1-on)^2 ...
            - 0.30*(Tn-0.5)^2;

        regen_eff(i) = min(max(regen_eff(i),0.55),0.80);

    end

end
```

=====

PART 8: BATTERY POWER FLOW

```

=====

P_batt_disch_max = 90e3;
P_batt_char_max  = 40e3;

P_accessory = 900;

Batt_capacity = 50; % kWh

P_drive = zeros(size(P_mech));
P_regen = zeros(size(P_mech));

for i = 1:length(P_mech)

    if P_mech(i) > 0

        P_drive(i) = P_mech(i) / drive_eff(i);

        P_drive(i) = min(P_drive(i), P_batt_disch_max);

    elseif P_mech(i) < 0

        P_regen(i) = abs(P_mech(i)) * regen_eff(i);

        P_regen(i) = min(P_regen(i), P_batt_char_max);

    end

end

P_batt = P_drive - P_regen + P_accessory;

```

PART 9: SOC MODEL

```

=====

SOC = zeros(size(t));

SOC(1) = 0.80;

for i = 2:length(t)

    E_step_Wh = P_batt(i) * dt / 3600;

    SOC(i) = SOC(i-1) - E_step_Wh/(Batt_capacity*1000);

```

```
end
```

=====

PART 10: PLOTS


=====

```
figure('Name','EV UDDS Simulation');

subplot(3,1,1)
plot(t,v*3.6,'r','LineWidth',1.5)
xlabel('Time (s)')
ylabel('Speed (km/h)')
title('UDDS Drive Cycle')
grid on

subplot(3,1,2)
plot(t,P_drive/1000,'b'); hold on
plot(t,-P_regen/1000,'g')
xlabel('Time (s)')
ylabel('Power (kW)')
legend('Drive','Regen')
title('Battery Power Flow')
grid on

subplot(3,1,3)
plot(t,SOC*100,'k','LineWidth',1.5)
xlabel('Time (s)')
ylabel('SOC (%)')
title('Battery State of Charge')
grid on
```



=====

PART 11: FINAL RESULTS

=====

```
E_drive_Wh = trapz(t,P_drive)/3600;

E_regen_Wh = trapz(t,P_regen)/3600;

E_batt_net = E_drive_Wh - E_regen_Wh;

E_brake_mech = trapz(t,abs(min(P_mech,0)))/3600;

regen_percentage = (E_regen_Wh/E_brake_mech)*100;

P_drive_max = max(P_drive)/1000;

P_regen_max = max(P_regen)/1000;

P_wheel_max = max(P_mech)/1000;

SOC_initial = SOC(1)*100;
```

```
SOC_final = SOC(end)*100;

SOC_delta = SOC_initial - SOC_final;

avg_speed_kmh = mean(v)*3.6;
```

=====

PRINT RESULTS

=====

```
fprintf('\nVEHICLE & DRIVE CYCLE\n\n');
```

VEHICLE & DRIVE CYCLE

```
fprintf('Vehicle Mass\n: %.0f kg\n\n',m);
```

Vehicle Mass
: 1800 kg

```
fprintf('Total Distance Travelled\n: %.3f km\n\n',dist_km);
```

Total Distance Travelled
: 11.990 km

```
fprintf('Average Speed\n: %.2f km/h\n\n',avg_speed_kmh);
```

Average Speed
: 31.51 km/h

```
fprintf('Drive Cycle Duration\n: %.0f s\n\n',t(end));
```

Drive Cycle Duration
: 1369 s

```
fprintf('ENERGY CONSUMPTION\n\n');
```

ENERGY CONSUMPTION

```
fprintf('Wheel Mechanical Energy\n: %.2f Wh\n\n',E_Wh);
```

Wheel Mechanical Energy
: 3086.55 Wh

```
fprintf('Battery Energy Drawn\n: %.2f Wh\n\n',E_drive_Wh);
```


Battery Energy Drawn
: 4413.01 Wh

```
fprintf('Battery Energy Regenerated\n: %.2f Wh\n\n',E_regen_Wh);
```

Battery Energy Regenerated
: 366.46 Wh

```
fprintf('Net Battery Energy Used\n: %.2f Wh\n\n',E_batt_net);
```

Net Battery Energy Used
: 4046.55 Wh

```
fprintf('Specific Energy Consumption\n: %.2f Wh/km\n\n',E_batt_net/dist_km);
```

Specific Energy Consumption
: 337.49 Wh/km

```
fprintf('POWER PERFORMANCE\n\n');
```

POWER PERFORMANCE

```
fprintf('Maximum Wheel Power\n: %.2f kW\n\n',P_wheel_max);
```

Maximum Wheel Power
: 53.55 kW

```
fprintf('Maximum Battery Drive Power\n: %.2f kW\n\n',P_drive_max);
```

Maximum Battery Drive Power
: 61.42 kW

```
fprintf('Maximum Regen Power\n: %.2f kW\n\n',P_regen_max);
```

Maximum Regen Power
: 20.32 kW

```
fprintf('REGENERATIVE BRAKING\n\n');
```

REGENERATIVE BRAKING

```
fprintf('Mechanical Braking Energy\n: %.2f Wh\n\n',E_brake_mech);
```

Mechanical Braking Energy
: 561.29 Wh

```
fprintf('Regen Energy Recovery\n: %.2f %%\n\n',regen_percentage);
```

```
Regen Energy Recovery  
: 65.29 %
```

```
fprintf('BATTERY STATE OF CHARGE\n\n');
```

```
BATTERY STATE OF CHARGE
```

```
fprintf('Initial SOC\n: %.2f %%\n\n',SOC_initial);
```

```
Initial SOC  
: 80.00 %
```

```
fprintf('Final SOC\n: %.2f %%\n\n',SOC_final);
```

```
Final SOC  
: 71.22 %
```

```
fprintf('Net SOC Change\n: %.3f %%\n\n',SOC_delta);
```

```
Net SOC Change  
: 8.778 %
```

=====

MOTOR TORQUE SPEED CHARACTERISTIC

=====


```
omega_range = linspace(0, max(omega)*1.2, 500);  
  
T_motor = zeros(size(omega_range));  
  
for i = 1:length(omega_range)  
    if omega_range(i) <= omega_base  
        T_motor(i) = T_motor_max;  
    else  
        T_motor(i) = P_motor_max / omega_range(i);  
    end  
end  
  
figure  
  
plot(omega_range, T_motor, 'LineWidth',2);
```

```

xlabel('Motor Speed (rad/s)');
ylabel('Torque (Nm)');
title('EV Motor Torque-Speed Curve');

grid on;

```



=====

MOTOR EFFICIENCY MAP

=====

```

speed_norm = omega/omega_max;

torque = P_mech ./ max(omega,eps);

torque_norm = abs(torque)/T_motor_max;

figure

scatter(speed_norm, torque_norm, 15, drive_eff,'filled')

colorbar


xlabel('Normalized Speed');

```

```
ylabel('Normalized Torque');

title('Motor Efficiency Map');

grid on;
```



=====

ENERGY FLOW ANALYSIS

=====

```
E_accessory = trapz(t, ones(size(t))*P_accessory)/3600;

fprintf('\nENERGY FLOW ANALYSIS\n\n');
```

ENERGY FLOW ANALYSIS

```
fprintf('Drive Energy From Battery : %.2f Wh\n',E_drive_Wh);
```

Drive Energy From Battery : 4413.01 Wh

```
fprintf('Recovered Regen Energy      : %.2f Wh\n',E_regen_Wh);
```

Recovered Regen Energy : 366.46 Wh

```
fprintf('Accessory Consumption : %.2f Wh\n',E_accessory);
```

Accessory Consumption : 342.25 Wh

```
fprintf('Net Battery Consumption : %.2f Wh\n',E_batt_net);
```

Net Battery Consumption : 4046.55 Wh

=====

RANGE ESTIMATION

=====

```
usable_SOC = 0.8 - 0.2; % 80% to 20%
```

```
usable_energy = Batt_capacity * usable_SOC * 1000; % Wh
```

```
range_est = usable_energy / (E_batt_net/dist_km);
```

```
fprintf('\nESTIMATED EV RANGE\n\n');
```

ESTIMATED EV RANGE

```
fprintf('Estimated Range (UDDS Based) : %.1f km\n',range_est);
```

Estimated Range (UDDS Based) : 88.9 km