BOM Nixie Calculator Controller Rev.1 08/07/2023

ID Qua	nntity Value	Additional	Designator	Footprint	Туре	Manufacturer Part	Manufacturer
1	1 1.2M	1/4W, 1%	R1	0805	Resistor	RK73H2ATTD1204F	KOA Speer
2	1 510k	1/4W	R2	0805	Resistor	RK73H2ATTD5103F	KOA Speer
3	1 15k	1/4W, 1%	R3	0805	Resistor	RK73H2ATTD1502F	KOA Speer
4	1 1k	1/4W	R4	0805	Resistor	RK73H2ATTDD1001F	KOA Speer
5	1 47k	1/4W, 1%	R5	0805	Resistor	RK73H2ATTD4702F	KOA Speer
6	2 10	1/4W	R6,R7	0805	Resistor	RK73H2ATTD10R0F	KOA Speer
7	2 330	1/4W	R8,R12	0805	Resistor	RK73H2ATTD3300F	KOA Speer
8	6 4.7k	1/4W	R10,R11,R14,R17,R21,R23	0805	Resistor	RK73H2ATTD4701F	KOA Speer
9	3 10k	1/4W	R9,R24,R25	0805	Resistor	RK73H2ATTD1002F	KOA Speer
10	3 150	1/4W	R13,R15,R16	0805	Resistor	RK73H2ATTD1500F	KOA Speer
11	1 see schematic	1/4W	R18	0805	Resistor		
12	1 see schematic	1/4W	R19	0805	Resistor		
13	2 3.9k	1/4W	R20,R22	0805	Resistor	RK73H2ATTD3901F	KOA Speer
14	1 220u	25V	C1	8mm dia	Capacitor	GYB1E221MCQ1GS	Nichicon
15	9 100n	50V	C2,C6,C10,C12-C17	0805	Capacitor	C0805C104M5RACTU	KEMET
16	2 10u	25V	C3,C7	1206	Capacitor	TMK316BJ106MLHT	Taiyo Yuden
17	4 22u	25V	C4,C5,C8,C9	1206	Capacitor	TMK316BBJ226ML-T	Taiyo Yuden
18	1 10u	16V	C11	0805	Capacitor	GRM21BR61C106KE15K	Murata Electronics
19	1 B340A-13-F		D1	SMA	Diode	B340A-13-F	Diodes Incorporated
20	1 LED yellow		LED1	1206	LED	599-0240-007F	Dialight
21	1 LED red		LED2	1206	LED	599-0210-007F	Dialight
22	1 LED blue		LED3	1206	LED	599-0291-007F	Dialight
23	1 3.9uH inductor		L1	8043	Inductor	SRU8043-3R9Y	Bourns
24	1 4.7uH inductor		L2	8043	Inductor	SRU8043-4R7Y	Bourns
25	1 LTC4365		U1	SOT-8	IC	LTC4365ITS8-1#TRMPBF	Analog Devices
26	1 AP63203WU-7		U2	TSOT-26-6	IC	AP63203WU-7	Diodes Incorporated
27	1 AP63205WU-7		U3	TSOT-26-6	IC	AP63205WU-7	Diodes Incorporated
28	1 ESP-WROOM-32E	16MB	U4		MC module	ESP32-WROOM-32E-N16	Espressif Systems
29	1 CD40109B		U5	SO-16	IC	CD40109BNSR	Texas Insruments
30	1 DS3231MZ+		U6	SOIC-8	IC	DS3231MZ+TRL	Maxim Integrated
31	1 CSD88537ND Dual N		Q1	SOIC-8	Mosfet	CSD88537ND	Texas Insruments
32	4 BSS138		Q2,Q3,Q4,Q5	SOT-23	Mosfet	BSS138N H6327	Infineon Technologies
33	1 DC power connector		DCIN		DC power connector	PJ-057AH	CUI Devices
34	1 Fuse 1.25A Fast		F1		Fuse	0034.6015	Schurter
35	1 Fuse holder				Fuse holder	0031.7601	Schurter
36	2 Tactile Switch		SW1,SW2		Switch	TL1105AF160Q	E-Switch
37	1 Tactile Switch	right angle	BUTTON1		Switch	TL1105SF160Q	E-Switch
38	1 CR2032 battery holder	0 11 01			Battery holder	SMTU2032-LF	Renata
39	1 CR2032 battery		B1		Battery		
40	1 1x2 header/2.54mm	male	SWITCH		Header		
41	2 1x3 header/2.54mm	male	LED,IOEX		Header		
42	*1 1x4 header/2.54mm	male	SERIAL		Header		
43	2 1x5 header/2.54mm	male	12C		Header		
44	2 1x6 header/2.54mm	male	FLASH, DRIVER		Header		
45	1 3 poles terminal block	1	TOHVPSU		Fixed Terminal Block	TB006-508-03BE	CUI Devices
451							

^{*} do not populate