1. **Connect a USB webcam to your computer, install any required drivers, and verify that the webcam works by opening the default camera app and capturing a photo.**

Step	Action	Description
1.	Connect the webcam	Plug the USB webcam into an available USB port on the computer.
2.	Install drivers	Wait for Windows to detect the webcam and automatically install the required drivers.
3.	Check Device Manager	Open Device Manager → Cameras and check whether the webcam appears in the list.
4.	Open Camera App	Search for Camera in the Windows Start menu and open the application.
5.	Test the webcam	Check whether the webcam displays a live video feed.
6.	Capture a photo	Click the camera button to take a photo and verify that it is saved successfully.

2. **Set up a local printer (USB or network), install the correct driver, and print a test page to confirm successful installation.**

Step	Action	Description
1.	Connect the printer	Connect the printer to the computer using a USB cable or connect both devices to the same Wi-Fi network.
2.	Switch on the printer	Turn on the printer and check that it has enough paper and ink or toner.
3.	Install the driver	Download and install the correct printer driver from the manufacturer's official website, or allow Windows to install it automatically.
4.	Open Printer Settings	Go to Settings → Devices → Printers & scanners in Windows.

5.	Add the printer	Click Add a printer or scanner, select your printer, and follow the instructions.
6.	Set as default printer	Select the installed printer and choose Manage → Set as default, if required.
7.	Print a test page	Open printer properties and click Print Test Page.
8.	Verify the result	Check whether the printer prints the test page correctly without errors.

3. **Simulate a connectivity issue by unplugging the printer's USB cable, then use Windows Device Manager to identify and resolve the 'printer not detected' problem.

Hint: Check for error icons and use the 'Scan for hardware changes' option after reconnecting.**

Step	Action	Description
1.	Disconnect the USB cable	Unplug the printer's USB cable from the computer to simulate a connection problem.
2.	Open Device Manager	Press Windows + X and select Device Manager.
3.	Check printer status	Expand Printers or Print queues and check whether the printer is missing or showing a yellow warning icon.
4.	Reconnect the printer	Plug the USB cable back into the computer and make sure the printer is switched on.
5.	Scan for hardware changes	In Device Manager, click Action → Scan for hardware changes to make Windows search for the connected printer again.
6.	Check the driver	Confirm that the printer appears without any warning icon. If there is a driver error, update or reinstall the correct printer driver.
7.	Test the printer	Open Settings → Printers & scanners and check whether the printer is detected. Print a test page to confirm that it works.

4. **A user reports that their webcam video is not displaying in Zoom, but it works in the default camera app. Troubleshoot and resolve the issue so the webcam works in both applications.

Hint: Check if another app is using the webcam or if Zoom permissions are enabled.**

Step	Action	Description
1.	Close other applications	Close the Windows Camera app, Skype, Microsoft Teams, or any other application that may be using the webcam.
2.	Check Zoom camera settings	Open Zoom → Settings → Video and check whether the correct webcam is selected.
3.	Check Windows camera permissions	Go to Settings → Privacy → Camera and turn ON camera access and access for desktop apps.
4.	Restart Zoom	Completely close Zoom and open it again to refresh the webcam connection.
5.	Update Zoom and webcam drivers	Install the latest Zoom updates and check Device Manager → Cameras for available driver updates.
6.	Test the webcam in Zoom	Open Zoom → Settings → Video and check whether the webcam displays a live video feed.