

Safety & Emergency Operating Guidelines

This document defines emergency procedures for the factory floor. It applies in addition to, not instead of, the Preventive Maintenance SOP.

Section 1: Emergency Stop Procedure

Any operator may trigger an emergency stop on any machine showing visible smoke, a burning smell, unusual grinding or screeching noise, or any sensor reading at DANGER level combined with a physical warning sign. Press the red emergency stop button at the machine control panel, then notify the shift supervisor immediately. Do not attempt to restart the machine until it has been inspected and cleared by a qualified maintenance technician.

Section 2: Lockout-Tagout (LOTO)

Before any maintenance technician performs physical work on a machine that has been stopped for a DANGER-level event, the machine's energy source must be isolated and tagged (lockout-tagout) so it cannot be re-energized until the work is complete and the tag is removed by the technician who applied it.

Section 3: Personal Protective Equipment

Safety glasses and hearing protection are required within two meters of any running CNC or Press machine. Heat-resistant gloves are required when working near an Injection Molder due to elevated operating temperature.

Section 4: Incident Reporting

Every emergency stop event must be recorded within 24 hours with: machine ID, timestamp, operator name, description of the triggering condition, and the maintenance action taken. This record feeds into the maintenance-note dataset used for incident classification.