

Table 35. Current consumption of peripherals (continued)

| Peripheral                      | Bus | Consumption in $\mu\text{A}/\text{MHz}$ |
|---------------------------------|-----|-----------------------------------------|
| All APB peripherals             | APB | 35                                      |
| AHB to APB bridge (2)           |     | 0.3                                     |
| TIM3                            |     | 3.7                                     |
| RTCAPB                          |     | 1.4                                     |
| WWDG1                           |     | 0.3                                     |
| USART2                          |     | 1.9                                     |
| I2C1                            |     | 0.9                                     |
| I2C1 independent clock domain   |     | 2.5                                     |
| I2C2                            |     | 0.9                                     |
| DBGMCU1                         |     | 0.1                                     |
| PWR                             |     | 0.3                                     |
| SYSCFG                          |     | 0.5                                     |
| TIM1                            |     | 6.6                                     |
| TIM2                            |     | 4.4                                     |
| SPI1                            |     | 2.0                                     |
| SPI1 independent clock domain   |     | 0.6                                     |
| SPI2                            |     | 1.7                                     |
| USART1                          |     | 2.3                                     |
| USART1 independent clock domain |     | 5.2                                     |
| TIM14                           |     | 1.4                                     |
| TIM16                           |     | 2.5                                     |
| TIM17                           |     | 2.6                                     |
| ADC1                            |     | 1.3                                     |
| ADC1 independent clock domain   |     | 0.1                                     |
| All peripherals                 |     | 57.2                                    |