

Table 12. Pin assignment and description (continued)

Pin Number ⁽¹⁾							Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
WLCSP19 GP	TSSOP20 GP/N	UFQFPN28 GP/N	LQFP32, UFQFPN32 GP/N	LQFP48, UFQFPN48 GP/N	LQFP64 GP/N	UFPGA64 N						
E4	4	3	4	6	8	D1	VDD/VDDA	S	-	-	-	-
G4	5	4	5	7	9	E1	VSS/VSSA	S	-	-	-	-
-	-	-	-	8	10	F1	PF0- OSC_IN (PF0)	I/O	FT	-	CRS_SYNC, TIM14_CH1	OSC_IN
-	-	-	-	9	11	G1	PF1- OSC_OUT (PF1)	I/O	FT	-	OSC_EN	OSC_OUT
J4	6	5	6	10	12	E2	PF2-NRST	I/O	RST, FT	(2)	MCO, TIM1_CH4	NRST
-	-	-	-	-	13	E3	PC0	I/O	FT	-	-	-
-	-	-	-	-	14	F2	PC1	I/O	FT	-	-	-
-	-	-	-	-	15	G2	PC2	I/O	FT	-	SPI2_MISO	-
-	-	-	-	-	16	H1	PC3	I/O	FT	-	SPI2_MOSI	-
J4	7	6	7	11	17	H2	PA0	I/O	FT_a	-	SPI2_SCK, USART2_CTS/USART2_NSS, TIM16_CH1, TIM2_ETR/TIM2_CH1, USART1_TX, TIM1_CH1	ADC_IN0, WKUP1
H3	8	7	8	12	18	H3	PA1	I/O	FT_a	-	SPI1_SCK/I2S1_CK, USART2_RTS/USART2_DE/ USART2_CK, TIM17_CH1, TIM2_CH2, USART1_RX, TIM1_CH2, I2C1_SMBA, EVENTOUT	ADC_IN1
L4	9	8	9	13	19	G3	PA2	I/O	FT_a	-	SPI1_MOSI/I2S1_SD, USART2_TX, TIM16_CH1N, TIM3_ETR, TIM1_CH3, TIM2_CH3	ADC_IN2, WKUP4, LSCO
K3	10	9	10	14	20	F3	PA3	I/O	FT_a	-	SPI2_MISO, USART2_RX, TIM1_CH1N, TIM2_CH4, TIM1_CH4, EVENTOUT	ADC_IN3
-	-	-	-	15	21	H4	PA4	I/O	FT_a	-	SPI1_NSS/I2S1_WS, USART2_TX, TIM1_CH2N, SPI2_MOSI, TIM14_CH1, TIM17_CH1N, USB_NOE, EVENTOUT	ADC_IN4, RTC_OUT2
J2	11	10	11	-	-	-	PA4	I/O	FT_a	-	SPI1_NSS/I2S1_WS, USART2_TX, TIM1_CH2N, SPI2_MOSI, TIM14_CH1, TIM17_CH1N, USB_NOE, EVENTOUT	ADC_IN4, RTC_TS, RTC_OUT1, WKUP2
H1	12	11	12	16	22	G4	PA5	I/O	FT_a	-	SPI1_SCK/I2S1_CK, USART2_RX, TIM1_CH3N, TIM2_ETR/TIM2_CH1, TIM1_CH1, EVENTOUT	ADC_IN5
L2	13	12	13	17	23	F4	PA6	I/O	FT_fa	-	SPI1_MISO/I2S1_MCK, TIM3_CH1, TIM1_BKIN, TIM16_CH1, I2C2_SDA	ADC_IN6
K1	14/-	13	14	18	24	E4	PA7	I/O	FT_fa	-	SPI1_MOSI/I2S1_SD, TIM3_CH2, TIM1_CH1N, TIM14_CH1, TIM17_CH1, I2C2_SCL	ADC_IN7
-	-	-	-	-	25	H5	PC4	I/O	FT_a	-	USART1_TX, TIM2_ETR/TIM2_CH1	ADC_IN11
-	-	-	-	-	26	H6	PC5	I/O	FT_a	-	USART1_RX, TIM2_CH2	ADC_IN12, WKUP5
-	-	14	15	19	27	F5	PB0	I/O	FT_a	-	SPI1_NSS/I2S1_WS, TIM3_CH3, TIM1_CH2N	ADC_IN17
-	-	15	16	20	28	G5	PB1	I/O	FT_a	-	TIM14_CH1, TIM3_CH4, TIM1_CH3N, TIM1_CH2N, EVENTOUT	ADC_IN18