

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
15	13	16	22	22	33	33	45	PA12	I/O	FT_fu	-	TIM1_ETR, LPUART1_RTS, USART2_RX, SPI2_SCK/ I2S2_CK, UART4_TX, USART1_RTS, I2C1_SDA, FDCAN1_TX, COMP2_OUT, EVENTOUT	USB_DP
16	14	17	23	23	34	34	46	PA13 (JTMS/ SWDIO)	I/O	FT	(3)	JTMS/SWDIO, COMP1_OUT, EVENTOUT	-
-	-	-	-	-	35	35	47	VSS	S	-	-	-	-
-	-	-	-	-	36	36	48	VDD	S	-	-	-	-
17	15	18	24	24	37	37	49	PA14 (JTCK/ SWCLK)	I/O	FT	(3)	JTCK/SWCLK, EVENTOUT	-
18	16	19	25	25	38	38	50	PA15 (JTDI)	I/O	FT	(3)	JTDI, TIM2_CH1, TIM1_CH2N, LPTIM1_ETR, I2C1_SMBA, SPI1_NSS/I2S1_WS, SPI2_NSS/I2S2_WS, USART2_CK, UART4_RTS, USART1_TX, TIM8_CH4N, TIM2_ETR, EVENTOUT	-
-	-	-	-	-	-	-	51	PC10	I/O	FT	-	TIM8_CH1N, I3C1_SCL, SPI2_SCK/I2S2_CK, USART2_TX, UART4_TX, EVENTOUT	-
-	-	-	-	-	-	-	52	PC11	I/O	FT	-	TIM8_CH2N, I3C1_SDA, SPI2_MISO/I2S2_SDI, USART2_RX, UART4_RX, EVENTOUT	-
-	-	-	-	-	-	-	53	PC12	I/O	FT	-	TRACED3, TIM15_CH1, TIM8_CH3N, SPI2_MOSI/ I2S2_SDO, USART2_CK, UART5_TX, EVENTOUT	-
-	-	-	-	-	-	-	54	PD2	I/O	FT	-	TRACED2, TIM15_BKIN, UART5_RX, EVENTOUT	-

