

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	20	20	28	28	32	37	PB2	I/O	FT_a	-	RTC_OUT2, TIM8_CH4N, SPI1_RDY, LPTIM1_CH1, SPI2_SCK/I2S2_CK, SPI3_MOSI/ I2S3_SDO, EVENTOUT	ADC2_IN8, COMP1_INP3, LSCO
-	-	-	-	-	-	33	38	PE7	I/O	FT	-	TIM1_ETR, EVENTOUT	-
-	-	-	-	-	-	34	39	PE8	I/O	FT	-	TIM1_CH1N, EVENTOUT	-
-	-	-	-	-	-	35	40	PE9	I/O	FT	-	TIM1_CH1, EVENTOUT	-
-	-	-	-	-	-	36	41	PE10	I/O	FT	-	TIM1_CH2N, EVENTOUT	-
-	-	-	-	-	-	-	42	PE11	I/O	FT	-	TIM1_CH2, SPI1_RDY, EVENTOUT	-
-	-	-	-	-	-	-	43	PE12	I/O	FT	-	TIM1_CH3N, COMP1_OUT, EVENTOUT	-
-	-	-	-	-	-	-	44	PE13	I/O	FT	-	TIM1_CH3, EVENTOUT	-
-	-	-	-	-	-	-	45	PE14	I/O	FT	-	TIM1_CH4, EVENTOUT	-
-	-	-	-	-	-	-	46	PE15	I/O	FT	-	TIM1_BKIN, TIM1_CH4N, EVENTOUT	-
-	-	21	21	29	29	37	47	PB10	I/O	FT_f	-	TIM2_CH3, TIM8_CH1, LPTIM1_IN1, I2C2_SCL, SPI2_SCK/I2S2_CK, USART3_TX, EVENTOUT	-
15	16	22	22	30	30	38	48	VCAP	S	-	-	-	-
16	-	23	23	31	31	39	49	VSS	S	-	-	-	-
17	17	24	24	32	32	40	50	VDD	S	-	-	-	-
-	-	25	25	33	33	41	51	PB12	I/O	FT_f	⁽⁴⁾	TIM1_BKIN, TIM8_CH3, I2C2_SDA, SPI2_NSS/I2S2_WS, USART3_CK, FDCAN1_RX, UART5_RX, EVENTOUT	-

