

Table 13. STM32C562xx pin/ball definition

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	1	1	1	1	1	1	PE2	I/O	FT	-	TRACECLK, LPTIM1_IN2, SPI3_SCK/I2S3_CK, EVENTOUT	-
-	-	-	-	-	2	2	2	PE3	I/O	FT	-	TRACED0, TIM15_BKIN, USART1_RX, EVENTOUT	-
-	-	-	-	-	3	-	3	PE4	I/O	FT	-	TRACED1, TIM15_CH1N, SPI3_NSS/I2S3_WS, USART1_TX, EVENTOUT	-
-	-	-	-	-	4	-	4	PE5	I/O	FT	-	TRACED2, TIM15_CH1, SPI3_MISO/I2S3_SDI, USART1_CK, EVENTOUT	-
-	-	-	-	-	-	-	5	PE6	I/O	FT	-	TRACED3, TIM1_BKIN2, TIM15_CH2, SPI3_MOSI/ I2S3_SDO, USART1_CTS/ USART1_NSS, EVENTOUT	WKUP3
-	-	-	-	-	-	-	6	PH15	I/O	FT	-	USART1_RTS, EVENTOUT	-
-	-	2	2	2	-	3	7	PC13	I/O	FT_t	(2)(3)	FDCAN1_TX, EVENTOUT	TAMP_IN1, RTC_OUT1/ RTC_TS, WKUP4
2	2	3	3	3	-	4	8	PC14-OSC32_IN (OSC32_IN)	I/O	FT	(2)	TIM12_CH1, FDCAN1_RX, EVENTOUT	OSC32_IN
-	-	4	4	4	-	5	9	PC15- OSC32_OUT (OSC32_OUT)	I/O	FT	(2)	TIM12_CH2, EVENTOUT	OSC32_OUT
-	-	-	-	-	-	6	10	VSS	S	-	-	-	-
-	-	-	-	-	-	7	11	VDD	S	-	-	-	-
2	2	5	5	5	5	8	12	PH0-OSC_IN (PH0)	I/O	FT_f	-	I2C1_SDA, EVENTOUT	OSC_IN
3	3	6	6	6	6	9	13	PH1-OSC_OUT (PH1)	I/O	FT_f	-	I2C1_SCL, EVENTOUT	OSC_OUT
4	4	7	7	7	7	10	14	NRST	I/O	RST	-	-	-

