

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
5	5	9	9	13	13	16	21	32	VREF+	S		-	-	-
-	-	-	-	-	-	17	22	33	PH5	I/O	FT_a	-	EVENTOUT	ADC2_IN13, ADC3_IN13
6	6	10	10	14	14	18	23	34	PA0	I/O	FT_a	-	TIM2_CH1, TIM5_CH1, TIM8_ETR, TIM15_BKIN, SPI2_RDY, SPI3_RDY, USART2_CTS/USART2_NSS, UART4_TX, SPI2_NSS/ I2S2_WS, ETH1_MII_CRD, XSPI1_IO3, TIM2_ETR, EVENTOUT	ADC1_IN0, ADC2_IN0, COMP1_INP1, TAMP_IN2, WKUP1
7	7	11	11	15	15	19	24	35	PA1	I/O	FT_a	-	TIM2_CH2, TIM5_CH2, TIM8_BKIN, TIM15_CH1N, LPTIM1_IN1, USART2_RTS, UART4_RX, XSPI1_IO3, ETH1_MII_RX_CLK/ ETH1_RMII_REF_CLK, XSPI1_DQS, EVENTOUT	ADC1_IN1, ADC2_IN1, TAMP_IN3
8	8	12	12	16	16	20	25	36	PA2	I/O	FT_a	-	TIM2_CH3, TIM5_CH3, LPUART1_RX, TIM15_CH1, LPTIM1_IN2, USART2_TX, ETH1_MDIO, XSPI1_NCLK, EVENTOUT	ADC1_IN2, ADC2_IN2, TAMP_IN3, WKUP2
9	9	13	13	17	17	21	26	37	PA3	I/O	FT_a	-	TIM2_CH4, TIM3_CH3, LPUART1_TX, TIM15_CH2, SPI2_NSS/I2S2_WS, SPI3_MOSI/I2S3_SDO, USART2_RX, TIM5_CH4, ETH1_MII_COL, XSPI1_CLK, COMP1_OUT, EVENTOUT	ADC1_IN3, ADC2_IN3
-	-	-	-	18	18	22	27	38	VSS	S		-	-	-
-	-	-	-	19	19	23	28	39	VDD	S		-	-	-
10	10	14	14	20	20	24	29	40	PA4	I/O	TT_a	-	TIM3_CH4, SPI3_MOSI/ I2S3_SDO, SPI1_NSS/I2S1_WS, SPI3_NSS/I2S3_WS, USART2_CK, TIM5_ETR, EVENTOUT	ADC1_IN4, DAC1_OUT1

