

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
-	-	-	-	-	-	-	18	PF6	I/O	FT	-	UART7_RX, TIM16_CH1, XSPI1_IO3, EVENTOUT	-
-	-	-	-	-	-	-	19	PF7	I/O	FT	-	TIM17_CH1, UART7_TX, XSPI1_IO2, EVENTOUT	-
-	-	-	-	-	-	-	20	PF8	I/O	FT	-	UART7_RTS, TIM16_CH1N, XSPI1_IO1, ETH1_MII_TX_ER, EVENTOUT	-
-	-	-	-	-	-	-	21	PF9	I/O	FT	-	TIM17_CH1N, UART7_CTS, ETH1_MDC, XSPI1_IO0, EVENTOUT	-
-	-	-	-	-	-	-	22	PF10	I/O	FT	-	XSPI1_CLK, TIM16_BKIN, EVENTOUT	-
2	2	5	5	5	8	12	23	PH0-OSC_IN(PH0)	I/O	FT_f	-	I2C1_SDA, EVENTOUT	OSC_IN
3	3	6	6	6	9	13	24	PH1-OSC_OUT(PH1)	I/O	FT_f	-	I2C1_SCL, EVENTOUT	OSC_OUT
4	4	7	7	7	10	14	25	NRST	I/O	RST	-	-	-
-	-	-	-	8	11	15	26	PC0	I/O	FT_a	-	SPI2_RDY, TIM16_BKIN, XSPI1_IO7, EVENTOUT	ADC1_IN8
-	-	-	-	9	12	16	27	PC1	I/O	FT_a	-	TRACED0, SPI2_MOSI/I2S2_SDO, XSPI1_IO4, ETH1_MDC, XSPI1_IO6, EVENTOUT	ADC1_IN9, ADC2_IN9, TAMP_IN2, WKUP6
-	-	-	-	10	13	17	28	PC2	I/O	FT_a	-	PWR_CSLEEP, TIM17_CH1, TIM4_CH4, SPI2_MISO/I2S2_SDI, XSPI1_IO2, ETH1_MII_TXD2, XSPI1_IO5, EVENTOUT	ADC1_IN10, ADC2_IN10
-	-	-	-	11	14	18	29	PC3	I/O	FT_a	-	PWR_CSTOP, LPUART1_TX, SPI2_MOSI/I2S2_SDO, XSPI1_IO6, XSPI1_IO0, ETH1_MII_TX_CLK, XSPI1_IO4, EVENTOUT	ADC1_IN11, ADC2_IN11
-	-	-	-	-	-	19	30	PH4	I/O	FT_a	-	EVENTOUT	ADC2_IN12, ADC3_IN12
-	-	8	8	12	15	20	31	VREF-	S		-	-	-
5	5	9	9	13	16	21	32	VREF+	S		-	-	-

