

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
-	-	20	20	28	32	37	48	PB2	I/O	FT_a	-	RTC_OUT2, TIM8_CH4N, SPI1_RDY, LPTIM1_CH1, SPI2_SCK/I2S2_CK, SPI3_MOSI/I2S3_SDO, XSPI1_CLK, XSPI1_DQS, ETH1_MII_RXD0/ETH1_RMII_RXD0, EVENTOUT	ADC2_IN8, ADC3_IN2, COMP1_INP3, LSCO
-	-	-	-	-	-	-	49	PF11	I/O	FT	-	XSPI1_NCLK, EVENTOUT	-
-	-	-	-	-	-	-	50	PF12	I/O	FT	-	EVENTOUT	-
-	-	-	-	-	-	-	51	VSS	S		-	-	-
-	-	-	-	-	-	-	52	VDD	S		-	-	-
-	-	-	-	-	-	-	53	PF13	I/O	FT	-	EVENTOUT	-
-	-	-	-	-	-	-	54	PF14	I/O	FT	-	TIM3_ETR, EVENTOUT	-
-	-	-	-	-	-	-	55	PF15	I/O	FT_f	-	TIM4_ETR, I3C1_SDA, ETH1_CLK, EVENTOUT	-
-	-	-	-	-	-	-	56	PG0	I/O	FT	-	TIM4_CH1, EVENTOUT	-
-	-	-	-	-	-	-	57	PG1	I/O	FT	-	TIM4_CH2, SPI2_MOSI/I2S2_SDO, EVENTOUT	-
-	-	-	-	-	33	38	58	PE7	I/O	FT	-	TIM1_ETR, UART7_RX, XSPI1_IO4, EVENTOUT	ADC3_IN3
-	-	-	-	-	34	39	59	PE8	I/O	FT_a	-	TIM1_CH1N, UART7_TX, XSPI1_IO5, EVENTOUT	ADC3_IN4
-	-	-	-	-	35	40	60	PE9	I/O	FT_a	-	TIM1_CH1, UART7_RTS, XSPI1_IO6, EVENTOUT	ADC3_IN5
-	-	-	-	-	-	-	61	VSS	S		-	-	-
-	-	-	-	-	-	-	62	VDD	S		-	-	-
-	-	-	-	-	36	41	63	PE10	I/O	FT_a	-	TIM1_CH2N, UART7_CTS, XSPI1_IO7, EVENTOUT	ADC3_IN6
-	-	-	-	-	-	42	64	PE11	I/O	FT_a	-	TIM1_CH2, SPI1_RDY, XSPI1_NCS1, EVENTOUT	ADC3_IN7
-	-	-	-	-	-	43	65	PE12	I/O	FT_a	-	TIM1_CH3N, ETH1_MDIO, COMP1_OUT, EVENTOUT	ADC3_IN8
-	-	-	-	-	-	44	66	PE13	I/O	FT_a	-	TIM1_CH3, EVENTOUT	ADC3_IN9
-	-	-	-	-	-	45	67	PE14	I/O	FT_a	-	TIM1_CH4, EVENTOUT	ADC3_IN10

