

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
-	-	-	-	52	64	79	112	PC11	I/O	FT_f	-	TIM8_CH2N, I3C1_SDA, SPI3_MISO/I2S3_SDI, USART3_RX, UART4_RX, XSPI1_NCS1, EVENTOUT	-
-	-	-	-	53	65	80	113	PC12	I/O	FT	-	TRACED3, TIM15_CH1, TIM8_CH3N, SPI3_MOSI/I2S3_SDO, USART3_CK, UART5_TX, ETH1_PPS_OUT, EVENTOUT	-
-	-	-	-	-	66	81	114	PD0	I/O	FT	-	TIM8_CH4N, UART4_RX, FDCAN1_RX, XSPI1_NCS2, EVENTOUT	-
-	-	-	-	-	67	82	115	PD1	I/O	FT	-	UART4_TX, FDCAN1_TX, ETH1_MII_RX_DV/, ETH1_RMII_CRS_DV, EVENTOUT	-
-	-	-	-	54	68	83	116	PD2	I/O	FT	-	TRACED2, TIM3_ETR, TIM15_BKIN, UART5_RX, XSPI1_NCS2, EVENTOUT	WKUP7
-	-	-	-	-	-	84	117	PD3	I/O	FT	-	SPI2_SCK/I2S2_CK, USART2_CTS/USART2_NSS, EVENTOUT	-
-	-	-	-	-	-	85	118	PD4	I/O	FT	-	USART2_RTS, ETH1_CLK, XSPI1_IO4, EVENTOUT	-
-	-	-	-	-	-	86	119	PD5	I/O	FT	-	TIM1_CH4N, SPI2_RDY, USART2_TX, FDCAN1_TX, ETH1_MII_CRS, XSPI1_IO5, EVENTOUT	-
-	-	-	-	-	-	-	120	VSS	S		-	-	-
-	-	-	-	-	-	-	121	VDD	S		-	-	-
-	-	-	-	-	-	87	122	PD6	I/O	FT	-	SPI3_MOSI/I2S3_SDO, USART2_RX, XSPI1_IO6, EVENTOUT	-
-	-	-	-	-	-	88	123	PD7	I/O	FT	-	SPI1_MOSI/I2S1_SDO, SPI3_MISO/I2S3_SDI, USART2_CK, XSPI1_IO7, EVENTOUT	-

