

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
28	28	41	41	57	71	91	135	PB5	I/O	FT_f	-	TIM17_BKIN, TIM3_CH2, I3C1_SDA, I2C1_SMBA, SPI1_MOSI/I2S1_SDO, SPI3_MOSI/I2S3_SDO, LPUART1_RTS, FDCAN2_RX, ETH1_PPS_OUT, USART3_CK, TIM8_CH3, UART5_RX, EVENTOUT	-
29	29	42	42	58	72	92	136	PB6	I/O	FT_f	-	TIM4_CH1, I3C1_SCL, I2C1_SCL, SPI3_MISO/I2S3_SDI, USART1_TX, LPUART1_TX, FDCAN2_TX, TIM16_CH1N, USART3_CTS/USART3_NSS, ETH1_MII_TX_ER, TIM8_CH4, UART5_TX, EVENTOUT	-
30	30	43	43	59	73	93	137	PB7	I/O	FT_f	-	TIM17_CH1N, TIM4_CH2, I3C1_SDA, I2C1_SDA, SPI3_SCK/I2S3_CK, USART1_RX, LPUART1_RX, FDCAN1_TX, TIM16_CH1, USART3_RTS, EVENTOUT	WKUP5
31	-	44	44	60	74	94	138	PH2-BOOT0	I/O	FT	-	MCO1, TIM17_CH1N, LPTIM1_IN2, FDCAN1_RX, EVENTOUT	-
32	31	45	45	61	75	95	139	PB8	I/O	FT_f	-	TIM17_CH1, TIM4_CH3, I3C1_SCL, I2C1_SCL, SPI3_NSS/I2S3_WS, UART4_RX, FDCAN1_RX, ETH1_MII_TXD3, XSPI1_NCS1, EVENTOUT	-
-	-	46	46	62	76	96	140	PB9	I/O	FT_f	-	TIM4_CH4, I3C1_SDA, I2C1_SDA, SPI2_NSS/I2S2_WS, SPI3_SCK/I2S3_CK, UART4_TX, FDCAN1_TX, EVENTOUT	-
-	-	-	-	-	77	97	141	PE0	I/O	FT	-	LPTIM1_ETR, TIM4_ETR, SPI3_RDY, FDCAN1_RX, XSPI1_NCS2, EVENTOUT	-
-	-	-	-	-	78	98	142	PE1	I/O	FT	-	LPTIM1_IN2, FDCAN1_TX, EVENTOUT	-
-	32	47	47	63	79	99	143	VSS	S		-	-	-

