BRK - Sub Lattice

User manual and parameter reference · 1.4.1

A polyphonic subtractive synthesizer with two oscillators, two filters and a 16-slot modulation matrix.

Quick start

1. Insert Sub Lattice on an instrument track and play MIDI notes, or use its keyboard.
2. Load a factory preset from the name menu, or start with Init.
3. Turn down a filter cutoff and add an envelope-to-cutoff matrix route to hear the filter move.

Editor window

980 × 995 minimum; resizable. Dimensions are logical editor pixels, before host window chrome. HELP adds 92 pixels of height (Gear adds a one-pixel divider too). Allow enough usable screen space at your display scale. Press HELP again to close the help area.

Operation

Each oscillator supplies its main waveform and a sub oscillator. Tune, Fine and octave controls set pitch; Shape changes the waveform, while FM, Feedback, Ring and the modulation mode add more complex spectra. Oscillator volume and filter balance decide where each source goes.

The two filters can run in series or parallel. Model chooses the circuit; Variant, response and slope depend on that model. Cutoff sets the frequency, resonance emphasizes the boundary, key tracking follows played pitch and drive changes the filter input character.

Amp controls the note level. The three modulation envelopes supply additional movement. Attack rises to the peak, Decay approaches Sustain and Release falls after note-off. Curve controls change each segment, and Sync converts times to note divisions.

The three LFOs offer Free, Sync and Audio rate modes, plus start phase, delay, ramp and retrigger/DAW-phase behavior. A custom waveform can be drawn. The modulation matrix connects sources to targets with an amount, optional Via source, curve and polarity.

Voices, Mono/Legato, Glide, Master Tune, bend range and the MIDI keyboard govern performance. Advanced settings include quality, oscillator/filter options, MPE, modulation interpretation and sync-note choices. Advanced settings belong to the host session and user defaults; loading a sound preset leaves them unchanged.

Use HELP for the hovered or focused control and Manual / PDF for this reference. Tab reaches named controls, arrows adjust values and Return operates focused choices. Envelope and custom-shape drawing still requires a pointer. The minimum editor size is 980 by 995 pixels.

Every parameter

Values and defaults are taken from the plugin. A control's effect can depend on the selected mode; see the operation notes above. Choices keep their saved identity between versions. Knobs and switches can be automated unless marked otherwise.

Parameter	What it does	Values and default
Osc 1 Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Tri, Saw, Square, Noise, Rect, Trap, Organ Default: Saw Not host automatable
Osc 1 Phase	Sets the phase or phase behavior described in the source and synchronization notes.	0 deg to Random Default: 180 deg
Osc 1 Tune	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-48 st to +48 st Default: 0 st
Osc 1 Fine	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-100 ct to +100 ct Default: 0 ct
Osc 1 Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	0% to 100% Default: 0%
Osc 1 Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to x16.00 Default: Off
Osc 1 Sub Level	Sub level	0% to 100% Default: 0%
Osc 1 Drift	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	0% to 100% Default: 0%
Osc 1 Volume	Sets the signal level at this stage. Output is the final listening trim unless the signal-flow notes describe a wet-only output control.	0% to 100% Default: 100%
Osc 1 Sub Octave	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-1 Oct, -2 Oct Default: -1 Oct Not host automatable
Osc 1 Sub Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Square, Saw, Tri Default: Sine Not host automatable
Osc 1 Sub Direct	Routes the first sub oscillator around the filters, directly to the output.	Off to On Default: Off
Osc 1 Filter	Blends the processed and dry signals. The signal-flow notes specify whether Output changes the wet signal alone or the complete blend.	0% to 100% Default: 0%

Parameter	What it does	Values and default
Osc 1 Mod Type	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off, Steps, Blend, Warp, Bits, Fold, Jitter Default: Off Not host automatable
Osc 1 Mod	Sets the first oscillator modulation amount for its selected modulation mode.	0% to 100% Default: 0%
Osc 1 Sync Window	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off
Osc 1 FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	0% to 100% Default: 0%
Osc 1 Feedback	Returns part of a signal to its input. More feedback increases the strength or persistence of the selected effect.	0% to 100% Default: 0%
Osc 1 Ring	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	0% to 100% Default: 0%
Osc 1 Unison	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	1, 2, 3, 4, 5, 6, 7, 8, 9 Default: 1 Not host automatable
Osc 1 Detune	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	0.0 ct to 50.0 ct Default: 10.0 ct
Osc 1 Unison Spread	Spread: how the unison voices sit across the detune range. Even steps, bunched at the centre, pushed to the edges, or a random place per note; between two, a blend.	Even to Random Default: Even
Osc 1 Unison Phase	Phase: where the unison copies start against the oscillator's Phase. Aligned with it, spread evenly around the cycle, alternating half cycles, or random per note; between two, a blend.	Aligned to Random Default: Aligned
Osc 1 Pan	Places or spreads the signal across the stereo field.	L 100 to R 100 Default: C
Osc 1 Unison Width	Width: how far the unison copies fan out either side of Pan, each by its place in the detune layout (the most detuned furthest out). Full by default; 0 keeps them mono.	0% to 100% Default: 100%
Osc 1 Sub Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Off to On Default: Off
Osc 1 Drift Target	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	Pitch, Shape, Both Default: Pitch Not host automatable

Parameter	What it does	Values and default
Osc 2 Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Tri, Saw, Square, Noise, Rect, Trap, Organ Default: Saw Not host automatable
Osc 2 Phase	Sets the phase or phase behavior described in the source and synchronization notes.	0 deg to Random Default: 180 deg
Osc 2 Tune	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-48 st to +48 st Default: 0 st
Osc 2 Fine	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-100 ct to +100 ct Default: 0 ct
Osc 2 Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	0% to 100% Default: 0%
Osc 2 Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to x16.00 Default: Off
Osc 2 Sub Level	Sub level	0% to 100% Default: 0%
Osc 2 Drift	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	0% to 100% Default: 0%
Osc 2 Volume	Sets the signal level at this stage. Output is the final listening trim unless the signal-flow notes describe a wet-only output control.	0% to 100% Default: 0%
Osc 2 Sub Octave	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	-1 Oct, -2 Oct Default: -1 Oct Not host automatable
Osc 2 Sub Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Square, Saw, Tri Default: Sine Not host automatable
Osc 2 Sub Direct	Routes the second sub oscillator around the filters, directly to the output.	Off to On Default: Off
Osc 2 Filter	Blends the processed and dry signals. The signal-flow notes specify whether Output changes the wet signal alone or the complete blend.	0% to 100% Default: 0%
Osc 2 Mod Type	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off, Steps, Blend, Warp, Bits, Fold, Jitter Default: Off Not host automatable

Parameter	What it does	Values and default
Osc 2 Mod	Sets the second oscillator modulation amount for its selected modulation mode.	0% to 100% Default: 0%
Osc 2 Sync Window	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off
Osc 2 FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	0% to 100% Default: 0%
Osc 2 Feedback	Returns part of a signal to its input. More feedback increases the strength or persistence of the selected effect.	0% to 100% Default: 0%
Osc 2 Ring	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	0% to 100% Default: 0%
Osc 2 Unison	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	1, 2, 3, 4, 5, 6, 7, 8, 9 Default: 1 Not host automatable
Osc 2 Detune	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	0.0 ct to 50.0 ct Default: 10.0 ct
Osc 2 Unison Spread	Spread: how the unison voices sit across the detune range. Even steps, bunched at the centre, pushed to the edges, or a random place per note; between two, a blend.	Even to Random Default: Even
Osc 2 Unison Phase	Phase: where the unison copies start against the oscillator's Phase. Aligned with it, spread evenly around the cycle, alternating half cycles, or random per note; between two, a blend.	Aligned to Random Default: Aligned
Osc 2 Pan	Places or spreads the signal across the stereo field.	L 100 to R 100 Default: C
Osc 2 Unison Width	Width: how far the unison copies fan out either side of Pan, each by its place in the detune layout (the most detuned furthest out). Full by default; 0 keeps them mono.	0% to 100% Default: 100%
Osc 2 Sub Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Off to On Default: Off
Osc 2 Drift Target	Adds pitch variation or layers detuned voices. Use a small amount for movement; larger values spread the source more strongly.	Pitch, Shape, Both Default: Pitch Not host automatable
Voices	Voices: drag up or down, double-click to reset. One voice is Mono. Reads active/total while notes play.	1 to 16 Default: 1

Parameter	What it does	Values and default
Legato	Legato. Mono: notes glide from the held note without retriggering, and releasing returns to it. Poly: glide only into notes played over a held one.	Off to On Default: On
Master Tune	Master Tune: shifts every note by any fraction of a semitone, for smooth automation. Drag up or down, Shift for fine steps, double-click to reset. The range is on the Advanced page.	-12.00 st to +12.00 st Default: 0 st
Master Tune Range	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	+/-12 st, +/-24 st, +/-48 st Default: +/-12 st Not host automatable
Bend Range	Bend Range: how far the pitch wheel bends every note at full deflection, in semitones. Drag up or down, double-click to reset to 2 st.	0 st to 48 st Default: 2 st
Glide	Sets the time for pitch to move between notes; Mono/Legato determines when it applies.	0.0 to 1200.0 Default: 0.0
Glide Curve	Glide curve	-1.00 to 1.00 Default: -0.00
Filters Serial	Routes Filter 1 into Filter 2 when enabled; otherwise the filters run in parallel.	Off to On Default: On
Filter 1 Cutoff	Sets the frequency boundary of this filter or band. Its mode and slope determine which frequencies it changes.	20.0 Hz to 20.0 kHz Default: 20.0 kHz
Filter 1 Resonance	Emphasizes frequencies near the filter cutoff; high settings can ring or self-oscillate on some filter models.	0.000 to 1.000 Default: 0.150
Filter 1 Key Track	Moves Filter 1 cutoff with MIDI note pitch.	-100% to +100% Default: 0%
Filter 1 Model	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	SVF, Ladder, Diode, MS-20, Z-Plane, Formant, Comb, Disperse Default: Ladder Not host automatable
Filter 1 Slope	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	12 dB, 18 dB, 24 dB Default: 24 dB Not host automatable
Filter 1 Response	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	LP, HP, BP, Notch Default: LP Not host automatable
Filter 1 Variant	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	1, 2, 3, 4, 5 Default: 1 Not host automatable

Parameter	What it does	Values and default
Filter 1 Drive	Pushes the first filter harder into its nonlinear response.	0.0 to 24.0 Default: 0.0
Filter 1 Drive Type	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	Soft, Hard, Tube, Fold, Rect Default: Soft Not host automatable
Filter 2 Cutoff	Sets the frequency boundary of this filter or band. Its mode and slope determine which frequencies it changes.	20.0 Hz to 20.0 kHz Default: 20.0 kHz
Filter 2 Resonance	Emphasizes frequencies near the filter cutoff; high settings can ring or self-oscillate on some filter models.	0.000 to 1.000 Default: 0.150
Filter 2 Key Track	Moves Filter 2 cutoff with MIDI note pitch.	-100% to +100% Default: 0%
Filter 2 Model	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	SVF, Ladder, Diode, MS-20, Z-Plane, Formant, Comb, Disperse Default: Ladder Not host automatable
Filter 2 Slope	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	12 dB, 18 dB, 24 dB Default: 24 dB Not host automatable
Filter 2 Response	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	LP, HP, BP, Notch Default: LP Not host automatable
Filter 2 Variant	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	1, 2, 3, 4, 5 Default: 1 Not host automatable
Filter 2 Drive	Pushes the second filter harder into its nonlinear response.	0.0 to 24.0 Default: 0.0
Filter 2 Drive Type	Chooses the filter circuit, response or slope. Variants depend on the selected model; see the filter operation notes.	Soft, Hard, Tube, Fold, Rect Default: Soft Not host automatable
LFO 1 Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Tri, Saw, Square, S&H, Noise, Lorenz, Rossler, Custom Default: Tri Not host automatable
LFO 1 Rate	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	0.01 to 30.00 Default: 1.00
LFO 1 Rate Mode	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	Hz, Sync, Audio Default: Hz Not host automatable

Parameter	What it does	Values and default
LFO 1 Phase Mode	Sets the phase or phase behavior described in the source and synchronization notes.	Retrig, DAW Default: Retrig Not host automatable
LFO 1 Audio Rate Hz	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	1.0000000 to 20000.0000000 Default: 110.0000458
LFO 1 Phase	Sets the phase or phase behavior described in the source and synchronization notes.	0 deg to Random Default: 0 deg
LFO 1 Delay	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0
LFO 1 Ramp	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0
LFO 1 Custom Mode	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	Loop, One-shot, Sustain Default: Loop Not host automatable
LFO 2 Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Tri, Saw, Square, S&H, Noise, Lorenz, Rossler, Custom Default: Tri Not host automatable
LFO 2 Rate	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	0.01 to 30.00 Default: 1.00
LFO 2 Rate Mode	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	Hz, Sync, Audio Default: Hz Not host automatable
LFO 2 Phase Mode	Sets the phase or phase behavior described in the source and synchronization notes.	Retrig, DAW Default: Retrig Not host automatable
LFO 2 Audio Rate Hz	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	1.0000000 to 20000.0000000 Default: 110.0000458
LFO 2 Phase	Sets the phase or phase behavior described in the source and synchronization notes.	0 deg to Random Default: 0 deg
LFO 2 Delay	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0

Parameter	What it does	Values and default
LFO 2 Ramp	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0
LFO 2 Custom Mode	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	Loop, One-shot, Sustain Default: Loop Not host automatable
LFO 3 Wave	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Sine, Tri, Saw, Square, S&H, Noise, Lorenz, Rossler, Custom Default: Tri Not host automatable
LFO 3 Rate	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	0.01 to 30.00 Default: 1.00
LFO 3 Rate Mode	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	Hz, Sync, Audio Default: Hz Not host automatable
LFO 3 Phase Mode	Sets the phase or phase behavior described in the source and synchronization notes.	Retrig, DAW Default: Retrig Not host automatable
LFO 3 Audio Rate Hz	Sets the LFO speed. Free mode uses frequency; synchronized mode uses note divisions; audio mode extends the range for audible modulation.	1.0000000 to 20000.0000000 Default: 110.0000458
LFO 3 Phase	Sets the phase or phase behavior described in the source and synchronization notes.	0 deg to Random Default: 0 deg
LFO 3 Delay	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0
LFO 3 Ramp	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0.0 to 5000.0 Default: 0.0
LFO 3 Custom Mode	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	Loop, One-shot, Sustain Default: Loop Not host automatable
Output	Sets the signal level at this stage. Output is the final listening trim unless the signal-flow notes describe a wet-only output control.	-24.0 to 6.0 Default: -3.0
Amp Attack	Sets how quickly this envelope or detector rises. Longer values soften the start; shorter values respond more quickly.	0.0 to 5000.0 Default: 0.0
Amp Decay	Sets the time from the envelope peak to its sustain level.	0.0 to 5000.0 Default: 120.0

Parameter	What it does	Values and default
Amp Sustain	Sets the envelope level held while a note remains down.	0.000 to 1.000 Default: 1.000
Amp Release	Sets the fall after release or the recovery time of the selected processor; see the envelope or detector description above.	Snap to 5000.0 ms Default: Snap
Amp Attack Curve	Attack curve	-1.00 to 1.00 Default: -0.20
Amp Decay Curve	Decay curve	-1.00 to 1.00 Default: -0.30
Amp Release Curve	Release curve	-1.00 to 1.00 Default: -0.30
Amp Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Amp Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off
Env 1 Attack	Sets how quickly this envelope or detector rises. Longer values soften the start; shorter values respond more quickly.	0.0 to 5000.0 Default: 0.0
Env 1 Decay	Sets the time from the envelope peak to its sustain level.	0.0 to 5000.0 Default: 180.0
Env 1 Sustain	Sets the envelope level held while a note remains down.	0.000 to 1.000 Default: 0.000
Env 1 Release	Sets the fall after release or the recovery time of the selected processor; see the envelope or detector description above.	0.0 to 5000.0 Default: 120.0
Env 1 Attack Curve	Attack curve	-1.00 to 1.00 Default: -0.20
Env 1 Decay Curve	Decay curve	-1.00 to 1.00 Default: -0.30
Env 1 Release Curve	Release curve	-1.00 to 1.00 Default: -0.30
Env 1 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Env 1 Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off

Parameter	What it does	Values and default
Env 2 Attack	Sets how quickly this envelope or detector rises. Longer values soften the start; shorter values respond more quickly.	0.0 to 5000.0 Default: 0.0
Env 2 Decay	Sets the time from the envelope peak to its sustain level.	0.0 to 5000.0 Default: 180.0
Env 2 Sustain	Sets the envelope level held while a note remains down.	0.000 to 1.000 Default: 0.000
Env 2 Release	Sets the fall after release or the recovery time of the selected processor; see the envelope or detector description above.	0.0 to 5000.0 Default: 120.0
Env 2 Attack Curve	Attack curve	-1.00 to 1.00 Default: -0.20
Env 2 Decay Curve	Decay curve	-1.00 to 1.00 Default: -0.30
Env 2 Release Curve	Release curve	-1.00 to 1.00 Default: -0.30
Env 2 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Env 2 Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off
Env 3 Attack	Sets how quickly this envelope or detector rises. Longer values soften the start; shorter values respond more quickly.	0.0 to 5000.0 Default: 0.0
Env 3 Decay	Sets the time from the envelope peak to its sustain level.	0.0 to 5000.0 Default: 180.0
Env 3 Sustain	Sets the envelope level held while a note remains down.	0.000 to 1.000 Default: 0.000
Env 3 Release	Sets the fall after release or the recovery time of the selected processor; see the envelope or detector description above.	0.0 to 5000.0 Default: 120.0
Env 3 Attack Curve	Attack curve	-1.00 to 1.00 Default: -0.20
Env 3 Decay Curve	Decay curve	-1.00 to 1.00 Default: -0.30
Env 3 Release Curve	Release curve	-1.00 to 1.00 Default: -0.30

Parameter	What it does	Values and default
Env 3 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Env 3 Sync	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Off to On Default: Off
Mod 1 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Env 1 Not host automatable
Mod 1 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 1 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-10.00 oct to +10.00 oct Default: 0 oct
Mod 1 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 1 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 1 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 1 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Filter 1 Cutoff Not host automatable
Mod 2 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Env 2 Not host automatable
Mod 2 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 2 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-10.00 oct to +10.00 oct Default: 0 oct
Mod 2 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 2 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 2 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 2 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Filter 2 Cutoff Not host automatable
Mod 3 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 3 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 3 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 3 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 3 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 3 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 3 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 4 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 4 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 4 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 4 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 4 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 4 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 4 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 5 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 5 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 5 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 5 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 5 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 5 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 5 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 6 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 6 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 6 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 6 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 6 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 6 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 6 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 7 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 7 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 7 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 7 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 7 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 7 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 7 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 8 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 8 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 8 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 8 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 8 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 8 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 8 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 9 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 9 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 9 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 9 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 9 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 9 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 9 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 10 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 10 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 10 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 10 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 10 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 10 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 10 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 11 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 11 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 11 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 11 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 11 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 11 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 11 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 12 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 12 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 12 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 12 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 12 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 12 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 12 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 13 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 13 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 13 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 13 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 13 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 13 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 13 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 14 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 14 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 14 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 14 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 14 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 14 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 14 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 15 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 15 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 15 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 15 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 15 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 15 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 15 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Mod 16 Source	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 16 Via	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Off, Env 1, Env 2, Env 3, LFO 1, LFO 2, LFO 3, Velocity, Keyboard, Pressure, Mod Wheel, Amp Env, Const, Osc 1, Osc 2 Default: Off Not host automatable
Mod 16 Amount	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-120.0 st to +120.0 st Default: 0 st
Mod 16 Curve	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	-1.00 to 1.00 Default: -0.00
Mod 16 Curve Shape	Chooses or changes the source waveform or curve. Shape changes harmonic content; curve controls change how a segment progresses.	Exp, S-Curve, Sine Default: Exp Not host automatable
Mod 16 Polarity	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Auto, Uni, Bi Default: Auto Not host automatable

Parameter	What it does	Values and default
Mod 16 Target	Configures this modulation route: Source supplies movement, Target receives it, Via scales it, Amount sets depth, and Curve/Polarity shape the movement.	Osc 1 Pitch, Osc 1 Shape, Osc 1 Sync, Osc 1 Sub, Osc 1 Volume, Osc 1 Mod, Osc 1 Pan, Osc 1 FM, Osc 2 Pitch, Osc 2 Shape, Osc 2 Sync, Osc 2 Sub, Osc 2 Volume, Osc 2 Mod, Osc 2 Pan, Osc 2 FM, Filter 1 Cutoff, Filter 1 Res, Filter 1 Drive, Filter 2 Cutoff, Filter 2 Res, Filter 2 Drive, Amp Attack, Amp Decay, Amp Release, Amp A Curve, Amp D Curve, Amp R Curve, Env 1 Attack, Env 1 Decay, Env 1 Release, Env 1 A Curve, Env 1 D Curve, Env 1 R Curve, Env 2 Attack, Env 2 Decay, Env 2 Release, Env 2 A Curve, Env 2 D Curve, Env 2 R Curve, Env 3 Attack, Env 3 Decay, Env 3 Release, Env 3 A Curve, Env 3 D Curve, Env 3 R Curve, LFO 1 Rate, LFO 2 Rate, LFO 3 Rate, Glide Time Default: Osc 1 Pitch Not host automatable
Steal Mode	Chooses how a sounding voice hands over when the voice limit is reached.	Hard, Keep Filter, Free Phase, Zero-Cross, Crossfade, Tail + Snap Default: Tail + Snap Not host automatable
Steal Crossfade	Sets the smoothing time when a voice is stolen.	1.0 to 20.0 Default: 5.0 Not host automatable
Filter Mod Mode	Chooses how the filter interprets modulation; this Advanced option stays unchanged when loading sound presets.	Cutoff in Octaves, Cutoff in Hz Default: Cutoff in Octaves Not host automatable
Pitch Mod Mode	Changes the pitch of this source. Fine tuning is useful for small offsets; octave/semitone controls make larger musical intervals.	Pitch in Semitones, Pitch in Hz Default: Pitch in Semitones Not host automatable
MPE	Enables per-note MIDI expression from an MPE controller.	MPE Off to MPE On Default: MPE On Not host automatable
MPE Bend Range	Sets the pitch-bend range expected from the MPE controller.	1 to 96 Default: 48 Not host automatable
Osc Quality	Selects processing quality. Higher oversampling reduces aliasing at additional CPU cost and can change latency.	PolyBLEP, PolyBLEP + 2x Default: PolyBLEP + 2x Not host automatable

Parameter	What it does	Values and default
Filter Quality	Selects processing quality. Higher oversampling reduces aliasing at additional CPU cost and can change latency.	Filter 1x, Filter 2x Default: Filter 1x Not host automatable
Filter Headroom	Sets the internal level allowance of the filter model; this is an Advanced setting.	0.0 to 24.0 Default: 12.0 Not host automatable
Delay Comp	Controls compensation for internal processing delay; this is an Advanced setting.	0.00 to 5.00 Default: 0.30 Not host automatable
LFO Band Limit	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	Band-limited, Raw Default: Band-limited Not host automatable
Sync Dotted	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	No Dotted to + Dotted Default: + Dotted Not host automatable
Sync Triplets	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	No Triplets to + Triplets Default: + Triplets Not host automatable
Sync Knob	Sets tempo or source synchronization for this section. The related time/rate control then follows the selected synchronization mode.	Snap, Smooth Default: Snap Not host automatable
LFO Seed	Controls repeatable modulation or its timing. The saved seed makes random movement repeat; phase and synchronization decide where it starts.	0 to 9999 Default: 1 Not host automatable
Osc 1 Linear FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off to On Default: Off
Osc 2 Linear FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off to On Default: Off
Osc 1 Exp FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off to On Default: Off
Osc 2 Exp FM	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	Off to On Default: Off
FM Style	Controls oscillator modulation. These modes change harmonic content; consult the oscillator modulation notes before combining large amounts.	FM Original, FM True PM Default: FM True PM Not host automatable

Presets and files

Presets are browsed with the arrows or the preset-name menu. A star marks an edited patch. Save supports folders, Rename, Delete and opening the user preset folder; dropping a compatible preset file onto the bar loads it. A newer-file indication means this version could not apply every setting.

The host session stores the complete patch. A product preset can deliberately leave listening trim, audition or display controls unchanged; the product-specific rules below describe those exceptions.

User presets use .sublattice in ~/Library/Audio/Presets/Barakigal Audio/Sub Lattice. Sub Lattice presets include Output but leave Advanced settings unchanged. Sessions retain Advanced settings and custom LFO shapes. Very early presets without choice IDs retain their original index interpretation; older modulation mappings may need checking.

Installation and help

Download the macOS archive from the product page and quit your audio host. Place the AU .component in ~/Library/Audio/Plug-Ins/Components, VST3 in ~/Library/Audio/Plug-Ins/VST3, or CLAP in ~/Library/Audio/Plug-Ins/CLAP. The product page also offers an installer with format selection. Restart or rescan the host. To uninstall, quit the host and remove that product's bundles from those folders; saved sessions and user presets are separate.

For questions or a problem report, use BRK Audio support on GitHub. Include the plugin version, macOS version, host and format, sample rate and a short description of how to reproduce it.