



Organ Model PT339

TYPICAL SPECIFICATION *Three Manual Lighted Tab Console*

PEDAL

1 Contra Violone	32
2 Principal	16
3 Bourdon	16
4 Dulciana	16
5 Octave	8
6 Bass Flute	8
7 Choral Bass	4
8 Mixture	III
9 Posaune	16
10 Trumpet	8
(i) Great to Pedal	
(ii) Swell to Pedal	
(iii) Choir to Pedal	
(iv) Midi to Pedal	

ACCESSORIES

Program Display (LCD)
Two Specifications
Expression pedal to the Swell organ
Expression pedal to the Choir organ
Programmable Crescendo Pedal
Multi- program Lexicon MPX110 reverb
Reverb level control
Overall volume control
Transposer +3/-3
Fine Tune
Capture lock switch
Pedal light

TECHNICAL DATA

Manuals: 3x61 notes
Pedals: 32 note AGO
Audio: Yamaha XM6150
Power Amplifier--
6 x100 watts RMS
Input: 2 channel socket
Midi: In, Out, Thru
Headphones socket

GREAT

1 Open Diapason	8
2 Chimney Flute	8
3 Dulciana	8
4 Octave	4
5 Harmonic Flute	4
6 Fifteenth	2
7 Fourniture	IV
8 Tromba	8
(i) Tremulant	
(ii) Swell to Great	
(iii) Choir to Great	
(iv) Gt & Ped on Choir	
Expression	
(v) Auto Pedal	
(vi) Midi to Great	

COMBINATION ACTION

6 Thumb pistons to the Swell organ
6 Thumb pistons to the Great organ
6 thumb pistons to the Choir organ
8 General thumb pistons

1 rev. thumb piston Swell to Great
1 rev. thumb piston Swell to Pedal
1 rev. thumb piston Swell to Choir
1 rev. thumb piston Great to Pedal
1 rev. thumb piston Choir to Great
1 rev. thumb piston Choir to Pedal
1 thumb piston General Cancel
1 thumb piston Setter

3 thumb pistons Program, + and -

SWELL

1 Geigen Diapason	8
2 Claribel Flute	8
3 Viola di Gamba	8
4 Voix Celeste	8
5 Principal	4
6 Lieblich Flute	4
7 Fifteenth	2
8 Mixture	III
9 Double Trumpet	16
10 Trumpet	8
11 Oboe	8
12 Clarion	4
(i) Tremulant	
(ii) Midi to Swell	

CHOIR

1 Bourdon	8
2 Salicional	8
3 Spire Flute	4
4 Block Flute	2
5 Cornet	II
6 Scharf	III
7 Clarinet	8
8 Tuba	8
9 Chimes	
(i) Tremulant	
(ii) Swell to Choir	
(iii) Midi to Choir	