



Organ Model PD245

TYPICAL SPECIFICATION

Two Manual Drawknob Console

PEDAL

1	Contra Violone	32
2	Principal	16
3	Bourdon	16
4	Lieblich Gedeckt	16
5	Dulciana	16
6	Octave	8
7	Bass Flute	8
8	Choral Bass	4
9	Open Flute	4
10	Mixture	IV
11	Bombarde	32
12	Trombone	16
13	Trumpet	8
14	Clarion	4

- (i) Great to Pedal
- (ii) Swell to Pedal
- (iii) Auto Pedal
- (iv) Midi to Pedal

GREAT

1	Gemshorn	16
2	Open Diapason	8
3	Rohrflöte	8
4	Dulciana	8
5	Unda Maris II	8
6	Octave	4
7	Stopped Flute	4
8	Twelfth	2-2/3
9	Super Octave	2
10	Fourniture	IV
11	Cymbel	III
12	Trumpet	8
13	Chimes	

- (i) Tremulant
- (ii) Swell to Great
- (iii) Great/Pedal Pistons
Coupled
- (iv) Midi to Great

SWELL

1	Bourdon	16
2	Geigen Diapason	8
3	Stopped Diapason	8
4	Salicional	8
5	Voix Celeste	8
6	Principal	4
7	Harmonic Flute	4
8	Nazard	2-2/3
9	Fifteenth	2
10	Block Flute	2
11	Tierce	1-3/5
12	Larigot	1-1/3
13	Plein Jeu	IV
14	Double Trumpet	16
15	Cornoepen	8
16	Oboe	8
17	Vox Humana	8
18	Clarion	4

- (i) Tremulant
- (ii) Midi to Swell

ACCESSORIES

Program Display (LCD)
Three Specifications
Multi-program Lexicon MPX110 reverb
Reverb Level control
Reverb Time control
Overall volume control
Transposer +3/-3
Fine Tune
Expression pedal to the Swell organ
Expression pedal to the Great organ
Programmable Crescendo Pedal
Capture lock switch
Pedal light

COMBINATION ACTION

6 Thumb pistons to the Swell organ
6 Thumb pistons to the Great organ
6 Toe pistons to the Pedal
8 General thumb pistons
8 General Toe pistons
16 Combination memories

1 reversible thumb piston Swell to Great
1 reversible thumb piston Swell to Pedal
1 reversible thumb piston Great to Pedal
1 reversible toe piston Great to Pedal
1 thumb piston General Cancel
1 thumb piston Setter
1 thumb piston “-”
1 thumb piston “+”
1 thumb piston “FN”

TECHNICAL DATA

Manuals: 2 x 61 notes
Pedals: 32 notes AGO
Audio: 6 x 120 W
Input: 2 channel socket
Midi: In, Out1, Out2 sockets
Headphones socket