FROM PARKESTON
POWER STATION
33kV OVERHEAD LINE
FIM A (BY KCGM)

33kV OVERHEAD LINE
FIM A POLE FA35
RECLOSER

NSR
ENABLING WORKS
PRIMERO
PROJECT SCOPE

33kV INCOMER 1
FROM PARKESTON POWER STATION
33kV OVERHEAD LINE FIM A
POLE FA42 (BY KCGM)

33kV OVERHEAD LINE
FIM A POLE FA42
RECLOSER

NSR
ENABLING WORKS
PRIMERO
PROJECT SCOPE

NOTES

1. FOR DETAILS OF 33kV PLANT HV DISTRIBUTION SWITCHBOARD THREE POSITION DISCONNECT/EARTH SWITCHES, BREAKERS AND BUS TIES REFER TO 2000-F00-SLD-EL-10002 .. -10006. FOR KEY INTERLOCKING, REFER TO KEY INTERLOCKING DIAGRAMS 2000-F00-SLD-EL-10051 .. -10055

F00-SR-001
PLANT 33kV HV DISTRIBUTION SWITCHROOM

F00-SW-010
PLANT 33kV HV DISTRIBUTION SWITCHBOARD

2000-F00-SLD-EL-10002

2000-F00-SLD-EL-10003

36kV 2000A 3~E 31.5kA FOR 3s

B01 B02 B03 B04 B05 B06 B07 B08 B09

2000A

630A 630A 630A 630A 2000A 630A 630A 630A

CONT'D ON SHEET 2 DRG 2000-F00-SLD-EL-10011

F12-TR-012
33 / 11 kV
5000 kVA

F12-SR-001
PRIMARY CRUSHING
11kV SWITCHROOM

630A
11kV 1250A 3E~
F12-SW-012
PRIMARY CRUSHING
11kV SWITCHBOARD
2000-F12-SLD-EL-10001
630A

F12-GE-101
415V 400kVA

F12-SR-002
PRIMARY CRUSHING
415V SWITCHROOM

F12-TR-001
11 / 0.433 kV
2500 kVA

630A 400A 4000A
415V 630A 3NE~ 415V 4000A 3NE~
F12-SW-101
PRIMARY CRUSHING
415V ESSENTIAL SWB
2000-F12-SLD-EL-10211
F12-SW-001
PRIMARY CRUSHING
415V MCC
2000-F12-SLD-EL-10201

F13-SW-102
2000-F00-SLD-EL-10011

F13-GE-103
415V 550kVA

F13-SR-002
BALL MILL
415V SWITCHROOM

F13-TR-003
33 / 0.433 kV
2500 kVA

250A 800A 800A 4000A
415V 1000A 3NE~ 415V 4000A 3NE~
F13-SW-103
BALL MILL
415V ESSENTIAL SWB
2000-F13-SLD-EL-10911
F13-SW-003
BALL MILL
415V MCC
2000-F13-SLD-EL-10901

33kV SPARE
(1)

FULLY
EQUIPPED

33kV INCOMER
AND VT (1)

-

33kV BUS TIE
(1)

FULLY
LOAD RATED

F28-GE-109
415V 250kVA

F28-SR-002
ULTRAFINE GRINDING
415V SWITCHROOM

F28-TR-009
33 / 0.433 kV
1000 kVA

400A 1600A
415V 600A 3NE~ 415V 1600A 3NE~
F28-SW-109
ULTRAFINE GRINDING
415V ESSENTIAL SWB
2000-F28-SLD-EL-10211
F28-SW-009
ULTRAFINE GRINDING
415V MCC
2000-F28-SLD-EL-10201

F28-TR-013
33 / 11 kV
12500 kVA

F28-SR-001
ULTRAFINE GRINDING
11kV SWITCHROOM

1250A
11kV 1250A 3E~
F28-SW-013
ULTRAFINE GRINDING
11kV SWITCHBOARD
2000-F28-SLD-EL-10001

F13-GE-114
415V 250kVA

F13-SR-004
RECYCLE CRUSHING
415V SWITCHROOM

F13-TR-014
33 / 0.433 kV
2500 kVA

400A 400A 4000A
415V 600A 3NE~ 415V 4000A 3NE~
F13-SW-114
RECYCLE CRUSHING
415V ESSENTIAL SWB
2000-F13-SLD-EL-10411
F13-SW-014
RECYCLE CRUSHING
415V MCC
2000-F13-SLD-EL-10401

25400kVA
33 / 3.8 / 3.8kV
33 / 3.8 / 3.8kV
33 / 0.415 / 0.415kV

F13-TR-402
BALL MILL
VSD TRANSFORMER
2000-F00-SLD-EL-10002

F13-SR-003
SAG AND BALL MILLS
HV VSD SWITCHROOM

2
SM 3~ F13-MB-401A
10000kW
BALL MILL
MOTOR 1

SM 3~ F13-MB-401B
10000kW
BALL MILL
MOTOR 2

5600kVA
33 / 3.8kV

F13-TR-403
CYCLONE FEED PUMP
VSD TRANSFORMER
2000-F00-SLD-EL-10003

F13-SR-003
SAG AND BALL MILLS
HV VSD SWITCHROOM

CONT'D ON SHEET 2
DRG 2000-F00-SLD-EL-10011

2
M 3~ F13-PP-401
4800kW
CYCLONE
FEED PUMP

NORTHERN STAR
NORTHERN STAR MINING

Approved	X
Approved as Noted	
Not Approved	
For Information Only	

ACCEPTANCE DOES NOT RELIEVE THE SUPPLIER / CONTRACTOR OF ITS RESPONSIBILITY OR LIABILITIES UNDER THE PURCHASE ORDER / CONTRACT

2000-F00-SLD-EL-10001_Rev2

Single line diagram sheet 1