PARTIALLY AS CONSTRUCTED

R03 5

415V 3 PHASE + NEUTRAL 50Hz 2500A FORM 4 FAULT LEVEL 50kA FOR 1 sec.

CONTINUED DWG 34\E\0021-001

F02 1 — 50A — AFS
F35-PP-448 — F35SPP448-VS — VSD — M — 15 kW — 1RL3
F35-PP-448 — FEED CIRCUIT 2 — REF DWG: 2000-F34-SCM-EL-10003
TO SUBSTATION COMMS RACK

F02 2 — 20A — 1RL2 — AFS
F35-PP-435 — F35SPP435-VS — VSD — M — 5.5 kW — 1RL2
F35-PP-435 — UFG CIRCUIT 1 — FEED PUMP — REF DWG 2000-F34-SCM-EL-10002
TO SUBSTATION COMMS RACK

F02 3 — 100A 160A — AFS
F35-PP-61B — F35-PP-61BVS — VSD — M — 30 kW
F35-PP-61B — ULTRA FINE GRINDING CONCENTRATE THICKENER U/F PUMP B — REF. DWG. 34\E\0041-018
TO PROCESS CONTROL CUBICLE

F02 4 — 100A 160A — CA-60 — AFS
F35-PP-61A — F35-PP-61AVS — VSD — M — 30 kW
F35-PP-61A — ULTRA FINE GRINDING CONCENTRATE THICKENER U/F PUMP A — REF. DWG. 34\E\0041-010
TO PROCESS CONTROL CUBICLE

F02 5 — 315A 400A — CA6-210-EI @ 350A — AFS
F35-PP-63A — F35-PP-63AVS — VSD — RTD — M — NOTE 2. — 110 kW — 2
SPARE
F35-PP-63A — ULTRA FINE GRINDING CYCLONE FEED PUMP A — REF. DWG. 34\E\0041-010 — 2000-F34-SCM-EL-10005
TO PROCESS CONTROL CUBICLE

F03 1 — AFS
SPARE

F03 2 — 63A — AFS
F34-XE-02 — SUBSTATION No.10 240V UN INTERRUPTABLE POWER SUPPLY — REF. DWG. 34\E\0041-004
11
F34-XE-02F — SUBSTATION No.10 240V/110V PROTECTION EQUIPMENT SUPPLY — REF. DWG. 20\E\0421-002 & 20\E\0001
BYPASS SWITCH & TRANSFORMER — 240V — 110V

F03 3 — 80A 100A — AFS
SPARE

F03 4 — 125A 200A — CA-72 — AFS
F34-PP-01 — F34-PP-01VS — VSD — M — 37 kW
F34-PP-01 — ULTRA FINE GRINDING MILL FEED PUMP — REF. DWG. 34\E\0041-010
TO PROCESS CONTROL CUBICLE

F03 5 — 315A 400A — CA6-210-EI @ 350A — AFS
F35-PP-63B — F35-PP-63BVS — VSD — RTD — M — NOTE 2. — 110 kW — 2
F35-PP-63B — ULTRA FINE GRINDING DESLIME CYCLONE FEED PUMP B — FEED PUMP B — REF. DWG. 34\E\0041-010 — 2000-F34-SCM-EL-10005
TO PROCESS CONTROL CUBICLE

F04 1 — AFS
SPARE

F04 2 — 20A 32A — 415V/110V 2KVA — 16A — AFS
34-TR-03 — 110V SUPPLY — MCC 34-SW-01 — REF DWG 34\E\0041-001 ONWARDS

F04 5 — 110kW DRIVE PANEL 35-AG-61B — 2
35-AG-61B — FILTER FEED TANK No.2 AGITATOR — REF. DWG. 2000-F34-SCM-EL-10102

Approved ☒
Approved as Noted ☐
Not Approved ☐
For Information Only

ACCEPTANCE DOES NOT RELIEVE THE SUPPLIER / CONTRACTOR OF ITS RESPONSIBILITY OR LIABILITIES UNDER THE PURCHASE ORDER / CONTRACT

F02 2 — 63A — AFS
SPARE

R03 6 — 50A — AFS
F34-PP-443 — F34PP443-VS — VSD — M — 22 kW — 1RL3
F34-PP-443 — UFG MILL 1 PRODUCT PUMP — REF DWG: 2000-F34-SCM-EL-10001
TO SUBSTATION COMMS RACK

F35-PP-449 — F35PP449-VS — VSD — M — 15 kW — 2
F35-PP-449 — UFG CIRCUIT 3 FEED PUMP — REF. DWG: 2000-F34-SCM-EL-10004
TO SUBSTATION COMMS RACK

R03 7 — 10A 63A — AFS
F34-FV-01 — UFG VIBRATING FEEDER — REF. DWG 34\E\0041-xxx
xx kW

R03 8 — 6A 63A — AFS
F34-HE-01 — ULTRA FINE GRINDING MILL DRIVE HEATER — REF. DWG 34\E\0041-004
0.75 kW

R04 1
SPACE

R04 2 — 10A 63A — CA7-9 — AFS
F34-FN-01 — ULTRA FINE GRINDING GEARBOX OIL COOLING FAN — REF. DWG 34\E\0041-004
1.5 kW

R04 3 — 100A 100A — CA7-60 — AFS
F35-AG-62 — ULTRA FINE GRINDING PLANT FEED TANK AGITATOR — REF. DWG. 34\E\0041-006
TO PROCESS CONTROL CUBICLE
80/5 W — A/mA
30 kW — 2

R04 4 — 125A 60A — CA-76 — AFS
F35-PW-62 — ULTRA FINE GRINDING PLANT FEED PUMP — REF. DWG 34\E\0041-006
TO PROCESS CONTROL CUBICLE
125/5 W — A/mA
37 kW

R04 5 — 250A 400A — CA6-210-EI @ 350A — NOTE 3 — AFS
F35-AG-61B — ULTRA FINE GRINDING FILTER FEED TANK AGITATOR — REF. DWG. 34\E\0041-007
TO PROCESS CONTROL CUBICLE
250/5 W — A/mA
RTD — M — 110 kW — 2
SOFT STARTER
1RL1 — 2

NOTES
1. ALL AFS (ARC FLASH SENSORS) ARE CONNECTED TO THE ARC FLASH RELAY VIA I/O UNITS.
2. VSD OUTGOING FIELD CABLES DISCONNECTED AND MADE SAFE AT BOTH ENDS.
3. BUCKET R04/5 EQUIPMENT IS NOT TO BE MODIFIED. BYPASS THE CONTACTOR ONLY AND LEAVE INSITUE. NEW CABLE TERMINATES TO LOAD SIDE OF EXISTING FUSED SWITCH

LEGEND
- COMBINED FUSE SWITCH
- CONTACTOR
- OVERLOAD
- VSD — VARIABLE SPEED DRIVE
- RTD
- THERMISTOR
- LOCAL CONTROL STATION
- M — MOTOR
- BUCHHOLZ PROTECTION
- PQM — POWER QUALITY METER
- LINK
- FUSE
- UPS
- OVERCURRENT RELAY WITH TIME LAG
- I INST — INSTANTANEOUS EARTH CURRENT RELAY
- A mA — AMP SIGNAL CONVERTOR
- 5 20A — GPO
- HEATER
- CONTROL TRANSFORMER
- TRANSFORMER
- WITHDRAWABLE BREAKER HEATER
- DISTRIBUTION BOARD
- SOFT STARTER

LEGEND
- STAGE 1 - NEW
- STAGE 1 - REMOVE
- STAGE 1 - DECOMMISSIONED (OTHERS)
- STAGE 2 - NEW
- STAGE 2 - REMOVE
- STAGE 2 - DECOMMISSIONED (OTHERS)

KCGM GROWTH PROJECT
DRAWING NO: 2000-F34-SLD-EL-10102

1RL3	20/07/26	AS CONSTRUCTED FOR SP1
1RL2	04/06/26	AS CONSTRUCTED FOR F34.20.01

2000-F34-SLD-EL-10102_Rev2

Substation no 10 415V MCC 34-SW-02 - single line diagram