



Duress Watch Security System Training Manual





Table of Contents

SECTION 1: INTRODUCTION	3
SECTION 2: OVERVIEW & UNDERSTANDING THE WATCH ARMOUR SYSTEM	4
SECTION 3: FITTING THE WATCH.....	5
SECTION 4: UNDERSTANDING THE BUTTONS AND WHAT THEY DO.....	6
SECTION 5: USING YOUR WATCH (DAILY OPERATION).....	6
SECTION 6: LOG OFF AT THE END OF YOUR WORKDAY.....	7
SECTION 7: ALARM ACTIVATION AND RESETTING.....	7
SECTION 8: HOW TO ACTIVATE THE WATCH IN CASE OF EMERGENCY	8
SECTION 9: ACKNOWLEDGE EVENTS FROM OTHER STAFF MEMBERS.....	9
SECTION 10: CANCELLING AND RESETTING AN ALARM.....	9
SECTION 11: CHARGING YOUR WATCH.	10
SECTION 12: TESTING THE WATCH SYSTEM.....	10
SECTION 13: POWER DOWN OR RESET THE WATCH	10
SECTION 14: TROUBLESHOOTING	11
SECTION 15: CONTACTING THE TECHNICAL TEAM.....	11
SECTION 16: CONCLUSION	11

Section 1: Introduction

Welcome to the Watch Armour Duress System Training Manual.

This manual has been created to help you understand the importance and functionality of the Watch Armour System that is installed in this branch.

The Watch Armour System assists in the safety of employees and customers and works in hand with the existing OH&S policy for when staff are faced with an aggressive or threatening customer or robbery.

When the Watch is triggered, the system instantly alerts the other staff within the site wearing a watch.

Note: The Watch Armour is not a replacement for the **Fixed Point** alarms (holdup or duress) In a REAL incident, the watches should be used in conjunction with the fixed devices.

All events activated are sent to the Security Control Room in case of emergency situations.

The Watch Armour is worn from the time you begin your days' work, until you finish your day.

It is advised that this manual be kept handy and reviewed regularly.

Your safety and the safety of your fellow team members are the reason the Watch Armour is installed.

Section 2: Overview & Understanding the Watch Armour System

You won't need to understand the technical side of the system, however, knowing what it does and why it does it is an advantage.

Health and safety of staff at the workplace is the number one concern of the company. OH&S begins with you and your fellow staff members.

If you have ever been involved in such an incident, you will know, it's important that all staff are aware of the risk and or danger of being involved in such an incident.

The Watch Armour is a bespoke system that has been designed around the existing OH&S systems already in place in your workplace.

The Watch Armour has a Built in GPS - the location of the wearer is sent to Monitoring only when the watch has been activated.

The Watch Armour has a High-Definition Microphone built in. The Microphone is used to record 30 Seconds of audio that begins when the alarm event is activated. The recording is instantly sent to a Secure Server for storage, and if required, can be used for evidential purposes.

The Watch Armour is a security & safety device. Therefore, the Step Counter, Heart Rate Monitor, Calendar, Camera, and all other features are disabled and cannot be remotely activated. Therefore, nobody can watch, listen, or track you while wearing the watch. Unless of course it has been activated.



Section 3: Fitting the Watch

Fitting of the watch to your preferred wrist

The correct fitting of the watch band is essential for the comfort and functionality of a Watch Armour. The band ensures that the watch is securely fastened to the wrist, preventing it from sliding around or falling off. It also ensures that the watch is positioned correctly on the wrist, allowing for easy access to Watch Armour functions.

Fitting Watch Armour silicone or cloth Velcro band to a wrist is an easy process. Follow these steps:

Silicone bands:

1. Place the Watch Armour on your preferred wrist with the Crown Button located on the top right side of the watch.
2. Squeeze both sides of the band to the underside of your wrist.
3. Place the silver locating pin into the closest hole on the longer side. Ensure its not too tight or too loose.
4. Once comfortable, tuck the long side into the slot on the shorter side (below the silver pin) securing the end of the band.

Cloth Velcro bands:

1. Place the Watch Armour on your preferred wrist by sliding your hand through the band with the Crown Button located on the top right side of the watch.
2. Pull the loose end of the band until the watch is comfortable on your wrist.
3. Push the loose end against the band to secure the band onto your wrist.

You should be able to fit a Watch Armour silicone or Velcro band to your wrist easily and comfortably.

Section 4: Understanding the buttons and what they do.



The Watch Armour has been designed for ease of use.

Discreet Activation Location

Crown Activation Button

Power/Wake Button

Multi Touch Button

Discreet Activation Button:

This is a discreet method of activating an alarm on the watch without being detected by the offender/aggressor and escalating the event to another level.

Crown Button:

The Crown Button is used to Activate an Alarm Event

Power/Wake Button:

The Power/Wake Button is used to Wake the Screen and or Power On or Off the watch

Multi Touch Button

The Multi Touch Button is used to Log On/Off the Watch & Reset Active Alarms

Section 5: Using your Watch (Daily Operation)

Your watch has been assigned an individual name to identify who is wearing it. There may be some watches named a Spare.

Select your watch from the charger pad on the wall and fit to your preferred wrist.

- Push the Power/Wake Button to wake the screen. If the screen doesn't appear, Hold the Power/Wake button in and the watch will begin the start up process.
- Press the Logo at the bottom (Multi Touch Button) and hold until the login screen appears. (You will feel your watch vibrate/pulse).
- Enter the login PIN "1 2 3 4 5 6" and the OK button. (*May take a few seconds to log in*)
- The watch will display a spinning circle in the top centre next to the time. This indicates that the watch is connected to the Watch Armour System.
- Your name will also appear in the centre of the watch.

You have now logged on.

Section 6: Log Off at the end of your Workday.

It is very important the watches are logged off at the end of your working day and placed back onto the charger. The system will send any software updates when it's logged off as well as ensuring the system operation.

- To Log Off - Tap and hold the Multi Touch Button at the bottom of the screen, 5 pulses will be felt when Logging Off the watch.
- Place the watch back onto the charger ensuring the charger pins meet the pins on the watch.

Note: If a watch is left logged on and placed back on the charger, it will be automatically logged off overnight.

Section 7: Alarm Activation and Resetting

It is very important that you know how to activate an event on your watch.

In the event of an incident, there are 2 methods of activation on Watch Armour. Depending on the situation, **ORANGE** activations indicate a High possibility of a threat to the staff member and **RED** activations are when there is an actual threat or event.

A Relay Board installed interconnects the Watch Armour system to the branches security system. Should a Fixed Hold up or Duress Pendant be pressed the watches will display **RED** alarm with the words "**Branch Alarm**" to alert staff of the event.

ORANGE It is the First level of Alarm and is used to advise other users in the group that the user requires assistance. **ORANGE** would be activated if there is an issue pending, or lower priority event that all staff need to be alerted too.

RED It is the Second Level of Alarm and is used to advise other users in the branch that the user is in trouble or a dangerous situation and requires URGENT assistance. The **RED** level would be activated in the event of robbery, aggressive customer or other dangerous events that may arise.

Each event is sent to every watch that is logged on within the site as well as to the Security Control Room for appropriate action events.

Note: The **Orange** and **Red** alarms when sent to the SMC are acted upon the same as a Hold Up or Duress alarm. The SMC will not differentiate between **Orange** & **Red**. The **Orange** & **Red** events are for identifying the priority of the event for the purposes of your branch OH&S or "See Something, Do Something" actions upon an event occurring. It is very important to also press a fixed alarm (if & when possible).

Section 8: How to activate the Watch in case of emergency

Activation using the Crown Button to create an Alert

- Press and hold the crown button in and the watch will vibrate 3 times and an **Orange Alert** will appear on your watch - all other watches in the Group/Branch will receive this alert. Release the crown and the watch remains in the **Orange** alert state. Security Monitoring will be advised that you have an incident and require assistance.



- To escalate the event to a **Red Alert** from an **Orange Alert**, press the Crown Button again and hold until the **Red Alert** activates. All other watches will receive this alert, and the Security Monitoring Centre will be advised that you have a critical incident and require urgent assistance.



- To activate a **Red Alert** instantly (and bypass an **Orange Alert**), press the Crown Button and hold until the **Red Alert** activates (6 pulses). All other watches will indicate this alert, and the Security Monitoring Centre will be advised that you have a critical incident and require urgent assistance.

Activation using the Touch Screen to create an Alert

- Touch and hold the Spinning Circle and the watch will vibrate 3 times and an **Orange** alert will appear on your watch, and all other watches in the Group/Branch. Release and the **Orange alert** will remain. The Security Monitoring Centre will be advised that you have an incident and require assistance.



- To escalate the event to a **Red Alert** from an **Orange Alert**, touch and hold the Spinning Circle and the watch will vibrate 3 times the **Red Alert** activates. All other watches will indicate, and the Security Monitoring Centre will be advised that you have a critical incident and require urgent assistance.



- To activate a **Red Alert** instantly, touch and hold the Spinning Circle and the watch will vibrate 6 times the **Red Alert** activates. All other watches will indicate, and the Security Monitoring Centre will be advised that you have a critical incident and require urgent assistance.

Section 9: Acknowledge Events from other Staff Members

When an **Orange** or **Red** Alert is activated, acknowledging the event indicates to all staff that the event has been acknowledged and action is being taken.

Acknowledging an Event

The **Orange** or **Red** Alert on your watch from a co-worker, can be acknowledged by touching the event and holding until the exclamation mark appears in the event. Only Acknowledge if you can aid assistance. (Assistance could be just calling Police for example)
The event only requires acknowledgment once.

Not acknowledged



If there is an exclamation mark in the event, it has already been acknowledged by another colleague.

Acknowledged



On ALL alarms, ensure you follow the Branch See Something, Do Something instructions.

Section 10: Cancelling and Resetting an Alarm

To Reset/Cancel the activation, reset the alarms at the codepad (Area 4) and the watches will all reset.

Section 11: Charging your watch.

The watch in normal standby mode, will last from 18 to 24 hours therefore it must be logged off and placed back on charge at the end of each day/shift.

This will allow for the device to be on full charge at the start of the next day.

Watch Armour takes approximately 2 to 3 hours to fully charge from flat. If the watch is going to be left unused for an extended period, we suggest you power down the watch and store it in a drawer. **IMPORTANT:** *If unused devices are left on the charger for long periods, It is possible to cause damage to the battery and the watch. Should visible damage be noted, raise a job for a security technician to attend the branch to check.*

Section 12: Testing the Watch System

The watch system is always active. Testing of the system should be carried out monthly or when testing the branch security system.

NOTE: Watch testing **IS NOT** included in the monthly Branch Alarm testing.

Recommended Testing Procedure:

1. Call the SMC and advise you are going to be testing the watches.
2. All staff are wearing their watch and logged in.
3. Activate only one device only to a **RED Alert**.
4. Ensure the **RED Alert** is received on the other logged on watches.
5. Ensure the Red Warning lights have been activated.
6. Have a staff member Acknowledge the Red Alert by touching the red alert in their watch.
7. Check the Acknowledge symbol () appears on all devices in the **RED Alert**.
8. Reset the Security system Area 4. This will reset all devices.

The above procedure will prove the systems operation.

NOTE: It is recommended that a different watch is triggered each Month.

Section 13: Power down or Reset the Watch

1. Log out of Watch then Hold down the 'Power/Wake' button and select Red Power Button to shut down watch. This will conserve the current battery level until it is restarted.
2. To start the watch from a powered down state, hold down the Power/Wake button for 5 seconds and the watch will begin the start-up process.

Section 14: Troubleshooting

a. Resetting the Branch Alarm event on the Watch



The Branch Alarm event is triggered when a Hold Up or Duress Alarm is activated within the branch. It is to alert Watch wearers of a possible incident within the Branch. The alarm can only be reset at the Security System Codepad within the Bunker or the main Codepad that's used to arm and disarm the branch.

b. Changing the Name on a Watch

The name on the watch is very important to keep up to date. As staff come and go and or change from branch to branch the wearers name needs to be updated.

Contact the ANZ Properties team to request the name change. You will need the Watch Number, if not known, the watch will have a 3 or 4-digit number under the current name, e.g. "Peter 399". Provide that number and the new name. The number will be required for all name changes to establish the actual watch that requires the change.

NOTE: The watch **MUST** be logged **OFF** before the name can be changed.

Section 15: Contacting the technical team.

As with any fault with the Security System, including the Watch Armour, follow your standard procedure for reporting faults by raising a Security Work Order.

For Watch Name changes, refer to section 14 in the manual. Raise a job with Properties and request names to be changed.

Section 16: Conclusion

The Watch Armour Duress System is a critical component in ensuring the safety of employees and customers.

This training manual should serve as a comprehensive guide to understanding the system and following the best practices to ensure it functions effectively.

Please review this manual regularly, and if you have any questions or concerns, do not hesitate to contact the technical team.

For any additional information contact **SCSI Pty Ltd** on 1300 555 570 or 0408 422 540