



WISEPILL DISPENSER USER MANUAL

USING THE WISEPILL DISPENSER



SOMERSET WEST
SOUTH AFRICA
(ISSUE V 1.2)

WISEPILL DISPENSER USER MANUAL

USING THE WISEPILL DISPENSER

ABOUT THE WISEPILL DISPENSER

The Wisepill portable medication dispenser has a cellphone communication chip at its heart. Every time the dispenser is opened, the dispenser sends a medication event to a central management system (Wisepill Web Server).

Medication records are stored securely on the Wisepill Database and can be accessed securely using the Wisepill Web Application.

The Wisepill Web Server can be configured to send reminder text messages to a mobile phone.

You will need:

- 1) *Wisepill Dispenser*
- 2) *Wisepill Charger*



PARTS OF THE WISEPILL DISPENSER




Figure 1. *Wisepill Dispenser Opened*

OPENING THE WISEPILL DISPENSER

Opening the Wisepill Dispenser is as easy as one-two-three!



2

Figure 2. *The Wisepill Dispenser*



Figure 3. *Open the dispenser by pushing the lid forward*

To open the device, hold the **base** with one hand and open the **lid** with the other. With the lid open, you will be able to see half of the pill box which is in the **front bin**. The pills in the front bin that are now easy to get to but the ones in the back bin are not. When you run out of pills in the front bin, you can take the pill box out and turn it so that the available pills are in front.



Figure 4. *Slide the pill box out by pulling on the pill box.*



Figure 5. *Seven compartment Pill box*



Figure 6. *Two compartment Pill Box*

TAKING YOUR MEDICINE

1. Every time the dispenser is opened, the Wisepill device will attempt to send a medication event. You will notice that the green light will flash for about 2 minutes.
2. If the red light comes on after a little while, this indicates that the battery is low. – Go ahead and charge the device (See section on Charging the Wisepill Dispenser).
3. If the green light does not come on or if it goes off after a few seconds, your battery is most likely very low – Go ahead and charge the device (See section on Charging the Wisepill Dispenser).

THE DISPENSER BATTERY

There are three ways to know if your Wisepill Dispenser battery is flat:

- 1.) When the dispenser is opened and the battery is low, the red led will come on after a minute to indicate that the battery is low.
- 2.) The Wisepill System can be configured to send an SMS (text message) to your cell phone if the battery is low.
- 3.) A battery status record is available on the Web application and can be accessed via an internet browser.
- 4.) The Wisepill Dispenser battery should last for at least 3 months if only used once per day.

Note: The dispenser reports its battery voltage to the server every time it is opened. It is reported in milli Volts. Less than 3600 milli volts is regarded as low.

CHARGING THE WISEPILL DISPENSER

- 1.) If the device is plugged into the charger, the red light will come on to indicate the battery is being charged. The green light also flashes while the device is plugged into a charger.
- 2.) When the battery is full, the red light will go off.

Note: The device reports its battery voltage to the server (via GPRS or SMS) every time it is opened. It is reported in milli-Volts. Less than 3700 milli volts is regarded as low.

CARING FOR THE WISEPILL DISPENSER

- 1.) The Wisepill Dispenser is in reality a pill box with a built in cellphone modem. It should therefore be treated as you would treat a regular cell phone.
- 2.) You can clean your Wisepill Dispenser using a damp cloth to wipe it clean. As with a regular cellphone, the dispenser should be kept as dry as possible.