

User Manual for Intelligent Care System

Welcome to choose the intelligent care system of the “Help” smart home series products. This system consists of four parts: a Carer, a mobile app, a wireless network, and a cloud data interaction platform. Please read this manual carefully before using the product.

Target audience for the product: elderly people or those in need of special care

The functions of the care system

1. Users can send help messages to the mobile app through voice commands;
2. The mobile app manually sends reminder messages to the Carer;
3. The mobile app sends medication reminders to the Carer at regular intervals;
4. Area entry abnormal alarm refers to the system automatically issuing an alarm when the person being cared for does not enter the relevant area within the agreed time;
5. The mobile app will automatically save interactive information for future review and processing.

Installation Guide

Please complete the system setup in the following order. **Important reminder: Please keep the product away from sources of fire, heat, water, and gas, and ensure that it will not cause harm to children!**

● Installation of the app

Before installing the mobile app, please enable the location function on your phone, Press and hold the top (or top right) of the screen to scroll down, select Location Services, and click to turn it on.

Install mobile app Using the mobile app store, search for 'Carer', or using the mobile browser, scan the QR code in the manual to install the app. During the installation process, there will be requests for location services and message notification permissions. Please select 'Allow'. Follow the installation instructions to complete the installation.

● Authorized app

1. Authorize notification function

Follow the steps below on your phone: Settings - Apps - App Management - Select Carer- Notifications - Allow Notifications

Some phones need to enable voice permission in the notification permission, otherwise there will be no sound reminder when receiving notifications.

2. Authorize positioning function

Follow the steps below on your phone: Settings - Apps - App Management - Select Carer- Permissions - Location - Allow When Using

3. Authorize battery management function

Follow the steps below on your phone: Settings - Battery - Turn off power-saving mode - Background power management - Select Carer- Allow high power consumption in the background.

● Add the main unit of the Carer

Adding a Carer main unit first ensures that the phone is connected to the home's wireless network and knows the name and password of the wireless network; Turn on the main unit and when you hear the voice prompt "Distribution Network", click the three horizontal buttons in the upper left corner of the app page. Click "Add Main Unit" in the side menu. When "Carer" appears

to connect to the device, click "Connect". After running, the wireless network name will pop up (if you have tried to open the location function multiple times and cannot automatically obtain the wireless network name when entering the add main unit, please manually enter the wireless network name). Please enter your password and click the "OK" button. A window for entering a name will appear later. Please choose a suitable name and confirm. The newly added unit information will appear in the app, and you will hear a prompt sound indicating successful networking, indicating that the addition is complete. Otherwise, please repeat this process. After adding the main unit, your phone should automatically switch back to your local area network. If the switch is not completed, please manually switch back to ensure that your phone is connected to the local area network.

A Carer system can only have one main unit, and medication reminders are also sent through the main unit. Therefore, when there are multiple units, please choose the area where the person being cared for is most frequently active to install the main unit.

- Test the main unit

Clicking on the unit information will enter the "Unit Operation/Alarm History" screen. Here, you can click the "Take A Test" button. If everything is normal, you will receive a message of "The signal channel is unobstructed" later, which will be displayed in the "Alarm History" below. This feature is often used by users to test whether the system is working properly, and regular testing is a good way to ensure that the system is working properly.

- Add the slave unit (optional)

The Carer can cover a range of 5-6m without obstruction or noise. Users can add one or more sub units according to their needs to fully cover the elderly's activity area. Please install the slave unit after installing the main unit. The specific steps are as follows: power on the slave unit, when you hear the voice prompt of "distribution network", click the three horizontal buttons in the upper left corner of the app page, and click "add slave unit" in the side menu. Later, a window for entering a name will appear. Please choose a suitable name. When you hear that the distribution network is successful and the addition is complete, the newly added unit information will appear in the app. Otherwise, please repeat this process.

- Testing the slave Unit

Clicking on the unit information will enter the "Unit Operation/Alarm History" screen. Here, you can click the "Take A Test" button. If everything is normal, you will receive a message of "Signal Channel Smooth" later, which will be displayed in the "Alarm History" below. This feature is often used by users to test whether the system is working properly, and regular testing is a good way to ensure that the system is working properly.

- Placement and fixation of Carer

The installation position of the Carer should be between 0.8m and 1.6m above the ground, with a distance of less than 6m from the person being cared for. The Carer can be fixed to the wall with double-sided tape at the bottom of the Carer bracket, or placed on the desktop, while ensuring that there is no obstruction between it and the person being cared for.

Usage of the Carer

- Ask for help

When the user needs help, simply call out clearly 'Help', and when you hear the response "I'm here, master", please say "come help me". When you hear "master, your needs have been delivered", your help message has been received by your phone. Under normal circumstances, help messages will be sent to the bound mobile app

within 30 seconds. The system also includes common needs such as "I'm thirsty", "I'm hungry", "I need to go to the bathroom", etc., which can also be sent to the phone via voice.

- Response to Help Request

When the app receives a request for help, it can enter the corresponding unit's operation interface by clicking on the main unit or slave unit on the mobile app. Click the "Alarm Confirm" button on this interface to notify the seeker that the help information has been confirmed by the mobile user.

- Volume adjusting

You can first call 'Help', and after receiving a response from 'here, master', say 'increase volume' or 'decrease volume' to complete the volume adjustment. The adjusted volume will remain unchanged even after the monitor is powered off until the next volume adjustment.

App function settings and usage

Medication Reminder

The system provides medication reminder functions for up to 6 time points, with a reminder time error of less than ± 1 minute. In the main interface of the app, click on the three horizontal (Ξ) buttons in the upper left corner, click on "Function Settings", enter the function settings interface, click on the "00:00" style text, modify the reminder time, and swipe the switch on the right side. Sliding to the right indicates that the timer is turned on and the reminder function is effective; sliding to the left indicates that the timer is turned off and the reminder function is invalid.

Alarm notification selection

When the phone receives the "Help" message, do you need to notify the phone owner with the default ringtone or vibration? Users can choose to turn on or off these two options according to their own needs. If both options are turned off, the phone will only send notifications with the notification bar message and the default received message sound. For general needs such as "I'm thirsty", the phone will only send notification messages and will not ring or vibrate, which is not affected by this option. This function can be set in the "Function Settings" interface.

- Region entry exception

Click on each unit in the main interface to enter the unit operation/alarm history interface. Click on the "00:00" style text located at the top of the interface after the query time to modify the alarm time of the non entered area. The use of the slider switch after this time is the same as the medication reminder switch above. Sliding to the right indicates turning on the abnormal alarm; sliding to the left indicates turning off the abnormal alarm.

- The mobile app sends a reminder message to the Carer.

By clicking on the main or slave unit on the mobile app, you can enter the corresponding unit's operation interface. On this interface, you can send a separate message to the corresponding unit, and other units will not receive the message. For example, you can click the "Eat A Meal" button, and only the corresponding Carer will receive a reminder saying "Eat A Meal, Please". Other reminder functions can be operated in the same way.

Jilin Advantech Computer Technology Co., Ltd