

COMMON INSTRUMENT EFX	
VOL	Volume Offset <i>Relative: 01 adds 1; FF subtracts 1</i>
PIT	Pitch <i>Offset in semitones; 80–FF lowers</i>
FIN	Fine Tune <i>–1 to +1 semitone</i>
ERR	Error <i>Randomize pitch and params (not Hypersynth)</i>
SMX	ModFX Send <i>ModFX amount</i>
SDL	Delay Send <i>Delay amount</i>
SRV	Reverb Send <i>Reverb amount</i>
FIL	Filter Type <i>This instrument's filter (global is DJ*)</i>
CUT	Cutoff <i>Filter frequency</i>
RES	Resonance <i>Filter peak</i>
AMP	Amp <i>Gain into the limiter; LIM sets how it clips</i>
LIM	Limiter <i>CLIP, SIN, FOLD, WRAP, POST modes</i>
PAN	Pan <i>00 (left) – 80 (center) – FF (right)</i>

SEQUENCE FLOW	
HOP	Hop <i>Phrase: Y=row of next phrase (FF stops). Table: Y=row, X=times</i>
KIL/OFF	Kill / Note Off <i>XX ticks: KIL cuts, OFF starts ADSR release</i>
INS	Instrument <i>XX: switch to instrument XX</i>
NXT	Next Track <i>XX: instrument (00–7F) on track to the right</i>
RET	Retrigger <i>X: volume (0–7 down, 8–F up), Y: ticks</i>
REP/RTO	Repeat / Ramp <i>Steps the previous FX (80–FF down); RTO stops it</i>
CHA	Chance <i>Phrase: X=left, Y=right (0–F). Table: XX (00–FF)</i>
NTH	Nth Trigger <i>Skip left (X) or right (Y) side by loop count</i>
RND	Random <i>Randomize previous FX; X/Y: digit range (0–F)</i>
RNL	Random Left <i>Randomize the FX to its left; in FX1: note and instrument</i>
RMX	Remix <i>X selects tracks to the left; Y sets phrase row</i>
MTT	Micro Timing <i>Sub-tick shift (1/8 tick); 80–FF = earlier</i>

MACROSYNTH	
OSC	Shape <i>SHAPE model (see the Macrosynth guide)</i>
TBR	Timbre <i>TIMBRE: meaning varies per model</i>
COL	Color <i>COLOR: meaning varies per model</i>
DEG	Degrade <i>Sample rate reduction</i>
RED	Redux <i>Bit depth reduction</i>
TRG	Trigger <i>Re-strike shapes 1C–23 (plucked, bells, kick...)</i>

FM SYNTH	
ALG	Algorithm <i>Operator routing 00–0B; 0B = additive</i>
FM*	Mod 1–4 <i>FM1–FM4: MOD1–4 macro values</i>

WAVSYNTH	
OSC	Shape <i>00–08 basic shapes, 09–45 wavetables</i>
SIZ	Size <i>Waveform length (samples)</i>
MUL	Mult <i>Repeat the shape</i>
WRP	Warp <i>Push shape to one side</i>
SCN	Scan <i>Mirror point / wavetable scan</i>
SNC	Sync <i>Oscillator phase position</i>

HYPERSYNTH	
CRD	Chord <i>Pick one of 16 chord banks</i>
SWM	Swarm <i>Oscillator detune</i>
WID	Width <i>Stereo width</i>
SUB	Sub Oscillator <i>Below 80: –2 octaves · above 80: –1</i>

SAMPLER	
PLY	Play Mode <i>Fwd, rev, loops, ping-pong, OSC, REPITCH</i>
SLI	Slice <i>Cue slice marker XX</i>
STA	Start <i>Sample start position</i>
LOP	Loop Start <i>Loop point</i>
LEN	Length <i>Play length</i>

NOTES & SCALES	
ARP	Arpeggio <i>3–note arpeggio; XY = intervals</i>
ARC	Arp Config <i>X=mode, Y=speed (ticks)</i>
SCA/SCG	Scale <i>X=key, Y=scale; SCG sets all tracks</i>
DEL	Row Delay <i>Delay row by XX ticks</i>
PSL	Pitch Slide <i>Slide time</i>
PBN	Pitch Bend <i>Continuous bend (80–FF down)</i>
PVB	Vibrato <i>X=speed, Y=depth; PVX for extreme</i>

GLOBAL	
TPO	Tempo <i>BPM in hex (78 = 120)</i>
TSP	Global Transpose <i>Semitones, instruments with TRANSP. on</i>
GRV/GGR	Groove <i>Groove number; GGR sets all tracks</i>
SED	Seed <i>Lock random results</i>
DJ*	DJ Filter (global) <i>DJC cutoff (80 = off) · DJR resonance · DJT type</i>

TABLE COMMANDS	
TIC	Table Tick <i>Phrase: table speed from here · in a table: that column only</i>
TBL	Table Select <i>Switch this instrument's table</i>
THO	Table Hop <i>Hop to row 0X (all columns)</i>
TBX	Aux Table <i>Second table alongside the note; TBX 00 stops</i>

MODULATION · 1–4 = MOD SLOT	
EA1–4	Envelope <i>EA1 amount · AT1 attack · HO1 hold · DE1 decay</i>
ET1–4	Envelope Retrigger <i>ET1 with any value above 00 restarts slot 1</i>
LA1–4	LFO <i>LA1 amount · LF1 rate · LT1 retrigger at a phase</i>

TIC MODES · TABLE TIC OR TIC	
00	Next row on each instrument trigger
01–FB	Ticks per row
FC	Octave Map <i>Octave picks the row</i>
FD	Velocity Map <i>Velocity picks the row</i>
FE	Note Map <i>Note picks the row; HOP 00 limits the range</i>
FF	Next row at 200 Hz