

Acme Pharma - EDI Vendor Guidelines

Purchase Order - 850 (004010)

All content fictional. Synthetic fixture in the templated guide layout.

BEG Beginning Segment for Purchase Order Pos: 020 Max: 1

Heading - Mandatory

Loop: N/A Elements: 6

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Transaction Set

Element Summary:

BEG01 353 Transaction Set Purpose Code M ID 2/2 Must use

Description: Code identifying purpose of transaction set

Code List Summary (Total Codes: 65, Included: 1)

Code Name

00 Original

BEG02 92 Purchase Order Type Code M ID 2/2 Must use

Description: Code specifying the type of Purchase Order

Code List Summary (Total Codes: 69, Included: 1)

Code Name

NE New Order

BEG03 324 Purchase Order Number M AN 1/22 Must use

Description: Identifying number for Purchase Order assigned by the orderer

BEG04 328 Release Number O AN 1/30 Not used

BEG05 373 Date M DT 8/8 Must use

Description: Date expressed as CCYYMMDD

Acme Note: This is the date assigned by Acme Pharma to the purchase order.

Example:

BEG*00*NE*PO-2026-0810**20260810

CUR Currency Pos: 040 Max: 1

Heading - Optional

Loop: N/A Elements: 2

User Option (Usage): Used

Element Summary:

CUR01 98 Entity Identifier Code M ID 2/3 Used

CUR02 100 Currency Code M ID 3/3 Used

REF Reference Identification Pos: 050 Max: 1

Heading - Mandatory
Loop: N/A Elements: 2
User Option (Usage): Must use
Purpose: To specify identifying information

Element Summary:

REF01 128 Reference Identification Qualifier M ID 2/3 Must use

Code List Summary (Total Codes: 320, Included: 1)

Code Name

IA Internal Vendor Number

REF02 127 Reference Identification M AN 1/30 Must use

Acme Note: The internal vendor number is required in the heading of every order.

PER Administrative Communications Contact Pos: 060 Max: 3

Heading - Optional

Loop: N/A Elements: 4

User Option (Usage): Used

Element Summary:

PER01 366 Contact Function Code M ID 2/2 Used

PER02 93 Name O AN 1/60 Used

PER03 365 Communication Number Qualifier O ID 2/2 Used

PER04 364 Communication Number O AN 1/80 Used

DTM Date/Time Reference Pos: 150 Max: 10

Heading - Mandatory

Loop: N/A Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

DTM01 374 Date/Time Qualifier M ID 3/3 Must use

Code List Summary (Total Codes: 1112, Included: 1)

Code Name

002 Requested Delivery

DTM02 373 Date M DT 8/8 Must use

Acme Note: The requested delivery date is required on every order.

N1 Name Pos: 310 Max: 1

Heading - Mandatory

Loop: N1 Elements: 4

User Option (Usage): Must use

Element Summary:

N101 98 Entity Identifier Code M ID 2/3 Must use

N102 93 Name 0 AN 1/60 Must use

N103 66 Identification Code Qualifier 0 ID 1/2 Used

N104 67 Identification Code 0 AN 2/80 Used

N3 Address Information Pos: 330 Max: 2

Heading - Optional

Loop: N1 Elements: 2

User Option (Usage): Used

Element Summary:

N301 166 Address Information M AN 1/55 Used

N302 166 Address Information 0 AN 1/55 Used

N4 Geographic Location Pos: 340 Max: 1

Heading - Optional

Loop: N1 Elements: 3

User Option (Usage): Used

Element Summary:

N401 19 City Name 0 AN 2/30 Used

N402 156 State or Province Code 0 ID 2/2 Used

N403 116 Postal Code 0 ID 3/15 Used

P01 Baseline Item Data Pos: 010 Max: 1

Detail - Mandatory

Loop: P01 Elements: 9

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

P0101 350 Assigned Identification 0 AN 1/20 Must use

P0102 330 Quantity Ordered M R 1/15 Must use

P0103 355 Unit or Basis for Measurement Code M ID 2/2 Must use

P0104 212 Unit Price M R 1/17 Must use

P0105 639 Basis of Unit Price Code 0 ID 2/2 Not used

P0106 235 Product/Service ID Qualifier 0 ID 2/2 Must use

Code List Summary (Total Codes: 477, Included: 1)

Code Name
VN Vendor Part Number
P0107 234 Product/Service ID 0 AN 1/48 Must use
P0108 235 Product/Service ID Qualifier 0 ID 2/2 Must use
Code List Summary (Total Codes: 477, Included: 1)
Code Name
UP UPC Consumer Package Code
P0109 234 Product/Service ID 0 AN 1/48 Must use
Acme Note: Every P01 line must carry a UP qualifier pair with the UPC.

PID Product/Item Description Pos: 050 Max: 1
Detail - Optional
Loop: P01 Elements: 5
User Option (Usage): Used

Element Summary:
PID01 349 Item Description Type M ID 1/1 Used
Code List Summary (Total Codes: 3, Included: 1)
Code Name
F Free-form
PID05 352 Description 0 AN 1/80 Used

SAC Service, Promotion, Allowance, or Charge Information Pos: 130 Max: 25
Heading - Optional
Loop: N/A Elements: 5
User Option (Usage): Not used

Element Summary:
SAC01 248 Allowance or Charge Indicator M ID 1/1 Not used
SAC02 1300 Service, Promotion, Allowance, or Charge Code 0 ID 4/4 Not used
SAC05 610 Amount 0 N2 1/15 Not used

CTT Transaction Totals Pos: 010 Max: 1
Summary - Mandatory
Loop: N/A Elements: 2
User Option (Usage): Must use

Element Summary:
CTT01 354 Number of Line Items M N0 1/6 Must use
CTT02 347 Hash Total 0 R 1/10 Must use