

Petrol Blower

Hazards	Who maybe harmed and how?	Control Measures	Action to be taken to control the risk	Who needs to carry out the action?	When is the action needed by?	Done
Shocks and electrocution from improper use of power or accidentally energising other electrical systems. • Carbon monoxide from a generator's exhaust. • Fires from improperly refueling a generator or inappropriately storing the fuel for a generator. • Noise and vibration hazards.						
Manual Handling	All staff, users and observers may suffer sprains or fractures if they trip over debris or slip on spillages. Staff may suffer strains or bruising injuries to their back or elsewhere, from handling heavy/bulky objects.	All staff are trained how to lift properly. Staff are to work within their manual handling capabilities.	Staff to complete manual handling online training and wearing of PPE.	Manager/staff	new employee Work Induction P	
		Trolley available for moving generator and associated paraphenalia.	Staff to use trolley/ramp.	Manager/staff	now	3/8/2023
		Ingress / egress route kept clear.	Staff to recce route on ingress and egress.	staff	dynamic	
		Use of lift (rather than stairs) where possible.	Staff to identify lifts.	staff	dynamic	
		Portable ramp use when removing generator etc in and out of vehicle.	Ramp to be made accessible and part of vehicle SOPs.	staff	now	
		Generator associated paraphenalia to be secured in vehicle using appropriate anchor points and straps.	Anchor points and straps accessible.	Manager/staff	dynamic	
Slips, trips and falls	All staff, users and observers may suffer sprains or fractures if they trip over debris or slip on spillages.	Staff set up generator as per manufacturers specifications in appropriate location with level/firm/hard ground and remove any potential slip/trip/fall hazards within a 5 metre radius. Should be installed appropriate distance from ingress/egress and emergency exits.	Staff and users to keep an eye on the area around the genrator, and immediately clear away any items that present a risk.	Staff	dynamic	
		Staff / Users to 'clean as they go'.	Users are encouraged not to eat or drink whilst using the generator.	Staff/Users	dynamic	
		Any leads should be taped down or routed outside of access routes or area of foot traffic to prevent trips.	A safe and competent user identified to operate generator. Barriers utilised.	Staff/Users	dynamic	
		A barrier to be used to cordon off the genrator from public access.		staff		
		A fire extinguisher to be placed within the barrier location.		staff		
		Generator to be a minimum of 3 metres from the equipment/game.		staff		
		Fuel for the blower to be in approved container and placed within the barrier location.		staff		

		Once generator is installed in location by staff, game must not be moved without authority from FunProUK.		staff	dynamic	
Electrical Safety	All staff, users and observers may get electrical shocks or burns from faulty electrical equipment or on installation. Electrical faults can also lead to fires.	All components are PAT tested annually and manually inspected at time of installation.	ensure electrical equipment is maintained in order.	Manager/staff	Jul-23	
		Staff trained to spot and report any defective plugs, discoloured sockets, damaged cable and on/off switches, and to take any defective equipment out of use and mark up accordingly to prevent subsequent use.	staff to have sufficient knowledge to identify issues with electrical items.	Manager/staff	Jul-23	
		Any cables to be covered and routed away from areas that will have footfall.		staff	dynamic	
		No water to be within 1 metre of the game and power source (sockets).	Brief hirer / users	staff/users	dynamic	
Fire	All staff, users and observers risk of burns.	Ensure generator is turned off when refuelling and use funnel to pour in fuel to avoid spillage, replace fuel cap on contain and generator once fuelled.	Use appropriate fire extinguisher - Petrol is flammable liquid, a Class B fire extinguisher. CO2, Foam or Dry Powder. Spare fuel to be stored in appropriate container - metal (max 20 litres) or plastic (max 10 litres). Store in open air.	staff/users	dynamic	
		No smoking or vaping within 10 metres of the generator.			dynamic	
		All persons to remain away from generator except for authorised persons.			dynamic	
		Any spillage to be identified and absorbent material used to soak up (rather than scrubbing or washing into a bigger area).			dynamic	
		Any malfunction to be reported to a responsible person at the event.			dynamic	
Use of generator and associated paraphernalia.	All staff, users and observers be exposed to injury.	Equipment is supervised by a responsible adult either from the client or by FunProUK on behalf of the client.		Manager/staff	dynamic	
		Participants must follow the operators instructions at all times.	operator instructions made available	staff/client	now	
		Must be operated by an adult.		staff/client	dynamic	
		Public are not to be within the barrier area of the generator.		staff/client		
		Food and drink must not be consumed or in user possession whilst using the generator.	use of barriers around the generator. Members of the public to be a minimum of 5 metres from the generator.	staff	dynamic	
		Overnight or whilst un-attended for long period of time the equipment should be disabled from use.	turn off generator	staff/client	dynamic	
		Only FunProUK equipment to be run off the generator.	not to sit or hold generator.	staff/client	dynamic	
		Authorised persons only to use the generator, exception would be for emergency where deemed necessary to stop generator.	authority granted to individual responsible.	staff/hirer	dynamic	

Allergies and other reactions to fuel.	All staff, users and observers may risk of injury from fuels.	Generator will require refuelling, and PPE must be worn.	Known allergies to be identified, and risk of illness or injury, not to operate the generator. PPE appropriate is deemed as glasses, gloves, protective footwear.	staff	dynamic	
Weather	All staff, users and observers - carbon monoxide	Petrol Blower NOT to be used indoors.	Use in well ventilated areas and away from immediate vicinity of buildings.	staff	dynamic	
Vibration	All staff, users and observers - fatigue - vibration injuries/sensory nerve damage and other injuries.	Not to touch blower for prolonged periods.	not to sit or hold generator.	staff	dynamic	
Noise	All staff, users and observers - fatigue - hearing loss.	Position blower away from areas where persons are gathered.	Where hearing protection if not possible	staff/users	dynamic	
Criminal Activities (Security) or unsupervised use.	All staff, users and observers may suffer harm/injury due to equipment being tampered.	If possible the equipment should not be left unattended whilst area is open to guests/public. If it is necessary to leave the equipment unattended at any time it is disabled to prevent unsupervised use.	powerdown	staff/hirer	dynamic	

Risk Assessment completed by: Lucy Sewell							Date: 05/01/2026
Print:							
Sign:							