# ضروری ہدایات برائے اِنسٹالر حضرات

## بیٹری کنکشن:

بیٹری کنکشن کرتے وقت پوزیٹیو (Postitive) اُور نیگیٹیو (Negative) کے صحیح کنکشن کا خاص خیال رکھیں۔ بیٹری کے کنکشن غلط لگنے کی صورت میں MPPT کنٹرولر کو نقصان پہنچ سکتا ہے۔

اِس بات کو ممکن بنائیں کہ MPPT کنٹرولر سے بیٹری تک جانے والی تاروں کی لمبائی کو کم سے کم رکھا جائے۔

اس بات کا خاص خیال رکھیں کہ MPPT کنٹرولر کے بیٹری کنکشن ٹیرمینلر (Terminals) میں بیٹری سے آنے والے تار (Wire) مضبوطی سے لگے ہوں اور کسی قسم کی لوزِنگ (Loosing) نہ ہو۔ کنکشن میں لوزِنگ (Loosing) کی صورت میں ایمپیئر (Ampere) ضائع ہونے، اُور ہیٹنگ (Over-Heating) اور آگ لگنے کے اِمکانات ہوسکتے ہیں۔

بیٹری کنکشن کے لئے تار کی موٹائی لوڈ کے حساب سے ہونی چاہیے۔ صحیح تار کے انتخاب کے لئے مندرجہ ذیل چارٹ کا استعمال کریں۔

| | |
|---|---|
| 10 AMP - 20 AMP | 4 MM - 6 MM |
| 20 AMP - 35 AMP | 6 MM - 10 MM |
| 35 AMP - 50 AMP | 10 MM - 16 MM |
| 50 AMP - 65 AMP | 16 MM - 25 MM |
| 65 AMP - 100 AMP | 25 MM |



## 415W – 460W SOLAR PANELS ARRANGEMENT FOR MPPT

| No. OF PANELS | MODEL #: EXO-M-70 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | 3-IN SERIES 1 GROUP | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | 3-IN SERIES 2 GROUP |
| 9 | - | - |

| No. OF PANELS | MODEL #: EXO-M-100 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | 3-IN SERIES 1 GROUP | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | 3-IN SERIES 2 GROUP |
| 9 | - | - |

## 525W – 550W SOLAR PANELS ARRANGEMENT FOR MPPT

| No. OF PANELS | MODEL #: EXO-M-70 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | 3-IN SERIES 1 GROUP | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | 3-IN SERIES 2 GROUP |

| No. OF PANELS | MODEL #: EXO-M-100 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | 3-IN SERIES 1 GROUP | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | 3-IN SERIES 2 GROUP |

## 640W – 660W SOLAR PANELS ARRANGEMENT FOR MPPT

| No. OF PANELS | MODEL #: EXO-M-70 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | - | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | - |

| No. OF PANELS | MODEL #: EXO-M-100 | |
|---|---|---|
| | 12V MAX. 1500W | 24V MAX. 3000W |
| 1 | 1 DIRECT | - |
| 2 | 2-IN SERIES 1 GROUP | 2-IN SERIES 1 GROUP |
| 3 | - | 3-IN SERIES 1 GROUP |
| 4 | - | 2-IN SERIES 2 GROUP |
| 6 | - | - |