

MSXPi Quick Start Guide

Note: The documents in the MSXPi/documents folder are still referencing MSXPi features and commands from version 1.3 and earlier. The current release v1.4 greatly differ from previous versions, therefore many of the documents are outdated.

Changes to P commands in Version 1.4

The multiple P<function> commands were replaced by a single “p” <command> executable in the MSX-DOS. To see the list of commands available, type “p” without any parameters, or “p /help”. In this version, commands such as “prun” became “p run”, “pcd” became “p cd”, and so on.

*This section covers the actual **MSXPi hardware interface configuration**. For MSXPi setup under **openMSX emulator**, refer to **/MSXPi/software/openMSX/Contrib/README.MSXPi**.*

1. MSXPi Setup – Download the SD Card image with MSXPi server components installed and configured, and write it to a SD Card. Insert the SD Card in the Raspberry Pi and boot. The SD Card image link is:

<https://tinyurl.com/MSXPi-SDCardV3>

2. If Wi-Fi is not yet configured in the Raspberry Pi, configure from MSX-DOS:

```
p set WIFISSID Your Wifi Name
```

```
p set WIFIPWD YourWifiPassword
```

```
p wifi set
```

```
p reboot
```

2. Copy all MSXPi commands from <https://github.com/costarc/MSXPi/tree/master/software/target> to your MSX SD Card.

3. When needed, update the MSXPi components. The server-side components can be updated using these commands:

```
p run wget https://tinyurl.com/MSXPi-Setup
```

```
p run chmod 755 MSXPi-Setup
```

```
p run sudo ./MSXPi-Setup
```

This may take a long time, be patient. For the MSXPi PCB v1.2.1b and newer, the LED will turn on when Raspberry Pi completes the update and is ready to go.

Some Usage Tips – Read the Manual for more.

To disable MSXPi BIOS (in the EEPROM), remove the SLTSL/Enable jumper.

To switch the 16KB EEPROM bank, move the jumper from A15/Bank 2 to A14/Bank 1. Bank 1 contains the MSX-DOS1, and bank 2 contains a game.

You can replace the ROMS in the EEPROM at any time using the provided software
AT28C256.COM.

If you want to contribute to the project, contact the author in the MSXPi group on Facebook.