AnyCam 3.9.0-rc1.0 Audit Report

Release audit - 24 October 2026 - 16 items - tag 3.9.0-rc1.0 (local)

A release candidate with the scope CrystalHeeler confirmed on 2026-10-24: B68 and B69 from 3.8.4 (never published on its own) and every Ready ticket: B79, B72, B70, B74, B71, B73, B81, B78, B80, C31, B58, B63, B62 and C30. The recording work follows the review of CrystalHeeler's recordings (docs/Recording_Review_2026-10-24.md).

C30: the headlight pause

Part	3.9.0-rc1.0
Start	One comparison (each picture against the one 1 s older): 0.5% or more of the picture changed, 90% or more of the changed cells brighter by +25 grey levels or more on average, the changed cells at most 35% of the box around them (a lit lawn is scattered, a person is solid), and the 1.5 s before quiet (nothing over 1.5% unless it was itself a scattered brightening).
During	No recording starts; the slow-movement check drops its older pictures; the calibration log gives the reason "a passing light".
End	Two quiet comparisons (under 0.3%), or 4 s; a darker-only change within 3 s after continues it, at most 6 s in all; the camera turning from infrared to colour ends it (a light switched on: the porch light).
Pre-roll	A recording that starts within 1.5 s after a pause starts at the pause's beginning less the 3 s pre-roll; the recording buffer keeps 10 s instead of 3 s (about 10 MB at 8 Mbit/s per armed camera).
Evidence	The add-on's own functions replayed on 334 recordings of 2026-10-20 to 24: 73 of 113 night recordings paused at their trigger (headlights, cars on the street, the day-to-night switch); by day 4 of 221 (a dusk headlight, a cloud, two porch lights ended by the colour switch). The cat, the man, the boy, the insect and the IR-switch clip start no pause.
Changed during the build	The test suite's bright solid block (a person) started a pause; the 35% box limit was added (checked on the 334 recordings: 2 small, solid street lights lost, 71 kept). A solid bright shape no longer counts as a light growing.

The other items

Item	Change
B79	Start-up keeps every runtime.json entry; only the version changes (the card order was dropped at every start).
B70	Per-check zone, picture and slow-movement lines: DEBUG, at a movement's start, then at most every 5 s; the once-a-minute zone line at INFO only when a zone saw movement. DEBUG alone was not enough: log_debug is on by default.
B72	Two decimals when peak and threshold round alike; a WebRTC set-up close is DEBUG ("set up; WebRTC plays on"); a pre-warm failure names its error type.

Item	Change
B71	LIVE-DIAG: global addresses become public: (Python ipaddress is_global); private, VPN and link-local stay. A bug found by the test: addresses followed by a comma were not masked; fixed before release.
B73, B78	The slow-movement check drops its references at a light change, and never uses a picture within 0.6 s of one the fast checks rejected as an insect.
B74	A slow-movement start gets its calibration line: "recorded (slow movement, over 5 s) → file".
C31	Every zone that passed during a recording, in order, in recording_zones.json, the Storage tab (ellipsis, full list on hover) and the "recording stopped" line.
B80	After 3 failures through go2rtc: direct, then go2rtc's copy again once the pre-warm pass saw new bytes, waiting 1, 2, 4, then 10 min; a running picture loop switches back.
B58	When main and sub differ in one number and the brand table lists the next path, password entry checks it with one paced request.
B63	The brand matcher reads the RTSP server name; the scan's ONVIF request and RTSP check take turns 5 s apart.
B81, B62	A card player does not connect while Enhanced View is open (VideoRTC's own restarts included); 20 s after playing, one LIVE-PLAY report per camera and place every 5 min (WebRTC inbound-rtp numbers, or MSE quality and lag).
B68, B69	From 3.8.4: dialog parts keep their height; a drag out of a dialog does not close it.

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates; 58 contracts, new ones for C30, B71 and B79, the pre-roll contract updated.
Python integration	**PASS**	798 of 798; new section AU (25 checks); AE3 and M1 updated for B70 and the 10 s buffer.
JavaScript behaviour	**PASS**	217 of 217; B81, B62 and C31 checks.
Recording replay	**PASS**	C30 through the add-on's code on 334 recordings.
Visual (rule 10)	**PASS**	The Storage tab's zone list at 1366x768 and 812x375: inside the name column, ellipsis, full list on hover. At 375x812 the name column is 0 px, the known C23 fault.
Field	**NOTED**	Not run yet: an rc for field testing.

Not tested

- **C30 live.** The replay used recorded files (OpenCV decoding, 7 pictures a second); the add-on decodes the live sub-stream with ffmpeg. A night of field use is the test.
- **B80's switch back** on a real fall-back; B58 on a camera with a third stream; B63's 5 s spacing on the Microseven's scan.

- **B81 and the LIVE-PLAY report** in the HA app on the phone.
- **The 10 s buffer's memory** on the Pi with several armed cameras.

Best-practices compliance

Standard	Check applied	Result	Note
Rule 2	Logs before code	**PASS**	Every item came from field logs or videos.
6 Security	Validate at the boundary	**PASS**	LIVE-PLAY takes numbers only; public addresses masked.
P4 Async	No blocking I/O on the loop	**PASS**	recording_zones.json written in a thread.
Rule 10	Overlays fit	**PASS**	Zone label capped with an ellipsis.
Rule 9 (privacy)	New text	**PASS**	Made-up and documentation addresses in tests.

Files changed

File	Change
anycam_motion.py	C30, B70, B72, B73, B74, B78, C31; the 10 s buffer.
anycam_go2rtc.py	B71, B72, B80, the LIVE-PLAY line.
anycam_snap.py	B80's switch back.
anycam_credentials.py, anycam_brand.py, anycam_scan.py	B58, B63.
camera_discovery.py	B79; 3.9.0-rc1.0.
page_script.py, anycam_page.py	B81, B62, C31.
verify_release.py, tests/	Contracts; section AU, page checks.
CHANGELOG.md, config.yaml, docs	3.9.0-rc1.0 (3.8.4 folded in); build plan; recording review.