

#	GProhibited					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
WN.Z1	WN (R)	AP+AC	None	0.0		
WN.Z2	WN (C)	AP+AR	None	0.0		
CO.Z1	CO	AA+GC+GR	None	0.0		
CO.Z3	CO	M1	None	0.0		
V1.Z1	V1	M1	None	0.0		
V1.Z2	V1	M2	None	0.0		
#	WN-AC/AR related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
WN.W1	WN		Wmin	8.0		ER0001
WN.S1	WN	WN	Smin	12.0		ER0104
WN.S2	WN	WN (R)	Smin	9.5		ER0128
WN.S3	WN	WN (C)	Smin	12.0		ER0130
WN.S4	WN (R)	WN (C)	Smin	9.5		ER0132
WN.S5	WN (R)	WN (R)	Smin	8.0		ER0122
WN.S6	WN (C)	WN (C)	Smin	12.0		ER0129
WN.AP	WN	AP	Smin	5.0		ERWLMN01
WN.AN	WN	AN	Smin	10.0		ERWLMN03
AR.S1	AR	AR	Smin	4.0		ERWLRR03
AR.WR	AR	WN (R)	Emin	10.0		ERWLRR02
AN.WR	AN	WN (R)	Emin	5.0		ERWLRR01
AR.AN	AR	AN	Smin	4.0		ERWLRR04
AC.W1	AC		Wmin/max	28.5	120.0	Table I-2-1
AC.S1	AC	AC	Smin	???	???	
AC.WC	AC	WN (C)	Emin	???	???	
AN.WC	AN	WN (C)	Emin	3.0		ERCSIO04
AC.AN	AC	AN	Smin	2.8		ERCSIO11
AC.GC	AC	GC	Emin	1.4		ERCSIO13
AC.R1	AC	AN (C)	Donut	0.0		
#	AP/AN/DP/DN related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
AP.W1	AP		Wmin	1.4		ER0004
AP.S1	AP	AP	Smin	1.4		ER0028
AP.AN	AP	AN	Smin	2.8		ERWLMP04
AP.WM	PMOS	AP-GC	Wmin/max	3.4	60.0	Table I-2-1
AP.LM	PMOS	GC-AN	Lmin/max	1.0	30.0	Table I-2-1
AP.WN	AP	WN	Emin	7.0		ERWLMP02
DP.W1	DP		Wmin	2.8		
DP.S1	DP	DP	Smin	???	???	???
DP.AP	DP	AP	Smin	2.8		ERWLMP08
DP.AN	DP	AN	Smin	2.8		ERWLMP09
AN.W1	AN		Wmin	1.4		ER0004
AN.S1	AN	AN	Smin	1.4		ER0028
AN.AP	AN	AP	Smin	2.8		ERWLMN05
AN.WM	NMOS	AN-GC	Wmin/max	3.4	60.0	Table I-2-1
AN.LM	NMOS	GC-AN	Lmin/max	1.0	30.0	Table I-2-1
AN.WN	AN	WN (M)	Emin	5.0		ERWLMP03
DN.W1	DN		Wmin	2.8		
DN.S1	DN	DN	Smin	???	???	???
DN.AP	DN	AP	Smin	2.8		ERWLMN10
DN.AN	DN	AN	Smin	2.8		ERWLMN11
#	PC/CO related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
GC.W1	GC		Wmin	1.0	30.0	ER0014
GC.S1	GC	GC	Smin	1.2		ER0038
GC.AP	GC	AP	Smin	0.4		ERWLMP07
GC.AN	GC	AN	Smin	0.4		ERWLMN09
GC.EP	PMOS	GC	ECmin	1.2		ERMP06
GC.EN	NMOS	GC	ECmin	1.2		ERMN06
CO.W1	CO		Wmin	1.0		ER0020
CO.S1	CO	CO	Smin	1.0		ER0044
CO.WD	CO (D)		Wfix	1.2		ERDP05/ERDN05
CO.AD	CO (D)	AP+AN	Emin	1.2		ERDP24/ERDN23
CO.AP	CO	AP	Emin	0.8		ERMP10
CO.AN	CO	AN	Emin	0.8		ERMN11
CO.PG	CO	GC (G)	Smin	1.0		ERMP12/ERMN12
CO.GC	CO	GC	Emin	0.8		ER0050
#	AR/GR related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
AR.W1	RR	RR (L)	Wmin/max	2.8	20.0	Table I-2-1
AR.L1	RR	RR (W)	Lmin/max	13.0	100.0	Table I-2-1
AR.GC	GC	AR	Smin	1.0		ERRR15
AR.PW	GC (AR)		Wmin	2.0		ERRR06
AR.XY	AR	Bevel	XYmin	1.0		
GC.AN	GC (AR)	AN	Smin	???	???	
GC.R1	AR	GC (AR)	Donut	0.0		
GC.R2	GC	TieDown		0.0		
GR.W1	RS	RS (L)	Wmin/max	4.0	20.0	Table I-2-1
GR.L1	RS	RS (W)	Lmin/max	20.0	100.0	Table I-2-1

Function:

Wmin/max: L1 Width min/max
 Smin/max: L1 Space min/max (L1=L2)
 Smin/max: L1 Separate L2 min/max
 Emin/max: L1 Enclosed L2 min/max
 Fmin/max: L1 Enclosing L2 min/max
 ECmin: MOS Endcap min
 Wfix: L1 Windth equal
 Sfix: Space equal
 Donut: L1 Souounded by L2
 None: Not Exist

GR.S1	RS	RS	Smin	2.0		ERRS04
CR.W1	CO(RR)		Wmin	1.0		
CR.W2	CL(RR)		Wmin/max	1.0	97.5	CO(L)
CR.AT	CO(RR)	AR(T)	Emin	1.5		
CR.AS	CO(RR)	AR(S)	Emin	1.0		
CC.W1	CO(C)		Wmin	1.2		ERCSIO01
CC.S1	CO(C)	CO(C)	Smin	1.2		ERCSIO14
CC.AC	CO(C)	AC	Emin	2.9		ERCSIO03
CC.AN	CO(C)	AN	Emin	1.2		ERCSIO02
#	BEOL related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
M1.W1	M1		Wmin	1.8		ER0021
M1.S1	M1	M1	Smin	1.4		ER0045
M1.SC	M1(C)	M1(C)	Smin	10.0		ERCSIO05
M1.CO	M1	CO(S)	Fmin	0.8		ER0051
M1.CC	M1	CO(C)	Fmin	1.2		ERCSIO02
M1.CL	M1	CO(L)	Fmin	1.2		ER1305
M1.SW	M1(W)	M1	Smin	2.0		ER1402
V1.W1	V1		Wfix	1.4		ER0022
V1.S1	V1	V1	Smin	1.5		ER0046
V1.M1	V1	M1	Emin	1.0		ER0052
V1.GC	V1	GC	Smin	1.2		ER1508
V1.CO	V1	CO	Smin	1.0		ER1506
V1.CL	V1	CO(L)	Smin	1.4		ER1507
M2.W1	M2		Wmin	3.0		ER0023
M2.S1	M2	M2	Smin	2.0		ER0047
M2.V1	M2	V1	Fmin	1.0		ER0052
#	ESD related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
APE.WM	PMOS	AP-GC	Wmin/max	11.0	60.0	Table I-2-1
APE.LM	PMOS	GC-AN	Lmin/max	2.0	30.0	Table I-2-1
APE.AN	APE	AN	Smin	10.0		ERWLMPE15
APE.XY	APE	Bevel	XYmin	1.4		ERMPE06
APE.CO	APE	CO	Smin	2.0		ERWLMPE16
ANE.WM	NMOS	AN-GC	Wmin/max	11.0	60.0	Table I-2-1
ANE.LM	NMOS	GC-AN	Lmin/max	2.0	30.0	Table I-2-1
ANE.AP	ANE	AP	Smin	10.0		ERWLMN14
ANE.XY	ANE	Bevel	XYmin	1.4		ERMNE15
ANE.CO	ANE	CO	Smin	2.0		ERWLMN15
COE.W1	CO(E)		Wfix	3.0		ERMPE12/ERMNE13
COE.S1	CO(E)		Smin	1.6		ERMPE13/ERMNE15
CDE.GC	CD(E)	GC	Smin	7.0		ERMPE04/ERMNE08
CSE.GC	CS(E)	GC	Smin	3.0		ERMPE03/ERMNE09
COE.AP	CO(E)	AP	Emin	4.0		ERMPE05/ERMPE31
COE.AN	CO(E)	AN	Emin	4.0		ERMNE10/ERMNE32
#	PAD related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
PO.W1	PO		Wmin	70.0		ER1809
PO.S1	PO		Smin	64.0		ER1810
M2.PO	M2(P)	PO	Fmin	5.0		ER1703
M1.PO	M1(P)	PO	Fmin	5.0		ER1704
PO.V1	PO	V1	Emin	10.0		ER1811/ER1703
PO.AP	PO	AP	Smin	14.0		ER1808
PO.AN	PO	AN	Smin	14.0		ER1808
PO.GC	PO	GC	Smin	14.0		ER1807
PO.M1	PO	M1	Smin	14.0		ER1801
PO.M2	PO	M2	Smin	14.0		ER1802
M2.PE	M2	Extention		19.0		ER1803
M2.PW	M2	Extention	Wmin	40.0		ER1803
M1.PE	M2	Extention		19.0		ER1804
M1.PW	M2	Extention	Wmin	40.0		ER1804