

Heads Carolina, Tails California -- Jo Dee Messina

I'm Alright, 1996. ~118 BPM, est.

Bright, bouncy 90s country-pop -- road-trip energy, no edge to the tone anywhere. The bass just needs to sit clean and punchy under the groove, not compete for attention.

GP-5 only, P/J bass, no pedalboard.

Module chain

NR -- Gate, always on.

THRE: 25. Light touch -- just keeping the noise floor down between notes, nothing aggressive needed on a clean amp.

PRE -- Micro Boost, on CTL.

Gain: 45 when engaged.

Off for the verse, on for the chorus -- same clean tone throughout, just pushed a little harder and brighter for the hook.

DST -- off. No drive anywhere in this one -- the whole point is a clean, bright country-pop bass.

AMP/CAB -- NAM SnapTone, slot 51: CleanB15 (always on)

- Built from the `Ampeg B18 - Head DI - Bass Chan - Vol 2.5 (B-18N)` NAM and the Apg115 IR, combined into one snaptone.
- Real Ampeg B-18N flitop (the B-15 preamp circuit), captured clean at volume 2.5, into the Apg115 B-15 cab IR.
- Mid-90s country radio bass: clean, round, locked to the kick. Clean B-15 is the right voice.
- Gain: 60, VOL: 80, Bass: 55, Middle: 55, Treble: 65
- Gain 60: noticeably over default. This part wants more push than the other CleanB15 patches.
- Bass 55: a touch more low end.
- Middle 55: a touch more midrange.
- Treble 65: more top end.
- VOL 80: the level Michael set for this snaptone in the 2026-10-02 VOL audit. Trim here if the patch jumps in level against your others.
- Same in both CTL states. AMP and CAB are off in the `.prst`, so nothing stacks on the capture. The N->S block calls slot 51 directly.

EQ -- Bass EQ 2, always on.

50Hz: +2, 120Hz: +3, 400Hz: -3, 800Hz: 0, 4.5kHz: +6, VOL: 55.

Small low-end support, a light cut around 400Hz to avoid boxiness, and a real push at 4.5kHz for that bright, present pick attack the genre wants.

MOD -- off. No modulation -- straightforward part, no need to color it.

DLY -- off. Dry and direct.

RVB -- Room, on CTL.

Mix: 20, Decay: 35, Trail: true.

Off for the verse -- tight and dry. On for the chorus alongside the boost, giving the hook a touch more air without washing out the groove.

CTL footswitch

Two modules on CTL: PRE (Micro Boost) and RVB (Room).

- **CTL off** -- verse groove. Dry, tight, clean. Resting state the patch loads into.
- **CTL on** -- chorus lift. Brighter push plus a touch of room reverb, same amp tone, bigger for the hook.

Engage CTL going into each chorus, back off for the verses -- same two-state approach as the rest of this batch.