

Rainbow Connection -- Kenny Loggins

Kenny Loggins' version, from *Return to Pooh Corner* (1994). About 72 BPM, est.

Bass: Harley Benton P/J, 5-string, passive. GP-5 only.

Soft lullaby arrangement. The bass should feel like a gentle acoustic or upright underpinning: round, short, warm.

Roots and gentle walk-ups.

Thumb or soft fingers over the neck. P pickup soloed. Tone knob around 30%.

Module chain

NR -- Gate, always on.

THRE: 8.

Minimal.

PRE -- COMP (Ross), always on.

Sustain: 32, VOL: 58.

Gentle leveling.

DST -- off. No grit.

AMP/CAB -- NAM SnapTone, slot 51: CleanB15 (always on)

- Built from the `Ampeg B18 - Head DI - Bass Chan - Vol 2.5 (B-18N)` NAM and the Apg115 IR, combined into one snaptone.
- Real Ampeg B-18N fliptop (the B-15 preamp circuit), captured clean at volume 2.5, into the Apg115 B-15 cab IR.
- Gentle, acoustic-led arrangement. The clean B-15 stays soft and round.
- Gain: 47, VOL: 80, Bass: 58, Middle: 50, Treble: 30
- Gain 47: a little under default. This part wants less push than the other CleanB15 patches.
- Bass 58: more low end.
- Middle 50: flat.
- Treble 30: top end pulled back noticeably.
- VOL 80: the level Michael set for this snaptone in the 2026-10-02 VOL audit. Trim here if the patch jumps in level against your others.
- Same in both CTL states. AMP and CAB are off in the `.prst`, so nothing stacks on the capture. The N->S block calls slot 51 directly.

EQ -- Bass EQ 2, always on.

50Hz: 0, 120Hz: +2, 400Hz: +1, 800Hz: -1, 4.5kHz: -5, VOL: 52.

Woody 400Hz, dark top. It sounds acoustic, not electric.

MOD -- off.

DLY -- off.

RVB -- Hall, on CTL.

Mix: 14, Decay: 40, Trail: on.

A touch of hall for the dreamy choruses.

CTL footswitch

On CTL: RVB (Hall).

- **CTL off** -- Verses. Soft, dry, woody. This is the resting state the patch loads into.
- **CTL on** -- Choruses. The hall joins the bass to the dreamy wash.

Engage at the choruses.