

Giving It All to You -- Michael Gungor

Bass: Harley Benton P/J, 5-string, passive. Full board.

Part of a 5-song worship set. The board ahead of the GP-5 is fixed across all 5 songs -- see "Full Pedalboard" below. Only this GP-5 patch changes song to song.

Early Michael Gungor Band -- organic, indie-folk worship, warm and a little lo-fi, nothing hi-fi or aggressive about it. 100 BPM in C, mid-tempo and steady. This is a one-sound patch: the part sits in a supportive pocket the whole song, so there's no CTL split here -- just a warm, rounded tone that stays out of the vocal's way.

GP-5 Settings

Module order: NR -> PRE -> DST -> AMP -> CAB -> EQ -> MOD -> DLY -> RVB

NR -- Gate

- THRE: 20
- Always on. Light gate -- low-gain patch, barely needs it, just cleans up idle noise.

PRE -- COMP (Ross Compressor)

- Sustain: 45, VOL: 55
- Always on. Gentle glue and sustain for a fingerstyle folk part -- not squashing anything, just evening it out.

DST -- Off

Not used. No drive anywhere in this tone.

AMP -- Mess Bass (Mesa/Boogie Bass 400+)

- Gain: 35, VOL: 62, Bass: 55, Middle: 50, Treble: 50
- Always on. Low gain, flat-ish EQ -- warm and rounded rather than hi-fi or scooped. Matches the organic, unforced character of early Gungor Band recordings.

CAB -- AMPG 4x10 (Ampeg SVT-410HE)

- VOL: 55
- Always on.

EQ -- Bass EQ 1

- 33Hz: +4, 150Hz: +2, 600Hz: 0, 2kHz: -2, 8kHz: -3, VOL: 52
- Always on. Small low-end lift for foundation, top end rolled back slightly so it stays warm instead of glassy -- no aggressive presence boost here.

MOD -- A-Chorus (Arion SCH-1)

- Depth: 15, Rate: 0.5Hz, Tone: 40
- Always on. Very light touch, per the usual rule -- this isn't a drenched chorus tone, just enough shimmer underneath to give the part that organic, slightly wobbly indie-folk character instead of a dead-flat DI tone.

DLY -- Off

Not used.

RVB -- Room

- Mix: 12, Decay: 30, Trail: On
- Always on. Just a whisper of space -- keeps the tone from feeling too dry and dead in an intimate arrangement, without turning it into a wash.

No CTL on this patch -- one steady, supportive tone for the whole song.

Full Pedalboard -- Fixed For This Set

This patch is one of 5 built for one worship set (Unstoppable God, Giving It All to You, Your Love Changes Everything, The Bread Has Been Broken, Thrive). Every pedal ahead of the GP-5 is dialed in once and left untouched for the whole set -- only the GP-5 patch changes between songs. Don't touch these knobs between songs; that's the point.

1. Flamma FS-08 Octave -- Bypassed, entire set.

All four octave knobs at 0, Dry at 100, so nothing surprises you if the footswitch gets bumped. None of these five songs call for octave layering.

2. Donner Ultimate Comp -- Engaged, entire set.

- COMP: 42
- TONE: 50
- LEVEL: 55
- Mode: NORMAL

First in the chain -- evens out finger-attack dynamics before anything else touches the signal. Moderate COMP glues the sound together across a set that spans near-silence (Bread) to full push (Unstoppable God, Thrive) without squashing quiet sections. NORMAL mode stays neutral -- voicing is handled per-song downstream.

3. Donner Stylish Fuzz -- Bypassed, entire set.

No fuzz texture anywhere in this set. True bypass throughout.

4. Joyo Tidal Wave -- Engaged, entire set.

- Drive: 25
- Blend: 35
- Presence: 55
- Level: 55
- Treble: 55, Middle: 58, Bass: 55
- Mid-Frequency toggle: 500Hz
- Bass-Shift toggle: 80Hz (tight, keeps a full band mix from turning to mud)
- Cab-Sim (DI out): On
- Ground Lift: Off (only flip on if a specific room throws hum)

The constant foundation stage for the whole set. Drive is low and Blend under half -- this adds harmonic warmth and preamp glue, not an audible overdrive. Also feeds a consistent DI signal to FOH all night, cab-sim engaged. Actual tone character per song comes from the GP-5 patch downstream, not from this pedal.

5. Joyo Narcissus -- Bypassed, entire set.

Modulation is handled per-song by each GP-5 patch's own MOD module instead (this song: A-Chorus, light, always on). Stacking this pedal on top would fight with that. True bypass throughout.

6. Valeton GP-5 -- as detailed above.

Footswitch Choreography

None needed for this song. GP-5 loads its one patch state and stays there -- no CTL, no changes on the rest of the board.