Run the Radar on a New Laptop

5 steps - about 30 minutes - internet needed once

1	**Download** the project: **github.com/dani1560/SDR_Doppler_Radar_Pluto** → Code → Download ZIP → unzip it.
2	**Install Python** from python.org. On the first screen tick **Add python.exe to PATH**.
3	**Install the Pluto driver** (Pluto unplugged): open the `SDR_Radar_Deploy` folder, double-click `TOOLS.bat`, press **6**, click **Yes** to everything, then press **0**.
4	**Install GNU Radio:** download **radioconda** for Windows from github.com/radioconda/radioconda-installer/releases and install it. **Untick** Add to PATH.
5	**Plug in** the Pluto (**middle** USB port) and the Arduino, wait 30 s, then double-click `START_GNURADIO.bat`.

Done. Stand still for 3 seconds, then move straight towards the antennas. Close the window to stop.

If something does not work

Problem	Fix
Pluto not found	Use the middle USB port, wait 30 s, close any other radar window
Arduino not found	Install the CH340 driver (wch-ic.com) or try another USB cable
Nothing detected	Move closer and straight towards the antennas; set the Min signal slider to 12