

Sixth-order DIN A weighting filter

- Voltage-controlled voltage source
- Gain normalized at 1 kHz
- Noise-free

A1
 .subckt DIN_A outP outN inP inN

A2
 .param a_0=1

A5
 .param a_3=1.08260399772761e-7

A6
 .param a_4=2.18072514015132e-11

A3
 .param a_1=0.0171714881392805

A7
 .param a_5=5.14693104782210e-16

A4
 .param a_2=8.66240986229945e-5

A8
 .param a_6=3.24101285871316e-21

A9
 .param b_0=0 b_1=0 b_2=0 b_3=0 b_4=2.39511182980200e-11 b_5=0 b_6=0

